Temperature Controller Driver

1	System Configuration	
2	Selection of External Device	
3	Example of Communication Setting	11
4	Setup Items	
5	Cable Diagram	94
6	Supported Device	
7	Device Code and Address Code	
8	Error Messages	

Introduction

This manual describes how to connect the Display and the External Device (target PLC).

In this manual, the connection procedure will be described by following the below sections:

1	System Configuration This section shows the types of External Devices which can be connected and SIO type.	"1 System Configuration" (page 3)
2	Selection of External Device Select a model (series) of the External Device to be connected and connection method.	"2 Selection of External Device" (page 10)
3	Example of Communication Settings This section shows setting examples for communicating between the Display and the External Device.	"3 Example of Communication Setting" (page 11)
4	Setup Items This section describes communication setup items on the Display. Set communication settings of the Display with GP-Pro Ex or in off-line mode.	^{ভেল} "4 Setup Items" (page 89)
5	Cable Diagram This section shows cables and adapters for connecting the Display and the External Device.	ি "5 Cable Diagram" (page 94)
	Operation	

1 System Configuration

The system configuration in the case when the External Device of RKC INSTRUMENT INC. and the Display are connected is shown.

Series	CPU ^{*1}	Link I/F	SIO Type	Setting Example	Cable Diagram
СВ	CB1000000000000000000000000000000000000	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 1 (page 11)	Cable Diagram 1 (page 94)
	FB900-□□-□*□□1/□□-□□□□ FB400-□□-□*□□01/□□-□□□□	Terminal Block on the controller. (Communication 1)	RS232C	Setting Example 2 (page 13)	Cable Diagram 2 (page 99)
	FB900-□□-□*□□□4/□□-□□□□ FB400-□□-□*□□□4/□□-□□□□	Terminal Block on the controller. (Communication 1)	RS422/485 (4 wire)	Setting Example 3 (page 15)	Cable Diagram 10 (page 133)
	FB900-□□-□*□□5/□□-□□□□ FB400-□□-□*□□5/□□-□□□□	Terminal Block on the controller. (Communication 1)			
FB ^{*2}	FB900-□□-□*□□□Y/□□-□□□□ FB400-□□-□*□□□Y/□□-□□□□	Terminal Block on the controller. (Communication 2)	RS422/485 (2 wire)	Setting Example 4 (page 17)	Cable Diagram 1 (page 94)
	FB900-□□-□*□□□X/□□-□□□□ FB400-□□-□*□□□X/□□-□□□□	Terminal Block on the controller. (Communication 1)			
	FB900-00-0*00W/00-000	Terminal Block on the controller. (Communication 1)	RS232C	Setting Example 2 (page 13)	Cable Diagram 2 (page 99)
	FB400-□□-□*□□□W/□□-□□□□	Terminal Block on the controller. (Communication 2)	RS422/485 (2 wire)	Setting Example 4 (page 17)	Cable Diagram 1 (page 94)

Series	CPU ^{*1}	Link I/F	SIO Type	Setting Example	Cable Diagram
	HA900	Terminal Block on the controller.	RS232C	Setting Example 5 (page 19)	Cable Diagram 2 (page 99)
HA ^{*3}	HA900-D-D-D-D*D-D*D-D5D-D/D/D HA900-D-D-D-D*D-D*D-D/D/D HA901-D-D-D*D-D*D-D5D-D/D/D HA400-D-D-D*D-D*D-D5D-D/D/D HA400-D-D-D*D-D*D-D5D-D/D/D HA401-D-D-D*D-D5D-D/D/D HA401-D-D-D*D-D5D-D/D/D HA930-D-D-D*D-D5D/D/D HA430-D-D-D*D-D5D/D/D	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 6 (page 21)	Cable Diagram 1 (page 94)
	HA900-DDD*DD4-D/D HA901-DDD*DD4-D/D HA400-DDD*DD4-D/D HA401-DD*DD*D-D4-D/D HA930-DDD*DD4-D/D HA430-DDD*DD4-D/D	Terminal Block on the controller.	RS422/485 (4 wire) *4	Setting Example 7 (page 23)	Cable Diagram 10 (page 133)
	MA900-4□□□□-□-□*□□-□5/□ MA901-8□□□-□-□*□□-□5/□	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 8 (page 25)	Cable Diagram 1 (page 94)
MA900 *3 *5	MA900-4□□□□-□-□*□□-□4/□ MA901-8□□□-□-□*□□-□4/□	Terminal Block on the controller.	RS422/485 (4 wire)	Setting Example 9 (page 27)	Cable Diagram 10 (page 133)
	MA900-4□□□□-□-□*□□-□1/□ MA901-8□□□-□-□*□□-□1/□	Terminal Block on the controller.	RS232C	Setting Example 10 (page 29)	Cable Diagram 2 (page 99)
SRV	V-TIO-A-0000-00*000-00-0-0 V-TIO-C-0000-00*000-00-0-0	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 14 (page 37)	Cable Diagram 1 (page 94)
SRX	X-TIO-A-□□-□□*□□	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 15 (page 39)	Cable Diagram 1 (page 94)
SA100	SA1000000-00-0*00-50/00	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 16 (page 41)	Cable Diagram 1 (page 94)
SA200	SA2000000-00-0*00-50/0/00	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 17 (page 43)	Cable Diagram 1 (page 94)

Series	CPU ^{*1}	Link I/F	SIO Type	Setting Example	Cable Diagram
SR Mini HG (H-PCP- A/B)	H-PCP-□-□1N-□*□□	Modular connector 1 on the controller.	RS232C	Setting Example 38 (page 85)	Cable Diagram 11 (page 137)
	H-PCP-□-□4N-□*□□	Modular connector on the controller.	RS422/485 (4 wire)	Setting Example 39 (page 87)	Cable Diagram 8 (page 125)
	H-PCP-J-□4□-D*□□	COM.PORT1 and	RS422/485 (4 wire)	Setting Example 20 (page 49)	Cable Diagram 4 (page 103)
	H-PCP-J-□5□-D*□□	the controller.	RS422/485 (2 wire)	Setting Example 21 (page 51)	Cable Diagram 5 (page 107)
SR Mini HG (H-PCP- J)	H-PCP-J-□□1-D*□□		RS232C	Setting Example 22 (page 53)	Cable Diagram 12 (page 138)
	H-PCP-J-□□4-D*□□	COM.PORT3 on the controller.	RS422/485 (4 wire)	Setting Example 20 (page 49)	Cable Diagram 6 (page 114)
	H-PCP-J-□□5-D*□□		RS422/485 (2 wire)	Setting Example 21 (page 51)	Cable Diagram 7 (page 118)
REX- F9000	F9000-□□□-□*□□/□	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 13 (page 35)	Cable Diagram 1 (page 94)
	F4000000-00*00-000-10 F7000000-00*00-000-10 F9000000-00*00-000-10	Terminal Block on the controller.	RS232C	Setting Example 23 (page 55)	Cable Diagram 2 (page 99)
REX-F	F400000-00*00-000-40 F700000-00*00-00-40 F900000-00*00-00-40	Terminal Block on the controller.	RS422/485 (4 wire)	Setting Example 24 (page 57)	Cable Diagram 10 (page 133)
	F400000-00*00-000-50 F700000-00*00-000-50 F900000-00*00-00-50	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 25 (page 59)	Cable Diagram 1 (page 94)
REX-D	D400	Terminal Block on the controller.	RS422/485 (4 wire)	Setting Example 18 (page 45)	Cable Diagram 3 (page 100)
	D1000-00*00-50 D4000-0*00-0-5 D7000-0*00-0-5 D9000-0*00-0-5	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 19 (page 47)	Cable Diagram 1 (page 94)

Series	CPU ^{*1}	Link I/F	SIO Type	Setting Example	Cable Diagram
	G9□□□-□*□□-□□-1/A	Terminal Block on the controller.	RS232C	Setting Example 26 (page 61)	Cable Diagram 2 (page 99)
REX-G9	G9□□□-□*□□-□□-4/A	Terminal Block on the controller.	RS422/485 (4 wire)	Setting Example 27 (page 63)	Cable Diagram 10 (page 133)
	G9□□□-□*□□-□□-2/A	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 28 (page 65)	Cable Diagram 9 (page 128)
	P300□□□-□================================	Terminal Block on the controller.	RS232C	Setting Example 29 (page 67)	Cable Diagram 2 (page 99)
REX- P300	P300000-00-0*D-000-4	Terminal Block on the controller.	RS422/485 (4 wire)	Setting Example 30 (page 69)	Cable Diagram 3 (page 100)
	P300□□□-□□=D*D-□□□□-5	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 31 (page 71)	Cable Diagram 1 (page 94)
REX-	P250□□□-□*□-1	Terminal Block on the controller.	RS232C	Setting Example 32 (page 73)	Cable Diagram 2 (page 99)
P250	P250□□□-□*□-□-2	Terminal Block on the controller.	RS422/485 (4 wire)	Setting Example 33 (page 75)	Cable Diagram 9 (page 128)
PEY AD	AD410□-□*□-□-0-4/CE	Terminal Block on the controller.	RS422/485 (4 wire)	Setting Example 34 (page 77)	Cable Diagram 3 (page 100)
KLA-AD	AD410□-□*□-□-□-5/CE	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 35 (page 79)	Cable Diagram 1 (page 94)
REX-PG	PG410□□*□□-□4	Terminal Block on the controller.	RS422/485 (4 wire)	Setting Example 36 (page 81)	Cable Diagram 3 (page 100)
	PG410□□*□□-□5	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 37 (page 83)	Cable Diagram 1 (page 94)
AE500	AE500000-0*000-50/0	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 11 (page 31)	Cable Diagram 1 (page 94)
LE100	LE100-□□*□5□□-□□	Terminal Block on the controller.	RS422/485 (2 wire)	Setting Example 12 (page 33)	Cable Diagram 1 (page 94)

*1 The mode data " \Box " will vary depending on the type of option.

- *2 There are two communication port: Communication 1 and Communication 2. Communication 1 is used for host communication. Communication 2 is used for intercontroller communication, but can be also used for host communication. When Communication 2 is used for host communication, it is necessary to change the protocol of Communication 2 (RKC communication is set).
- *3 No memory area number is specified, "Control area" is used as default.
- *4 Only Communication 2 supports RS-422 connection.
- *5 Only support Single mode, Multi-point mode hasn't been supported.

■ COM Port of IPC

When connecting IPC with External Device, the COM port which can be used changes with series and SIO type. Please refer to the manual of IPC for details.

Usable port

Series	Usable port				
Ochos	RS-232C	RS-422/485(4 wire)	RS-422/485(2 wire)		
PS-2000B	COM1 ^{*1} , COM2, COM3 ^{*1} , COM4	-	-		
PS-3650A, PS-3651A	COM1 ^{*1}	-	-		
PS-3700A (Pentium®4-M) PS-3710A	COM1 ^{*1} , COM2 ^{*1} , COM3 ^{*2} , COM4	COM3 ^{*2}	COM3*2		
PS-3711A	COM1 ^{*1} , COM2 ^{*2}	COM2 ^{*2}	COM2 ^{*2}		

*1 The RI/5V can be switched. Please switch with the change switch of IPC.

*2 It is necessary to set up the SIO type with the Dip switch. Please set up as follows according to SIO type to be used.

Dip switch setting: RS-232C

Dip switch	Setting	Description	
1	OFF	Reserve (always OFF)	
2	OFF	SIO type: PS 232C	
3	OFF	510 type. K5-252e	
4	OFF	Output mode of SD (TXD) data: Always output	
5	OFF	Terminal resistance (220 Ω) insertion to SD (TXD): None	
6	OFF	Terminal resistance (220 Ω) insertion to RD (RXD): None	
7	OFF	Short-circuit of SDA (TXA) and RDA (RXA): Does not Exist	
8	OFF	Short-circuit of SDB (TXB) and RDB (RXB): Does not Exist	
9	OFF	– RS (RTS) Auto control mode: Disable	
10	OFF		

Dip switch setting: RS-422/485 (4 wire)

Dip switch	Setting	Description	
1	OFF	Reserve (always OFF)	
2	ON	SIQ type: RS-422/485	
3	ON	510 type. NS-422/403	
4	OFF	Output mode of SD (TXD) data: Always output	
5	OFF	Terminal resistance (220 Ω) insertion to SD (TXD): None	
6	OFF	Terminal resistance (220 Ω) insertion to RD (RXD): None	
7	OFF	Short-circuit of SDA (TXA) and RDA (RXA): Does not Exist	
8	OFF	Short-circuit of SDB (TXB) and RDB (RXB): Does not Exist	
9	OFF	– RS (RTS) Auto control mode: Disable	
10	OFF		

Dip switch setting: RS-422/485 (2 wire)

Dip switch	Setting	Description	
1	OFF	Reserve (always OFF)	
2	ON	STO turner DS 422/405	
3	ON	510 type. K5-422/465	
4	OFF	Output mode of SD (TXD) data: Always output	
5	OFF	Terminal resistance (220 Ω) insertion to SD (TXD): None	
6	OFF	Terminal resistance (220 Ω) insertion to RD (RXD): None	
7	ON	Short-circuit of SDA (TXA) and RDA (RXA): Exist	
8	ON	Short-circuit of SDB (TXB) and RDB (RXB): Exist	
9	ON	- RS (RTS) Auto control mode: Enable	
10	ON		

2 Selection of External Device

Select the External Device to be connected to the Display.

💰 New Pr	💰 New Project File 🗙 🗙					
Device/PL	C					
Maker	RKC INSTRUMENT INC.					
Driver	Temperature Controller					
🗖 Use S	Bystem Area Refer to the manual of this Device/PLC					
Connection Method Port COM1						
Back	Go to Device/PLC Manual Communication Detail Settings New Screen Cancel					

Setup Items	Setup Description
Maker	Select the maker of the External Device to be connected. Select "RKC INSTRUMENT INC.".
Driver	Select a model (series) of the External Device to be connected and connection method. Select "Temperature Controller". Check the External Device which can be connected in "Temperature Controller" in system configuration. I System Configuration" (page 3)
Use System Area	Not use at this driver.
Port	Select the Display port to be connected to the External Device.

3 Example of Communication Setting

Examples of communication settings of the Display and the External Device, recommended by Pro-face, are shown.

3.1 Setting Example 1

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC1	
Summary	Change Device/PLC
Maker RKCINSTRUMENTINC. Driver Temperature Controller	Port COM1
Text Data Mode 2 Change	
Communication Settings	
SID Type C RS232C	
Speed 9600	
Data Length C 7 💿 8	
Parity O NONE O EVEN O ODD	
Stop Bit 💿 1 💿 2	
Flow Control © NONE O ER(DTR/CTS) O XON/XOFF	
Timeout 3 💼 (sec)	
Retry 2	
Wait To Send 0 🚔 (ms)	
RI / VCC © RI C VCC	
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply), If you use the Digital's RS232C Isolation Unit, please select it to VCC.	
Device-Specific Settings	
Allowable No. of Device/PLCs 16 Unit(s)	
No. Device Name Settings No. Device Name Settings 1 PLC1 Image: Series=CB,Device Address=0	

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	CB	•
Device Address	0	-
		Default
OK (<u>0</u>)		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the Shift key to change from PV/SV display mode to communication setting mode.
- 2. Press the SET key and select parameters.
- 3. Press UP/Down keys to change the setting.
- 4. While depressing the SET key, press Shift key to change from communication setting mode to PV/SV display mode.
- 5. Turn off power to the temperature controller and turn on again to set the setting.

Setting value

Add	0
bPS	2
bIT	0

NOTE

3.2 Setting Example 2

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary Change Der	vice/PLC
Maker RKC INSTRUMENT INC. Driver Temperature Controller Port COM1	
Text Data Mode 2 Change	
Communication Settings	
SIO Type 💿 RS232C 🔿 RS422/485(2wire) 🔿 RS422/485(4wire)	
Speed 19200 💌	
Data Length C 7 💽 8	
Parity	
Stop Bit 💿 1 🔿 2	
Flow Control C NONE C ER(DTR/CTS) C XON/XOFF	
Timeout 3 😴 (sec)	
Retry 2	
Wait To Send 0 👘 (ms)	
RI / VCC RI	
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.	
Device-Specific Settings	
Allowable No. of Device/PLCs 16 Unit(s)	
1 PLC1 Series=FB,Device Address=0	

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	FB	•
Device Address	0	÷
		Default
OK (<u>0</u>)		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the Shift key and hold until display mode changes from PV/SV display mode to engineering mode.
- 2. Press the Up key several times to set the F60, and press the SET key.
- 3. Set 0 (zero) to CMP1.
- 4. While depressing the SET key, press the Shift key to change from engineering mode to PV/SV display mode.
- 5. While depressing the SET key, press the Shift key to change from PV/SV display mode to setup setting mode.
- 6. Press the SET key several times to select the parameter.
- 7. Press Up/Down keys to change the setting.
- 8. While depressing the SET key, press the Shift key to change from setup setting mode to PV/SV display mode.
- 9. Turn off power of the temperature controller and turn on again to set the setting.

Setting value

Add1	0
bPS1	19.2
bIT1	8n1

NOTE

3.3 Setting Example 3

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKCINSTRUMENT IN	Driver Temperature Controller Port COM1
Text Data Mode 2 Cha	192
Communication Settings	
SIO Type O RS23	2C C RS422/485(2wire) © RS422/485(4wire)
Speed 19200	_
Data Length 📀 7	• 8
Parity 💿 NON	C EVEN C ODD
Stop Bit 💿 1	© 2
Flow Control 💿 NON	O ER(DTR/CTS) O XON/XOFF
Timeout 3	÷ (sec)
Retry 2	-
Wait To Send 0	• (ms)
RI/VCC © RI	C VCC
In the case of RS232C, you ca or VCC (5V Power Supply). If Isolation Unit, please select it t	n select the 9th pin to RI (Input) ou use the Digital's RS232C VCC. Default
Device-Specific Settings	
Allowable No. of Device/PLCs	6 Unit(s)
No. Device Name	Settings Series=FB,Device Address=0

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	FB	•
Device Address	0	÷
		Default
OK (<u>O)</u>		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the Shift key and hold until display mode changes from PV/SV display mode to engineering mode.
- 2. Press the Up key several times to set the F60, and press the SET key.
- 3. Set 0 (zero) to CMP1.
- 4. While depressing the SET key, press the Shift key to change from engineering mode to PV/SV display mode.
- 5. While depressing the SET key, press the Shift key to change from PV/SV display mode to setup setting mode.
- 6. Press the SET key several times to select the parameter.
- 7. Press Up/Down keys to change the setting.
- 8. While depressing the SET key, press the Shift key to change from setup setting mode to PV/SV display mode.
- 9. Turn off power of the temperature controller and turn on again to set the setting.

Setting value

Add1	0
bPS1	19.2
bIT1	8n1

NOTE

3.4 Setting Example 4

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1			
Summary			Change Device/PLC
Maker RKC INSTRUMEN	TINC. Driver Temp	perature Controller	Port COM1
Text Data Mode 2	Change		
Communication Settings			
SIO Type 🔷 I	RS232C 💿 RS422/485(2wire)	C RS422/485(4wire)	
Speed 192	200 🔽		
Data Length 🛛 🖸	7 💿 8		
Parity 💽 I	NONE C EVEN	C ODD	
Stop Bit 📀 1	1 O 2		
Flow Control 💿 1	NONE O ER(DTR/CTS)	C XON/XOFF	
Timeout 3	÷ (sec)		
Retry 2			
Wait To Send 0	🕂 (ms)		
RI / VCC 💿 B	RI O VCC		
In the case of RS232C, y or VCC (5V Power Supply Isolation Unit, please sele	ou can select the 9th pin to RI (Inpu)). If you use the Digital's RS232C ct it to VCC.	() Default	
Device-Specific Settings			
Allowable No. of Device/PL	_Cs 16 Unit(s) 📊		
No. Device Name	Settings	Device Address 0	
A PLUI	Literies=FB,	Device Address=0	

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	FB	•
Device Address	0	÷
		Default
OK (<u>0</u>)		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the Shift key and hold until display mode changes from PV/SV display mode to engineering mode.
- 2. Press the Up key several times to set the F60, and press the SET key.
- 3. Set 0 (zero) to CMP1.
- 4. While depressing the SET key, press the Shift key to change from engineering mode to PV/SV display mode.
- 5. While depressing the SET key, press the Shift key to change from PV/SV display mode to setup setting mode.
- 6. Press the SET key several times to select the parameter.
- 7. Press Up/Down keys to change the setting.
- 8. While depressing the SET key, press the Shift key to change from setup setting mode to PV/SV display mode.
- 9. Turn off power of the temperature controller and turn on again to set the setting.

Setting value

Add1	0
bPS1	19.2
bIT1	8n1

NOTE

3.5 Setting Example 5

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary Change Device/PLC	
Maker RKCINSTRUMENT INC. Driver Temperature Controller Port COM1	1
Text Data Mode 2 Change	
Communication Settings	
SID Type 💿 RS232C 💿 RS422/485(2wire) 💿 RS422/485(4wire)	
Speed 9600 💌	
Data Length C 7 📀 8	
Parity © NONE © EVEN © ODD	
Stop Bit 💿 1 💿 2	
Flow Control © NONE O ER(DTR/CTS) O XON/XOFF	
Timeout 3 📑 (sec)	
Retry 2	
Wait To Send 0 👘 (ms)	
RI / VCC © RI © VCC	
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.	
Device-Specific Settings	
Allowable No. of Device/PLCs 16 Unit(s)	
No. Device Name Settings	

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	HA	•
Device Address	0	÷
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the Shift key to change from SV setting & monitor mode to setup setting mode.
- 2. Press the SET key and select parameters.
- 3. Press UP/Down keys to change the setting.
- 4. While depressing the SET key, press Shift key to change from setup setting mode to SV setting & monitor mode.
- 5. Turn off power to the temperature controller and turn on again to set the setting.

Setting value

Add1	0
bPS1	9.6
bIT1	8n1

NOTE

3.6 Setting Example 6

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary Change Device	/PLC
Maker RKCINSTRUMENT INC. Driver Temperature Controller Port COM1	
Text Data Mode 2 Change	
Communication Settings	
SIO Type O RS232C 💿 RS422/485(2wire) O RS422/485(4wire)	
Speed 9600	
Data Length C 7 📀 8	
Parity © NONE © EVEN © ODD	
Stop Bit 💿 1 🔿 2	
Flow Control C NONE C ER(DTR/CTS) C XON/XOFF	
Timeout 3 💼 (sec)	
Retry 2	
Wait To Send 0 🚊 (ms)	
RI/VCC C RI O VCC	
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.	
Device-Specific Settings	
Allowable No. of Device/PLCs 16 Unit(s)	
No. Device Name Settings 1 PLC1 Im Series=HA,Device Address=0	

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	HA	•
Device Address	0	÷
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the Shift key to change from SV setting & monitor mode to setup setting mode.
- 2. Press the SET key and select parameters.
- 3. Press UP/Down keys to change the setting.
- 4. While depressing the SET key, press Shift key to change from setup setting mode to SV setting & monitor mode.
- 5. Turn off power to the temperature controller and turn on again to set the setting.

Setting value

Add1	0
bPS1	9.6
bIT1	8n1

NOTE

3.7 Setting Example 7

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary Change Device/PLC	
Maker RKC INSTRUMENT INC. Driver Temperature Controller Port COM1	
Text Data Mode 2 Change	
Communication Settings	
SIO Type O RS232C O RS422/485(2wire) 💿 RS422/485(4wire)	
Speed 9600 💌	
Data Length 🔿 7 💿 8	
Parity © NONE O EVEN O ODD	
Stop Bit 💿 1 💿 2	
Flow Control © NONE O ER(DTR/CTS) O XON/XOFF	
Timeout 3 😑 (sec)	
Retry 2 📑	
Wait To Send 0 🔆 (ms)	
RL/VCC © RL O VCC	
In the case of R5232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's R5232C Isolation Unit, please select it to VCC.	
Device-Specific Settings	
Allowable No. of Device/PLCs 16 Unit(s)	
NO. Device Name Settings	_

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	HA	•
Device Address	0	•
		Default
OK (<u>0</u>)		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the Shift key to change from SV setting & monitor mode to setup setting mode.
- 2. Press the SET key and select parameters.
- 3. Press UP/Down keys to change the setting.
- 4. While depressing the SET key, press Shift key to change from setup setting mode to SV setting & monitor mode.
- 5. Turn off power to the temperature controller and turn on again to set the setting.

Setting value

Add1	0
bPS1	9.6
bIT1	8n1

NOTE

3.8 Setting Example 8

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Summary Unange Device/PLU
Maker RKC INSTRUMENT INC. Driver Temperature Controller Port COM1
Text Data Mode 2 Change
Communication Settings
SID Type C RS232C 💿 RS422/485(2wire) C RS422/485(4wire)
Speed 9600 💌
Data Length C 7 💿 8
Parity © NONE O EVEN O ODD
Stop Bit
Flow Control © NONE O ER(DTR/CTS) O XON/XOFF
Timeout 3 📻 (sec)
Retry 2
Wait To Send 0 🚊 (ms)
RI / VCC O RI O VCC
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.
Device-Specific Settings
Allowable No. of Device/PLCs 16 Unit(s)
NO. Device Name Settings No. Device Name Settings 1 PLC1 Image: Settings Settings

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	MA	•
Device Address	0	•
		Default
OK (<u>O)</u>		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the <R/S key to change from PV/SV display mode to setup setting mode.
- 2. Press the SET key and select parameters.
- 3. Press UP/Down keys and <R/S key to change the setting.
- 4. While depressing the SET key, press < R/S key to change from setup setting mode to PV/SV display mode.
- 5. Turn off power to the temperature controller and turn on again to set the setting.

Setting value

Add	0
bPS	960
bIT	8n1



3.9 Setting Example 9

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1		
Summary Change Device/PLC		
Maker RKC INSTRUMENT INC. Driver Temperature Controller Port COM1		
Text Data Mode 2 Change		
Communication Settings		
SIO Type C RS232C C RS422/485(2wire) C RS422/485(4wire)		
Speed 9600		
Data Length O 7 💿 8		
Parity © NONE C EVEN C ODD		
Stop Bit 💿 1 💿 2		
Flow Control © NONE © ER(DTR/CTS) © XON/XOFF		
Timeout 3 📑 (sec)		
Retry 2 🚊		
Wait To Send 0 📑 (ms)		
RI / VCC © RI C VCC		
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC. Default		
Device-Specific Settings		
Allowable No. of Device/PLCs 16 Unit(s)		
No. Device Name Settings Viol Device Name Settings Image: Provide Address = 0 Image: Provide Address = 0 Image: Provide Address = 0		

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	MA	•
Device Address	0	•
		Default
OK (<u>O)</u>		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the <R/S key to change from PV/SV display mode to setup setting mode.
- 2. Press the SET key and select parameters.
- 3. Press UP/Down keys and <R/S key to change the setting.
- 4. While depressing the SET key, press < R/S key to change from setup setting mode to PV/SV display mode.
- 5. Turn off power to the temperature controller and turn on again to set the setting.

Setting value

Add	0
bPS	960
bIT	8n1



3.10 Setting Example 10

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKC INSTR	JMENT INC. Driver Temperature Controller Port COM1
Text Data Mode	2 Change
Communication Settings	
SIO Type	
Speed	9600
Data Length	C 7 🕫 8
Parity	NONE C EVEN C ODD
Stop Bit	© 1 © 2
Flow Control	NONE O EF(DTR/CTS) O XON/XOFF
Timeout	3 📑 (sec)
Retry	2 -
Wait To Send	0 * (ms)
RI / VCC	RI O VCC
In the case of RS2 or VCC (5V Power Isolation Unit, pleas	I2C, you can select the 9th pin to RI (Input) Supply). If you use the Digital's RS232C e select it to VCC.
Device-Specific Settings	
Allowable No. of Dev	ce/PLCs 16 Unit(s)
No. Device Na	ne Settings Series=MA.Device Address=0
Speed Data Length Parity Stop Bit Flow Control Timeout Retry Wait To Send RI / VCC In the case of RS2 or VCC (SV Power Isolation Unit, pleas Device-Specific Settings Allowable No. of Dev No. Device Na X 1 PLC1	9600 Image: Constraint of the second sec

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	MA	•
Device Address	0	•
		Default
OK (<u>O)</u>		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the <R/S key to change from PV/SV display mode to setup setting mode.
- 2. Press the SET key and select parameters.
- 3. Press UP/Down keys and <R/S key to change the setting.
- $\label{eq:setting} \text{4. While depressing the SET key, press < R/S key to change from setup setting mode to PV/SV display mode. }$
- 5. Turn off power to the temperature controller and turn on again to set the setting.

Setting value

Add	0
bPS	960
bIT	8n1



3.11 Setting Example 11

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKC INSTRU	AENT INC. Driver Temperature Controller Port COM1
Text Data Mode	2 Change
Communication Settings	
SIO Type	C RS232C © RS422/485(2wire) C RS422/485(4wire)
Speed	9600
Data Length	○7
Parity	NONE C EVEN C ODD
Stop Bit	● 1
Flow Control	NONE O ER(DTR/CTS) O XON/XOFF
Timeout	3 📑 (sec)
Retry	2
Wait To Send	0 * (ms)
RI / VCC	© RI O VCC
In the case of RS23 or VCC (5V Power 9 Isolation Unit, please	C, you can select the 9th pin to RI (Input) ipply). If you use the Digital's RS232C select it to VCC. Default
Device-Specific Settings	
Allowable No. of Devi	e/PLCs 16 Unit(s)
No. Device Nar	Settings Series=AE.Device Address=0
Timeout Retry Wait To Send RI / VCC In the case of RS23 or VCC (SV Power 3 Isolation Unit, please Device-Specific Settings Allowable No. of Devi No. Device Nar No. Device Nar 1 PLC1	Settings Settings Settings Settings

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	AE	•
Device Address	0	÷
		Default
OK (<u>O)</u>		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

1. While depressing the Shift key, press the SET key to change from PV display mode to communication setting mode.

Device address of setting item is displayed.

2. Press the SET key to display the communication item to be set.

Every time the SET key is depressed, setting item switches.

- 3. Press the Shift key to move to the value setting display. Press the Up/Down keys and input the setting value.
- 4. Press the SET key to register the input value.
- 5. While depressing the Shift key, press the SET key to change from communication setting mode to PV display mode.

Setting value

Add	0
bPS	2
bIT	0

NOTE

3.12 Setting Example 12

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKC INSTR	JMENT INC. Driver Temperature Controller Port COM1
Text Data Mode	2 Change
Communication Settings	
SIO Type	C RS232C
Speed	9600
Data Length	○7 ⊙8
Parity	O EVEN ○ ODD O
Stop Bit	© 1 © 2
Flow Control	C NONE C ER(DTR/CTS) C XON/XOFF
Timeout	3 📑 (sec)
Retry	2 📑
Wait To Send	0 (ms)
RI / VCC	O RI O VCC
In the case of RS2 or VCC (5V Power Isolation Unit, plea	2C, you can select the 9th pin to RI (Input) jupply). If you use the Digital's RS232C s select it to VCC. Default
Device-Specific Settings	
Allowable No. of Dev	ce/PLCs 16 Unit(s)
No. Device Na	ie Settings Series=LE Device Address=0

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	LE	•
Device Address	0	÷
		Default
OK (<u>O)</u>		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

1. While depressing the Down key, press the SET key to change from PV display mode to device configuration setting mode.

Communication parameter group is displayed.

- 2. Press the UP/Down keys to display the communication parameter group "PG10".
- 3. Press the SET key to display the communication item to be set.

Every time the SET key is depressed, setting item switches.

- 4. Press the UP/Down keys and set the communication setting.
- 5. Turn off power of the temperature controller and turn on again to set the setting.

Setting value

Add	0
bPS	2
bIT	0

NOTE

3.13 Setting Example 13

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1				
Summary	Change Device/PLC			
Maker RKC INST	RUMENT INC. Driver Temperature Controller Port COM1			
Text Data Mode	2 Change			
Communication Settings				
SIO Type	O RS232C			
Speed	9600			
Data Length	O 7 O 8			
Parity	NONE O EVEN O ODD			
Stop Bit	© 1 © 2			
Flow Control	O NONE O ER(DTR/CTS) O XON/XOFF			
Timeout	3 👘 (sec)			
Retry	2			
Wait To Send	0 (ms)			
RI / VCC	© RI O VCC			
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC. Default				
Device-Specific Settings				
Allowable No. of Device/PLCs 16 Unit(s)				
No. Device Name Settings				
I I I I I I I I I I I I I I I I I				

Device Setting

💣 Individual Device Settings 🗙				
PLC1				
Series	REX-F	9000 💌		
Device Address	0	÷		
		Default		
OK (<u>0)</u>		Cancel		

Communication setting of the external device is set with the SEL, MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Set the external device to operation STOP status. Press the MODE key to display "Operation execution (RUN) /STOP transfer," and press the Down key to set the mode to STOP.
- 2. Press the SET key to change from SV setting mode to operator setting mode.
- 3. Depress the SET key for 5 seconds or more to change from operator setting mode to setup mode.
- 4. Press the Up key to display PG24.
- 5. Every time the SET key is depressed, setting item switches.

Display the item to be set, and select set contents with the Up/Down keys or the Shift key.

- 6. Press the SET key to set the set contents.
- 7. Press the MODE key to display "Operation execution (RUN)/STOP transfer," and press the Up key to set the mode to RUN.

Setting value

Add	0
bPS	3
bIT	0
CMPS	0

NOTE
3.14 Setting Example 14

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1		
Summary		Change Device/PLC
Maker RKC INST	UMENT INC. Driver Temperature Controller F	Port COM1
Text Data Mode	2 Change	
Communication Settings		
SIO Type	C RS232C	
Speed	9600 💌	
Data Length	○7 ●8	
Parity		
Stop Bit		
Flow Control	NONE O ER(DTR/CTS) O XON/XOFF	
Timeout	3 📑 (sec)	
Retry	2 😑	
Wait To Send	0 • (ms)	
RI / VCC	© RI O VCC	
In the case of RS or VCC (5V Powe Isolation Unit, plea	32C, you can select the 9th pin to RI (Input) Supply). If you use the Digital's RS232C e select it to VCC. Default	
Device-Specific Settings		
Allowable No. of De	ice/PLCs 16 Unit(s)	
No. Device N	me Settings	

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	SRV	•
Device Address	0	÷
		Default
OK (<u>O</u>)		Cancel

Communication setting of the external device is set with the rotary switch on the front face of the temperature controller and the dip switch in the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. Set module address with the rotary switch on the front face of the temperature controller.
- 2. Set communication speed and data bit construction with the dip switch on the side of the temperature controller.

Setting value

Rotary switch

,	
Upper Digit Setting	0
Lower Digit Setting	0

Dip switch

Dip switch	Setting	Description
SW1	ON	Communication speed
SW2	OFF	Communication speed
SW3	ON	
SW4	OFF	Data bit construction
SW5	OFF]
SW6	OFF	Protocol construction
SW7	OFF	Fixed
SW8	OFF	I IACU

3.15 Setting Example 15

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKCINSTRU	MENT INC. Driver Temperature Controller Port COM1
Text Data Mode	2 Change
Communication Settings	
SIO Type	C RS232C © RS422/485(2wire) C RS422/485(4wire)
Speed	9600 💌
Data Length	○7
Parity	NONE C EVEN C ODD
Stop Bit	€1 © 2
Flow Control	NONE O ER(DTR/CTS) O XON/XOFF
Timeout	3 📩 (sec)
Retry	2
Wait To Send	0 * (ms)
RI / VCC	O RI O VCC
In the case of RS23 or VCC (5V Power 1 Isolation Unit, pleas	IC, you can select the 9th pin to RI (Input) upply]. If you use the Digital's RS232C select it to VCC. Default
Device-Specific Settings	
Allowable No. of Devi	e/PLCs 16 Unit(s)
No. Device Nar	e Settings

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	SRX	•
Device Address	0	÷
		Default
OK (<u>0</u>)		Cancel

Communication setting of the external device is set with the rotary switch on the front face of the temperature controller and the dip switch in the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. Set module address with the rotary switch on the front face of the temperature controller.
- 2. Set communication speed and data bit construction with the dip switch on the side of the temperature controller.

Setting value

Rotary switch

Upper Digit Setting	0
Lower Digit Setting	0

Dip switch

Dip switch	Setting	Description
SW1	ON	Communication speed
SW2	OFF	Communication speed
SW3	ON	
SW4	OFF	Data bit construction
SW5	OFF	
SW6	OFF	Protocol construction
SW7	OFF	Fixed
SW8	OFF	i ixeu

3.16 Setting Example 16

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1		
Summary		Change Device/PLC
Maker RKC INSTRI	JMENT INC. Driver Temperature Controller	Port COM1
Text Data Mode	2 Change	
Communication Settings		
SIO Type	○ RS232C ● RS422/485(2wire) ○ RS422/4	85(4wire)
Speed	9600	
Data Length	⊙7 ⊙8	
Parity	NONE O EVEN O ODD	
Stop Bit		
Flow Control	NONE O ER(DTR/CTS) O XON/XOFF	
Timeout	3 📑 (sec)	
Retry	2 🕂	
Wait To Send	0 (ms)	
RI / VCC	RI VCC	
In the case of RS2 or VCC (5V Power Isolation Unit, pleas	2C, you can select the 9th pin to RI (Input) Supply). If you use the Digital's RS232C select it to VCC.	Default
Device-Specific Settings		
Allowable No. of Devi	ce/PLCs 16 Unit(s) 📷	
No. Device Nar	ne settings Series=SA100,Device Address	=0

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	SA100	•
Device Address	0	-
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the Shift key to change from PV/SV display mode to communication setting mode.
- 2. Press the SET key and select parameters.
- 3. Press UP/Down keys to change the setting.
- 4. While depressing the SET key, press Shift key to change from communication setting mode to PV/SV display mode.
- 5. Turn off power to the temperature controller and turn on again to set the setting.

Setting value

Add	0
bPS	960
bIT	8n1

NOTE

3.17 Setting Example 17

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1		
Summary		Change Device/PLC
Maker RKC INSTR	UMENT INC. Driver Temperature Controller Po	ort COM1
Text Data Mode	2 Change	
Communication Settings		
SIO Type	C RS232C • RS422/485(2wire) C RS422/485(4wire)	
Speed	9600 💌	
Data Length	C 7 C 8	
Parity		
Stop Bit		
Flow Control	NONE O ER(DTR/CTS) O XON/XOFF	
Timeout	3 📑 (sec)	
Retry	2 🕂	
Wait To Send	0 <u>*</u> (ms)	
RI / VCC	C RI C VCC	
In the case of RS2 or VCC (5V Power Isolation Unit, pleas	32C, you can select the 9th pin to RI (Input) Supply), If you use the Digital's RS232C se select it to VCC. Default	
Device-Specific Settings		
Allowable No. of Dev	/ice/PLCs 16 Unit(s) 📷	
No. Device Na	me Settings Series=SA200,Device Address=0	

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	SA200	•
Device Address	0	-
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the SET, Shift, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While depressing the SET key, press the Shift key to change from PV/SV display mode to communication setting mode.
- 2. Press the SET key and select parameters.
- 3. Press UP/Down keys to change the setting.
- 4. While depressing the SET key, press Shift key to change from communication setting mode to PV/SV display mode.
- 5. Turn off power to the temperature controller and turn on again to set the setting.

Setting value

Add	0
bPS	960
bIT	8n1

NOTE

3.18 Setting Example 18

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKC INSTRUMENT INC.	Driver Temperature Controller Port COM1
Text Data Mode 2 Change	2
Communication Settings	
SIO Type O RS232C	O RS422/485(2wire)
Speed 9600	•
Data Length 🛛 🔿 7	• 8
Parity NONE 	O EVEN O ODD
Stop Bit 💿 1	© 2
Flow Control © NONE	O ER(DTR/CTS) O XON/XOFF
Timeout 3	* (sec)
Retry 2	× -
Wait To Send 0	4 (ms)
RI / VCC 💿 RI	O VCC
In the case of RS232C, you can s or VCC (5V Power Supply). If you Isolation Unit, please select it to V	elect the 9th pin to RI (Input) use the Digital's RS232C CC. Default
Device-Specific Settings	
Allowable No. of Device/PLCs 161	Jnit(s)
No. Device Name	

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-D	
Device Address	0	÷
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the SEL, MONI/MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Depress the SEL key for 2 seconds to change from PV display mode to engineer setting mode. Parameter group is displayed.
- 2. Press the Up/Down keys to display the parameter group, "PG8."
- 3. Press the SEL key to display the setting item. Every time the SEL key is depressed, setting item switches.
- 4. Press the Up/Down keys to select the setting value, and press the SEL key.
- 5. Press the Monitor/Mode key to switch to the PV display mode.
- 6. Press the Monitor/Mode key and the SEL key at the same time to change from PV display mode to SETUP setting mode.
- 7. Press the SEL key several times to display Add.
- 8. Press the Up/Down keys to input set value, and press the SEL key to set the input value.
- 9. Press the Monitor/Mode keys to switch to the PV display mode.
- 10. Turn off power of external device off, and turn it on again.

Setting value

Engineer setting mode

bPS	3
bIT	0

SETUP setting mode

Add 0



3.19 Setting Example 19

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKC INST	RUMENT INC. Driver Temperature Controller Port COM1
Text Data Mode	2 Change
Communication Settings	
SIO Type	O RS232C I RS422/485(2wire) O RS422/485(4wire)
Speed	9600
Data Length	○7
Parity	NONE C EVEN C ODD
Stop Bit	© 1 © 2
Flow Control	💿 NONE 🔿 ER(DTR/CTS) 🔿 XON/XOFF
Timeout	3 🚔 (sec)
Retry	2
Wait To Send	0 (ms)
RI / VCC	O RI O VCC
In the case of RS or VCC (5V Powe Isolation Unit, ple	i232C, you can select the 9th pin to RI (Input) er Supply). If you use the Digital's RS232C ase select it to VCC. Default
Device-Specific Settings	\$
Allowable No. of De	evice/PLCs 16 Unit(s) 📷
No. Device N	Vame Settings
l i li con	ULL JOSIGS-HEAD DEVICE Address-0

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-D	•
Device Address	0	÷
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the SEL, MONI/MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Depress the SEL key for 2 seconds to change from PV display mode to engineer setting mode. Parameter group is displayed.
- 2. Press the Up/Down keys to display the parameter group, "PG8."
- 3. Press the SEL key to display the setting item. Every time the SEL key is depressed, setting item switches.
- 4. Press the Up/Down keys to select the setting value, and press the SEL key.
- 5. Press the Monitor/Mode key to switch to the PV display mode.
- 6. Press the Monitor/Mode key and the SEL key at the same time to change from PV display mode to SETUP setting mode.
- 7. Press the SEL key several times to display Add.
- 8. Press the Up/Down keys to input set value, and press the SEL key to set the input value.
- 9. Press the Monitor/Mode keys to switch to the PV display mode.
- 10. Turn off power of external device off, and turn it on again.

Setting value

Engineer setting mode

bPS	3
bIT	0

SETUP setting mode

Add 0



3.20 Setting Example 20

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKC INSTRUMENT INC.	Driver Temperature Controller Port COM1
Text Data Mode 2 Change	
Communication Settings	
SIO Type C RS232C	C RS422/485(2wire) © RS422/485(4wire)
Speed 9600	•
Data Length 🔿 7	© 8
Parity 💿 NONE	O EVEN O ODD
Stop Bit 📀 1	C 2
Flow Control 📀 NONE	C ER(DTR/CTS) C XON/XOFF
Timeout 3 📑 ((sec)
Retry 2 📑	
Wait ToSend 🛛 📑 ((ms)
RI / VCC © RI	C VCC
In the case of RS232C, you can select or VCC (5V Power Supply). If you use	ct the 9th pin to RI (Input) e the Dinital's RS232C
Isolation Unit, please select it to VCC.	Default
Device-Specific Settings	
Allowable No. of Device/PLCs 16 Unit	(s)
No. Device Name	Settings

Device Setting

💰 Individual Device Settings 🛛 🗙			×
PLC1			
Series	SR-Mini-H	G(H-PCP-J)	•
Device Address	0		÷
		Default	
OK		Cancel	

Communication setting of the external device is set with the rotary switch on the front face of the temperature controller and the dip switch in the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. Unit address is set with the rotary switch on the front face of the temperature controller.
- 2. Remove the temperature controller from the mother block, and set the communication speed and data construction with the dip switch in the temperature controller.

Setting value

Rotary switch

Upper Digit Setting	0
Lower Digit Setting	0

Dip switch

Dip switch	Setting	Description
SW1	OFF	Data construction
SW2	OFF	Data construction
SW3	ON	Communication speed
SW4	OFF	Communication speed

3.21 Setting Example 21

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1
Summary Change Device/PL0
Maker RKCINSTRUMENT INC. Driver Temperature Controller Port COM1
Text Data Mode 2 Change
Communication Settings
SIO Type C RS232C 💿 RS422/485(2wire) C RS422/485(4wire)
Speed 9600
Data Length 🔿 7 💿 8
Parity © NONE © EVEN © ODD
Stop Bit C 2
Flow Control O NONE O ER(DTR/CTS) O XON/XOFF
Timeout 3 📑 (sec)
Retry 2
Wait To Send 0 🔔 (ms)
RI/VCC © RI O VCC
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (SV Power Supply). If you use the Digital's RS232C Isolation Linit of page select if V/CC
Isolation only, please select it to view.
Device-Specific Settings
Allowable No. of Device/PLUs 16 Unit(s)
1 PLC1 Series=SR-Mini-HG(H-PCP-J),Device Address=0

Device Setting

💰 Individual	Device Se	ttings 🤇 🕽	<
PLC1			
Series	SR-Mini-H	G(H-PCPJ) 💌]
Device Address	0	:]
		Default	
OK		Cancel	

Communication setting of the external device is set with the rotary switch on the front face of the temperature controller and the dip switch in the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. Unit address is set with the rotary switch on the front face of the temperature controller.
- 2. Remove the temperature controller from the mother block, and set the communication speed and data construction with the dip switch in the temperature controller.

Setting value

Rotary switch

Upper Digit Setting	0
Lower Digit Setting	0

Dip switch

Dip switch	Setting	Description
SW1	OFF	Data construction
SW2	OFF	Data construction
SW3	ON	Communication speed
SW4	OFF	Communication speed

3.22 Setting Example 22

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1			
Summary		Change Device/F	<u>210</u>
Maker RKC INST	RUMENT INC.	Driver Temperature Controller Port COM1	_
Text Data Mode	2 Change		
Communication Settings			
SIO Type	• RS232C	C RS422/485(2wire) C RS422/485(4wire)	
Speed	9600	•	
Data Length	07	• 8	
Parity	NONE	O EVEN O ODD	
Stop Bit	● 1	© 2	
Flow Control	O NONE	O ER(DTR/CTS) O XON/XOFF	
Timeout	3 📫	(sec)	
Retry	2 🔹		
Wait To Send	0 🗧	(ms)	
RI / VCC	• RI	O VCC	
In the case of RS; or VCC (5V Powe Isolation Unit, plea	232C, you can sele r Supply), If you us ise select it to VCC	act the 9th pin to RI (Input) ;e the Digital's RS232C ~ Default	
Device-Specific Settings Allowable No. of De No. Device N	vice/PLCs 16 Uni ame	it(s) Settings	

Device Setting

💰 Individual	Device Se	ttings 🤇 🕽	<
PLC1			
Series	SR-Mini-H	G(H-PCPJ) 💌]
Device Address	0	:]
		Default	
OK		Cancel	

Communication setting of the external device is set with the rotary switch on the front face of the temperature controller and the dip switch in the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. Unit address is set with the rotary switch on the front face of the temperature controller.
- 2. Remove the temperature controller from the mother block, and set the communication speed and data construction with the dip switch in the temperature controller.

Setting value

Rotary switch

•	
Upper Digit Setting	0
Lower Digit Setting	0

Dip switch

Dip switch	Setting	Description
SW1	OFF	Data construction
SW2	OFF	Data construction
SW3	ON	Communication speed
SW4	OFF	Communication speed

3.23 Setting Example 23

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKCINSTRUMENT IN	C. Driver Temperature Controller Port COM1
Text Data Mode 2 Ch	nge
Communication Settings	
SIO Type 💿 RS23	2C O RS422/485(2wire) O RS422/485(4wire)
Speed 9600	•
Data Length 💿 7	08
Parity C NON	C EVEN
Stop Bit 🔿 1	• 2
Flow Control 💿 NON	O ER(DTR/CTS) O XON/XOFF
Timeout 3	📩 (sec)
Retry 2	
Wait To Send 0	* (ms)
RI / VCC RI	O VCC
In the case of RS232C, you c or VCC (5V Power Supply). If Isolation Unit, please select it	n select the 9th pin to RI (Input) ou use the Digital's RS232C o VCC. Default
Device-Specific Settings	
Allowable No. of Device/PLCs	6 Unit(s)
1 PLC1	Seturitys Series=REX-F,Device Address=0

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-F	•
Device Address	0	÷
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the SEL, MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Set the external device to the operation STOP status. Press the MODE key several times to display "Operation execution (RUN) /STOP transfer," and press the Down key to set the mode to STOP.
- 2. Press the SET key to call up the set operator level 1.
- 3. Depress the SET key for 5 seconds or more to call up the set operator level 2.
- 4. Depress the SET key for 5 seconds or more to call up the engineer level.
- 5. Press the Down key several times to display PG24.
- 6. Press the SET key to display the set contents. Every time the SET key is depressed, item to be set switches.
- 7. Input the set contents with the Up/Down key, and press the SET key.
- 8. Press the MODE key to display "Operation execution (RUN)/STOP transfer," and press the Up key to set the mode to RUN.

Setting value

Add	0
bPS	3
bIT	11

NOTE

3.24 Setting Example 24

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1			
Summary			Change Device/PLC
Maker RKC INS1	RUMENT INC.	Driver Te	Femperature Controller Port COM1
Text Data Mode	2 <u>Change</u>		
Communication Settings			
SIO Type	C RS232C	C RS422/485(2w	wire) 💿 RS422/485(4wire)
Speed	9600	-	
Data Length	• 7	C 8	
Parity	O NONE	C EVEN	⊙ ODD
Stop Bit	O 1		
Flow Control	O NONE	C ER(DTR/CTS)	i) O Xon/Xoff
Timeout	3 🕂	(sec)	
Retry	2 🕂		
Wait To Send	0 .	(ms)	
RI / VCC	© BI	C VCC	
In the case of R or VCC (5V Pow	6232C, you can sel er Supply), If you u	ect the 9th pin to RI (In se the Digital's RS232I	Input) 20
Isolation Unit, ple	ase select it to VLI		Default
Device-Specific Setting	s		
Allowable No. of D No. Device 1	evice/PLCs 16 Ur Jame	nit(s) 1111 Settings	
1 PLC1	iano -	Series=F	=REX-F,Device Address=0

Device Setting

💣 Individual	Device	Settings 🗙
PLC1		
Series	REX-F	•
Device Address	0	-
		Default
OK (<u>D</u>)		Cancel

Communication setting of the external device is set with the SEL, MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Set the external device to the operation STOP status. Press the MODE key several times to display "Operation execution (RUN) /STOP transfer," and press the Down key to set the mode to STOP.
- 2. Press the SET key to call up the set operator level 1.
- 3. Depress the SET key for 5 seconds or more to call up the set operator level 2.
- 4. Depress the SET key for 5 seconds or more to call up the engineer level.
- 5. Press the Down key several times to display PG24.
- 6. Press the SET key to display the set contents. Every time the SET key is depressed, item to be set switches.
- 7. Input the set contents with the Up/Down key, and press the SET key.
- 8. Press the MODE key to display "Operation execution (RUN)/STOP transfer," and press the Up key to set the mode to RUN.

Setting value

Add	0
bPS	3
bIT	11

NOTE

3.25 Setting Example 25

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1				
Summary				Change Device/PLC
Maker RKC INSTRUM	IENT INC.	Driver Temp	erature Controller	Port COM1
Text Data Mode 🛛 🗌	2 <u>Change</u>			
Communication Settings				
SIO Type	C RS232C	• RS422/485(2wire)	C RS422/485(4wire)	
Speed	9600	-		
Data Length 🤇	• 7	C 8		
Parity (O NONE (C EVEN	• ODD	
Stop Bit C	01 (€ 2		
Flow Control	🖲 NONE 🛛 🕴	C ER(DTR/CTS)	O XON/XOFF	
Timeout	3 📫 (se	c)		
Retry	2 📫			
Wait To Send 🛛	0 🕂 (ms	\$)		
RI/VCC (S RI 🛛 🕴	O VCC		
In the case of RS2320 or VCC (5V Power Su Isolation Unit, please s	2, you can select t pply). If you use th select it to VCC.	the 9th pin to RI (Input he Digital's RS232C) Default	
Device Constitute Collines				
Allowable No. of Device	/PLCs_16.Unit(s)	to a		
No. Device Name		Settings		
👗 1 PLC1		Series=RE×	F,Device Address=0	

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-F	•
Device Address	0	÷
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the SEL, MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Set the external device to the operation STOP status. Press the MODE key several times to display "Operation execution (RUN) /STOP transfer," and press the Down key to set the mode to STOP.
- 2. Press the SET key to call up the set operator level 1.
- 3. Depress the SET key for 5 seconds or more to call up the set operator level 2.
- 4. Depress the SET key for 5 seconds or more to call up the engineer level.
- 5. Press the Down key several times to display PG24.
- 6. Press the SET key to display the set contents. Every time the SET key is depressed, item to be set switches.
- 7. Input the set contents with the Up/Down key, and press the SET key.
- 8. Press the MODE key to display "Operation execution (RUN)/STOP transfer," and press the Up key to set the mode to RUN.

Setting value

Add	0
bPS	3
bIT	11

NOTE

3.26 Setting Example 26

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1		
Summary		Change Device/PLC
Maker RKC INST	RUMENT INC.	Driver Temperature Controller Port COM1
Text Data Mode	2 Change	
Communication Settings		
SIO Type	RS232C	O RS422/485(2wire) O RS422/485(4wire)
Speed	9600	
Data Length	O 7	• 8
Parity	NONE	C EVEN C ODD
Stop Bit	● 1	O 2
Flow Control	NONE	O ER(DTR/CTS) O XON/XOFF
Timeout	3 📫	(sec)
Retry	2 📫	
Wait To Send	0 🚦	(ms)
RI / VCC	RI	O VCC
In the case of RS or VCC (5V Powe Isolation Unit, plea	232C, you can sele r Supply), If you us ase select it to VCC	ect the 9th pin to RI (Input) se the Digital's RS232C
Device-Specific Settings		
Allowable No. of De	vice/PLCs 16 Un	nit(s) 📷
No. Device N	ame	Settings
		LED Joenes=HEX-G3,Device Address=0

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-0	i9 💌
Device Address	0	÷
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the MODE, PARA, >>>, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Press the MODE key to display "Operation execution (RUN)/STOP transfer." Press the >>> key to stop operation.
- Press PARA key to display "Setting (PARA) screen."
 Press the Up/Down keys, select PARA GROUP 24, and press the PARA key.
- Every time the PARA Key is depressed, setting item switches.
 Display the item to be set, and select the set contents with the Up/Down keys.
- After setting, press the MODE key to display "Operation execution (RUN)/STOP screen." Press the >>> key to put the operation into action.

Setting value

Bit Format	P (Parity): n DT (Data Bit): 8 SP (Stop bit): 1
Device Address	0
Speed	9600

NOTE

3.27 Setting Example 27

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKC INSTRUMENT INC. Driver Temperature Controller	Port COM1
Text Data Mode 2 Change	
Communication Settings	
SID Type C RS232C C RS422/485(2wire) 💿 RS422/485(4wire)
Speed 9600 💌	
Data Length C 7 💿 8	
Parity O NONE O EVEN O ODD	
Stop Bit	
Flow Control O NONE O ER(DTR/CTS) O XON/XOFF	
Timeout 3 😴 (sec)	
Retry 2	
Wait To Send 0 👘 (ms)	
RI / VCC © RI O VCC	
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.	Default
Device-Specific Settings	
Allowable No. of Device/PLCs 16 Unit(s)	
No. Device Name Settings 1 PLC1 Series=REX-G9.Device Address=	0

Device Setting

💰 Individual	Device	e Settings 🗙
PLC1		
Series	REX-	G9 💌
Device Address	0	*
		Default
OK (<u>O</u>)		Cancel

Communication setting of the external device is set with the MODE, PARA, >>>, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Press the MODE key to display "Operation execution (RUN)/STOP transfer." Press the >>> key to stop operation.
- Press PARA key to display "Setting (PARA) screen."
 Press the Up/Down keys, select PARA GROUP 24, and press the PARA key.
- Every time the PARA Key is depressed, setting item switches.
 Display the item to be set, and select the set contents with the Up/Down keys.
- After setting, press the MODE key to display "Operation execution (RUN)/STOP screen." Press the >>> key to put the operation into action.

Setting value

Bit Format	P (Parity): n DT (Data Bit): 8 SP (Stop bit): 1
Device Address	0
Speed	9600

NOTE

3.28 Setting Example 28

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary Change Device/F	PLC
Maker RKC INSTRUMENT INC. Driver Temperature Controller Port COM1	_
Text Data Mode 2 Change	
Communication Settings	
SID Type ORS232C ORS422/485(2wire) ORS422/485(4wire)	
Speed 9600 💌	
Data Length C 7 💽 8	
Parity © NONE © EVEN © ODD	
Stop Bit 💿 1 💿 2	
Flow Control O NONE O ER(DTR/CTS) O XON/XOFF	
Timeout 3 🚔 (sec)	
Retry 2 🚔	
Wait To Send 0 👘 (ms)	
RI/VCC © RI C VCC	
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.	
Device-Specific Settings	
Allowable No. of Device/PLCs 16 Unit(s)	
No. Device Name Settings X 1 PLC1 X 1 PLC1	

Device Setting

💰 Individual	Device	e Settings 🗙
PLC1		
Series	REX-	G9 💌
Device Address	0	•
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the MODE, PARA, >>>, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Press the MODE key to display "Operation execution (RUN)/STOP transfer." Press the >>> key to stop operation.
- Press PARA key to display "Setting (PARA) screen."
 Press the Up/Down keys, select PARA GROUP 24, and press the PARA key.
- Every time the PARA Key is depressed, setting item switches.
 Display the item to be set, and select the set contents with the Up/Down keys.
- After setting, press the MODE key to display "Operation execution (RUN)/STOP screen." Press the >>> key to put the operation into action.

Setting value

Bit Format	P (Parity): n DT (Data Bit): 8 SP (Stop bit): 1
Device Address	0
Speed	9600

NOTE

3.29 Setting Example 29

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKC INST	JMENT INC. Driver Temperature Controller Port COM1
Text Data Mode	2 Change
Communication Settings	
SIO Type	RS232C C RS422/485(2wire) C RS422/485(4wire)
Speed	9600
Data Length	C 7 C 8
Parity	NONE C EVEN C ODD
Stop Bit	
Flow Control	NONE O ER(DTR/CTS) O XON/XOFF
Timeout	3
Retry	2
Wait To Send	0 (ms)
RI / VCC	● RI C VCC
In the case of RS or VCC (5V Powe Isolation Unit, ple	I2C, you can select the 9th pin to RI (Input) Supply). If you use the Digital's RS232C e select it to VCC. Default
Device-Specific Settings	
Allowable No. of De	ce/PLCs 16 Unit(s) 📊
No. Device N	ne Settings
I PLUI	Joenes=ncA-rouu,Device Address=0

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-F	2300 💌
Device Address	0	÷
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the SET, MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. Press the SET key for 2 seconds to change from PV display mode to engineer setting mode. Parameter group is displayed.
- 2. Press the Up/Down keys to display the parameter group, "PG60."
- 3. Press the SET Key to display setting item. Every time the SET Key is depressed, item to be set switches.
- 4. Press the Up/Down keys to select set value, and press the SET Key.
- 5. Press the Reset key to reset the external device.
- 6. Press the Monitor/Mode key and the SET key at the same time to move to SETUP setting mode.
- 7. Press the SET key several times to display Add.
- 8. Press the Up/Down keys to select set value, and press the SET key.
- 9. Press the RUN/HOLD key to move to operation monitor mode.

Setting value

Engineer setting mode

bPS	2
bIT	0

SETUP setting mode

Add	0



3.30 Setting Example 30

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Summary Change Device/PLC
Maker RKC INSTRUMENT INC. Driver Temperature Controller Port COM1
Text Data Mode 2 Change
Communication Settings
SIO Type O RS232C O RS422/485(2wire) 💿 RS422/485(4wire)
Speed 9600 💌
Data Length 🔿 7 💿 8
Parity © NONE O EVEN O ODD
Stop Bit
Flow Control O NONE O ER(DTR/CTS) O XON/XOFF
Timeout 3 💼 (sec)
Retry 2 🕂
Wait To Send 0 👘 (ms)
RI / VCC © RI O VCC
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.
Device-Specific Settings
Allowable No. of Device/PLCs 16 Unit(s)
No. Device Name Settings No. Device Name Settings I PLC1 Image: Settings Settings

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-F	°300 💌
Device Address	0	-
		Default
OK (<u>O</u>)		Cancel

Communication setting of the external device is set with the SET, MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Press the SET key for 2 seconds to change from PV display mode to engineer setting mode. Parameter group is displayed.
- 2. Press the Up/Down keys to display the parameter group, "PG60."
- 3. Press the SET Key to display setting item. Every time the SET Key is depressed, item to be set switches.
- 4. Press the Up/Down keys to select set value, and press the SET Key.
- 5. Press the Reset key to reset the external device.
- 6. Press the Monitor/Mode key and the SET key at the same time to move to SETUP setting mode.
- 7. Press the SET key several times to display Add.
- 8. Press the Up/Down keys to select set value, and press the SET key.
- 9. Press the RUN/HOLD key to move to operation monitor mode.

Setting value

Engineer setting mode

bPS	2
bIT	0

SETUP setting mode

Add	0



3.31 Setting Example 31

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Summary Change Device/PLC Maker RKC INSTRUMENT INC. Driver Temperature Controller Port COM1 Text Data Mode 2 Change Change Comparison Comparison
Maker RKC INSTRUMENT INC. Driver Temperature Controller Port COM1 Text Data Mode 2 Change
Text Data Mode 2 Change
Communication Settings
SIO Type C RS232C © RS422/485(2wire) C RS422/485(4wire)
Speed 9600
Data Length O 7 💿 8
Parity © NONE © EVEN © DDD
Stop Bit 💿 1 💿 2
Flow Control © NONE C ER(DTR/CTS) C XON/XOFF
Timeout 3 🚔 (sec)
Retry 2 🕂
Wait To Send 🛛 🔭 (ms)
RI / VCC © RI O VCC
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC. Default
Device-Specific Settings
Allowable No. of Device/PLCs 16 Unit(s)
No. Device Name Settings V 1 PLC1 Image: Series=BEX-P300 Device Address=0

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-F	2300 💌
Device Address	0	÷
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the SET, MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Press the SET key for 2 seconds to change from PV display mode to engineer setting mode. Parameter group is displayed.
- 2. Press the Up/Down keys to display the parameter group, "PG60."
- 3. Press the SET Key to display setting item. Every time the SET Key is depressed, item to be set switches.
- 4. Press the Up/Down keys to select set value, and press the SET Key.
- 5. Press the Reset key to reset the external device.
- 6. Press the Monitor/Mode key and the SET key at the same time to move to SETUP setting mode.
- 7. Press the SET key several times to display Add.
- 8. Press the Up/Down keys to select set value, and press the SET key.
- 9. Press the RUN/HOLD key to move to operation monitor mode.

Setting value

Engineer setting mode

bPS	2
bIT	0

SETUP setting mode

Add	0


3.32 Setting Example 32

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1				
Summary				Change Device/PLC
Maker RKC INSTR	UMENT INC.	Driver Te	emperature Controller	Port COM1
Text Data Mode	2 Change			
Communication Settings				
SIO Type	• RS232C	C RS422/485(2w	ire) 🔿 RS422/485(4wire)	
Speed	4800	-		
Data Length	• 7	C 8		
Parity	C NONE	C EVEN	• ODD	
Stop Bit	O 1	● 2		
Flow Control	💿 NONE	C ER(DTR/CTS)	O XON/XOFF	
Timeout	3	(sec)		
Retry	2 📫			
Wait To Send	0 ÷	(ms)		
RI / VCC	• BI	O VCC		
In the case of RS2 or VCC (5V Power Isolation Unit, pleas	32C, you can sele Supply). If you us se select it to VCC.	ct the 9th pin to RI (In e the Digital's RS232I	put) C Default	
Device-Specific Settings				
Allowable No. of Dev	rice/PLCs 16 Uni	t(s) 📷		
No. Device Na	me	Settings	3FX.P250 Device Address=0	
		HUL JUENES-I	TEAT 200,0 CHOC Address=0	

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-P	250 💌
Device Address	0	÷
		Default
OK (<u>O)</u>		Cancel

Communication setting of the external device is set with the SET, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While lifting up the stopper located at the lower section of the external device with a finger, pull and remove it from the case.
- 2. Turn on the internal switch A at upper external device and put it back in the case.
- 3. Press the SET key to display the item to be set, and select the set contents with the Up/Down keys. Stop bit, data bit, and parity bit are displayed in a 3 digit character string at the setting item, bIT, so touch each one's digit, ten's digit, and hundred's digit on the SV indicator, and select the set contents with the Up/Down keys.
- 4. Press the SET key to set the set contents.
- 5. Remove the external device form the case, turn OFF the internal switch A mentioned in 2 above, and return it to the case.

Setting value

bPS	4800
bIT	o72
Add	0

NOTE

3.33 Setting Example 33

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1					
Summary			Change Device/PLC	ļ	
Maker RKC INST	Maker RKC INSTRUMENT INC. Driver Temperature Controller Port COM1				
Text Data Mode	2 Change				
Communication Settings					
SIO Type	O RS232C	C RS422/485(2w	wire) • RS422/485(4wire)		
Speed	4800	-			
Data Length	• 7	C 8			
Parity	O NONE	C EVEN	© ODD		
Stop Bit	0.1	2			
Flow Control	O NONE	C ER(DTR/CTS)) C XON/XOFF		
Timeout	3 📫	(sec)			
Retry	2 +				
Wait To Send	0 🕂	(ms)			
RI / VCC	© BI	O VCC			
In the case of RS3 or VCC (5V Power Isolation Unit, plea	232C, you can sele Supply). If you us	et the 9th pin to RI (In e the Digital's RS232	Input) I2C		
Isolation onic, piec			Default		
Device-Specific Settings					
Allowable No. of De No. Device N	vice/PLUs 16 Uni ame	t(s) 🛄 Settinas			
👗 1 PLC1		Series=F	=REX-P250,Device Address=0		

♦ Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-F	°250 💌
Device Address	0	•
		Default
OK (<u>O</u>)		Cancel

Communication setting of the external device is set with the SET, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- 1. While lifting up the stopper located at the lower section of the external device with a finger, pull and remove it from the case.
- 2. Turn on the internal switch A at upper external device and put it back in the case.
- 3. Press the SET key to display the item to be set, and select the set contents with the Up/Down keys. Stop bit, data bit, and parity bit are displayed in a 3 digit character string at the setting item, bIT, so touch each one's digit, ten's digit, and hundred's digit on the SV indicator, and select the set contents with the Up/Down keys.
- 4. Press the SET key to set the set contents.
- 5. Remove the external device form the case, turn OFF the internal switch A mentioned in 2 above, and return it to the case.

Setting value

bPS	4800
bIT	o72
Add	0

NOTE

3.34 Setting Example 34

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKCINSTRUMENT	INC. Driver Temperature Controller Port COM1
Text Data Mode 2	hange
Communication Settings	
SIO Type 🛛 C RS	232C 🔿 RS422/485(2wire) 💿 RS422/485(4wire)
Speed 9600	
Data Length 🛛 🔿 7	• 8
Parity 💿 NC	NE O EVEN O ODD
Stop Bit 📀 1	© 2
Flow Control 💿 NC	NE O ER(DTR/CTS) O XON/XOFF
Timeout 3	(sec)
Retry 2	
Wait To Send 0	(ms)
RI / VCC C RI	O VCC
In the case of RS232C, you or VCC (5V Power Supply). Isolation Unit, please select	can select the 9th pin to RI (Input) If you use the Digital's RS232C it to VCC. Default
Device-Specific Settings	
Allowable No. of Device/PLC:	3 16 Unit(s) 🔢
No. Device Name	Settings

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-4	AD 💌
Device Address	0	* *
		Default
OK (<u>0)</u>		Cancel

Communication setting of the external device is set with the SEL, MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Depress the SEL key for 2 seconds to change from PV display mode to engineer setting mode. Parameter group is displayed.
- 2. Press the Up/Down keys to display the parameter group, "PG9."
- 3. Press the SEL key to display the setting item. Every time the SEL key is depressed, setting item switches.
- 4. Press the Up/Down keys to display the setting value.
- 5. Press the Up/Down keys to select the setting value, and press the SEL key.
- 6. Press the Monitor/Mode key to switch to the PV display mode.
- 7. Press the Monitor/Mode key and the SEL key at the same time to change from PV display mode to SETUP setting mode.
- 8. Press the SEL key several times to display Add.
- 9. Press the Up/Down keys to display the setting value.
- 10. Press the Up/Down keys to display the setting value.
- 11. Press the Monitor/Mode keys to switch to the PV display mode.

Setting value

Engineer setting mode

8	
bPS	3
bIT	0

SETUP setting mode





3.35 Setting Example 35

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1
Summary Change Device/PLC
Maker RKC INSTRUMENT INC. Driver Temperature Controller Port COM1
Text Data Mode 2 Change
Communication Settings
SIO Type O RS232C O RS422/485(2wire) O RS422/485(4wire)
Speed 9600
Data Length C 7 💿 8
Parity © NONE O EVEN O ODD
Stop Bit 💿 1 🔿 2
Flow Control C NONE O ER(DTR/CTS) O XON/XOFF
Timeout 3 🚔 (sec)
Retry 2
Wait To Send 0 🔆 (ms)
RI / VCC © RI O VCC
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC. Default
Device-Specific Settings
Allowable No. of Device/PLCs 16 Unit(s)
No. Device Name Settings No. Device Name Settings I PLC1 Image: Settings Settings

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX	.D 💌
Device Address	0	-
		Default
OK (<u>0</u>)		Cancel

Communication setting of the external device is set with the SEL, MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Depress the SEL key for 2 seconds to change from PV display mode to engineer setting mode. Parameter group is displayed.
- 2. Press the Up/Down keys to display the parameter group, "PG9."
- 3. Press the SEL key to display the setting item. Every time the SEL key is depressed, setting item switches.
- 4. Press the Up/Down keys to display the setting value.
- 5. Press the Up/Down keys to select the setting value, and press the SEL key.
- 6. Press the Monitor/Mode key to switch to the PV display mode.
- 7. Press the Monitor/Mode key and the SEL key at the same time to change from PV display mode to SETUP setting mode.
- 8. Press the SEL key several times to display Add.
- 9. Press the Up/Down keys to display the setting value.
- 10. Press the Up/Down keys to display the setting value.
- 11. Press the Monitor/Mode keys to switch to the PV display mode.

Setting value

Engineer setting mode

8	
bPS	3
bIT	0

SETUP setting mode





3.36 Setting Example 36

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC1
Summary Change Device/PLC
Maker RKC INSTRUMENT INC. Driver Temperature Controller Port COM1
Text Data Mode 2 Change
Communication Settings
SID Type O RS232C O RS422/485(2wire) 💿 RS422/485(4wire)
Speed 9600 💌
Data Length 🔘 7 💿 8
Parity © NONE C EVEN C ODD
Stop Bit 💿 1 💿 2
Flow Control © NONE O ER(DTR/CTS) O XON/XOFF
Timeout 3 📑 (sec)
Retry 2
Wait To Send 0 🕂 (ms)
RI / VCC O RI O VCC
In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.
Device-Specific Settings
Allowable No. of Device/PLCs 16 Unit(s)
No. Device Name Settings X 1 PLC1 Figure 3

Device Setting

💰 Individual	Device	e Settings 🗙
PLC1		
Series	REX	PG 💌
Device Address	0	*
		Default
OK (<u>O)</u>		Cancel

Communication setting of the external device is set with the SEL, MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Depress the SEL key for 2 seconds to change from PV display mode to engineer setting mode. Parameter group is displayed.
- 2. Press the Up/Down keys to display the parameter group, "PG6."
- 3. Press the SEL key to display the setting item. Every time the SEL key is depressed, setting item switches.
- 4. Press the Up/Down keys to display the setting value.
- 5. Press the Up/Down keys to select the setting value, and press the SEL key.
- 6. Press the Monitor/Mode key to switch to the PV display mode.
- 7. Press the Monitor/Mode key and the SEL key at the same time to change from PV display mode to SETUP setting mode.
- 8. Press the SEL key several times to display Add.
- 9. Press the Up/Down keys to display the setting value.
- 10. Press the Up/Down keys to display the setting value.
- 11. Press the Monitor/Mode keys to switch to the PV display mode.

Setting value

Engineer setting mode

8	
bPS	3
bIT	0

SETUP setting mode





3.37 Setting Example 37

Settings of GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKC INSTRU	MENT INC. Driver Temperature Controller Port COM1
Text Data Mode 🛛	2 Change
Communication Settings	
SIO Type	C RS232C C RS422/485(2wire) C RS422/485(4wire)
Speed	9600
Data Length	C 7 • 8
Parity	O NONE C EVEN C ODD O
Stop Bit	
Flow Control	C NONE C ER(DTR/CTS) C XON/XOFF
Timeout	3 📑 (sec)
Retry	2 📑
Wait To Send	0 <u>*</u> (ms)
RI / VCC	© RI O VCC
In the case of RS23; or VCC (5V Power S Isolation Unit, please	2C, you can select the 9th pin to RI (Input) jupply). If you use the Digital's RS232C select it to VCC. Default
Device-Specific Settings	
Allowable No. of Devic	ze/PLCs 16 Unit(s)
No. Device Nam	e Settings

Device Setting

💰 Individual	Device	Settings 🗙
PLC1		
Series	REX-F	°G 💌
Device Address	0	•
		Default
OK (<u>O)</u>		Cancel

Communication setting of the external device is set with the SEL, MODE, UP and Down keys located on the front face of the temperature controller.

Please refer to the temperature controller manual for details.

Procedure

- Depress the SEL key for 2 seconds to change from PV display mode to engineer setting mode. Parameter group is displayed.
- 2. Press the Up/Down keys to display the parameter group, "PG9."
- 3. Press the SEL key to display the setting item. Every time the SEL key is depressed, setting item switches.
- 4. Press the Up/Down keys to display the setting value.
- 5. Press the Up/Down keys to select the setting value, and press the SEL key.
- 6. Press the Monitor/Mode key to switch to the PV display mode.
- 7. Press the Monitor/Mode key and the SEL key at the same time to change from PV display mode to SETUP setting mode.
- 8. Press the SEL key several times to display Add.
- 9. Press the Up/Down keys to display the setting value.
- 10. Press the Up/Down keys to display the setting value.
- 11. Press the Monitor/Mode keys to switch to the PV display mode.

Setting value

Engineer setting mode

0 0	
bPS	3
bIT	0

SETUP setting mode





3.38 Setting Example 38

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1	
Summary	Change Device/PLC
Maker RKC INSTRUMENT INC.	Driver Temperature Controller Port COM1
Text Data Mode 2 Change	2
Communication Settings	
SIO Type 💿 RS232C	C RS422/485(2wire) C RS422/485(4wire)
Speed 9600	•
Data Length 📀 7	© 8
Parity NONE	O EVEN O ODD
Stop Bit 💿 1	O 2
Flow Control 💿 NONE	O ER(DTR/CTS) O XON/XOFF
Timeout 3	t (sec)
Retry 2	
Wait To Send 0	a (ms)
RI / VCC RI	C VCC
In the case of RS232C, you can s or VCC (5V Power Supply). If you Isolation Unit, please select it to V	elect the 9th pin to RI (Input) use the Digital's RS232C CC. Default
Device-Specific Settings	
Allowable No. of Device/PLCs 161	Jnit(s)
No. Device Name	Settings
👗 1 PLC1	[]] [Series=SR-Mini-HG(H-PCP-A/B),Device Address=0

Device Setting

💰 Individual Device Settings 🛛 🗙				
PLC1				
Series	SR-Mini-H	G(H-PCP-A/B 🔻		
Device Address	0	* *		
		Default		
ОК	. (1)	Cancel		

Communication setting of the external device is set with the slave address setting switch on the front face of the temperature controller and the dip switch in the temperature controller. Please refer to the temperature controller manual for details.

Procedure

- 1. Set slave address for the host link with the slave address setting switch on the front face of the temperature controller.
- 2. Remove the temperature controller from the mother block and set communication speed and data construction with the dip switch in the temperature controller.

Setting value

Slave address setting switch

Upper Digit Setting	0
Lower Digit Setting	0

Dip switch

Dip switch	Setting	Discription	
1	ON	Data construction	
2	ON	Data construction	
3	ON	Communication spee	
4	OFF	Communication speed	

NOTE

3.39 Setting Example 39

- Settings of GP-Pro EX
- Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1				
Summary				Change Device/PLC
Maker RKCINSTRL	JMENT INC.	Driver Tem	perature Controller	Port COM1
Text Data Mode	2 Change			
Communication Settings				
SIO Type	C RS232C	C RS422/485(2wire) 💿 RS422/485(4wire)	
Speed	9600	•		
Data Length	O 7	• 8		
Parity	NONE	C EVEN	O ODD	
Stop Bit	● 1	C 2		
Flow Control	O NONE	C ER(DTR/CTS)	C XON/XOFF	
Timeout	3 📑 (sec)		
Retry	2 📫			
Wait To Send	0 🔅 (ms)		
RI / VCC	© BI	O VCC		
In the case of RS23 or VCC (5V Power S	2C, you can select Supply). If you use	t the 9th pin to RI (Inpu the Digital's RS232C	it]	
Isolation Unit, please	e select it to VLL.		Defau	lt
Device-Specific Settings				
Allowable No. of Devic No. Device Nam	ce/PLCs 16 Unit) ne	s) 🛄 Settings		
1 PLC1	10	Series=SR	-Mini-HG(H-PCP-A/B),Device	Address=0

♦ Device Setting

💰 Individual Device Settings 🛛 🗙				
PLC1				
Series	SR-Mini-H	G(H-PCP-A/B 🔻		
Device Address	0	* *		
		Default		
ОК	. (1)	Cancel		

Communication setting of the external device is set with the slave address setting switch on the front face of the temperature controller and the dip switch in the temperature controller. Please refer to the temperature controller manual for details.

Procedure

- 1. Set slave address for the host link with the slave address setting switch on the front face of the temperature controller.
- 2. Remove the temperature controller from the mother block and set communication speed and data construction with the dip switch in the temperature controller.

Setting value

Slave address setting switch

Upper Digit Setting	0
Lower Digit Setting	0

Dip switch

Dip switch Setting		Discription	
1	ON	Data construction	
2	ON	Data construction	
3	ON	Communication speed	
4	OFF	Communication speed	

NOTE

4 Setup Items

Set communication settings of the Display with GP-Pro EX or in off-line mode of the Display. The setting of each parameter must be identical to that of External Device.

"3 Example of Communication Setting" (page 11)

4.1 Setup Items in GP-Pro EX

Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Devi	ce/PLC 1			
Sun	nmary		Change Device/PLC	
	Maker RKCINSTR	UMENT INC.	Driver Temperature Controller Port COM1	1
	Text Data Mode	2 Change		
Con	nmunication Settings			
	SIO Type	RS232C	O RS422/485(2wire) O RS422/485(4wire)	
	Speed	19200	v	
	Data Length	C 7	© 8	
	Parity	NONE	O EVEN O ODD	
	Stop Bit	• 1	© 2	
	Flow Control	O NONE	O ER(DTR/CTS) O XON/XOFF	
	Timeout	3 📫 (s	(sec)	
	Retry	2 🔹		
	Wait To Send	1) <mark>÷</mark> (1	ms)	
	RI / VCC	BI B	O VCC	
	In the case of RS2 or VCC (5V Power Isolation Unit, pleas	32C, you can selec Supply). If you use e select it to VCC.	ct the 9th pin to RI (Input) e the Digital's RS232C Default	
Dev	vice-Specific Settings			
	Allowable No. of Dev	ice/PLCs 16 Unit((s) 📊	
	No. Device Na	me	Settings	
	M PLUI			

Setup Items	Setup Description		
SIO Type	Select the SIO type to communicate with the External Device.		
Speed	Select speed between the External Device and the Display.		
Data Length	Select data length.		
Parity	Select how to check parity.		
Stop Bit	Select stop bit length.		
Flow Control	Display the communication control method to prevent overflow of transmission and reception data.		
Timeout	Use an integer from 1 to 127 to enter the time (s) for which the Display waits for the response from the External Device.		
Retry	In case of no response from the External Device, use an integer from 0 to 255 to enter how many times the Display retransmits the command.		
Wait To Send	Use an integer from 0 to 255 to enter standby time (ms) for the Display from receiving packets to transmitting next commands.		
RI/VCC	You can switch RI/VCC of the 9th pin when you select RS232C for SIO type. It is necessary to change RI/5V by changeover switch of IPC when connect with IPC. Please refer to the manual of the IPC for more detail.		

Device Setting

o display the setting screen, click III ([Setting]) of External Device you want to set from [Device-Specific Settings] of [Device/PLC Settings].

When you connect multiple External Device, click if from [Device-Specific Settings] of [Device/PLC Settings] to add another External Device.

💰 Individual	Device	Settings 🗙
PLC1		
Series	FB	•
Device Address	0	•
		Default
OK (<u>O</u>)		Cancel

Setup Items	Setup Description
Series	Select the External Device series.
Device Address	Enter the address of the External Device, using 0 to 99.

4.2 Setup Items in Off-Line Mode

NOTE

• Please refer to Maintenance/Troubleshooting for more information on how to enter off-line mode or about operation.

Cf. Maintenance/Troubleshooting "2.2 Offline Mode"

Communication Settings

To display the setting screen, touch [Device/PLC Settings] from [Peripheral Settings] in off-line mode. Touch the External Device you want to set from the displayed list.

Comm.	Device	Option	,	
		,		/
Temperature Cor	itroller		[COM1]	Page 1/1
	SIO Type Speed Data Length Parity Stop Bit Flow Control Timeout(s) Retry Wait To Send(ms)	RS232C 9600 7 • NONE 1 NONE	● 8 ● EVEN ● 2 ■ 3 ■ ● ● ● ●	ODD
	Exit		Back	2006/03/09 16:58:58

Setup Items	Setup Description			
	Select the SIO type to communicate with the External Device.			
SIO Type	To make the communication settings correctly, confirm the serial interface specifications of Display unit for [SIO Type]. We cannot guarantee the operation if a communication type that the serial interface does not support is specified. For details concerning the serial interface specifications, refer to the manual for Display unit.			
Speed	Select speed between the External Device and the Display.			
Data Length	Select data length.			
Parity	Select how to check parity.			
Stop Bit	Select stop bit length.			
Flow Control	Display the communication control method to prevent overflow of transmission and reception data.			
Timeout	Use an integer from 1 to 127 to enter the time (s) for which the Display waits for the response from the External Device.			
Retry	In case of no response from the External Device, use an integer from 0 to 255 to enter how many times the Display retransmits the command.			

Setup Items	Setup Description
Wait To Send	Use an integer from 0 to 255 to enter standby time (ms) for the Display from receiving packets to transmitting next commands.

Device Setting

To display the setting screen, touch [Device/PLC Settings] from [Peripheral Settings]. Touch the External Device you want to set from the displayed list, and touch [Device].

Comm.	Device	Option		<i></i>
<i>.</i>				<i>1</i>
Temperature Con	troller		[COM1]	Page 1/1
Devic	e/PLC Name PLC1			
	Series	CB		
	Device Address		0 💌 🔺	j
	Exit		Back	2006/03/09 16:59:00

Setup Items	Setup Description		
Device/PLC Name	Select the External Device for device setting. Device name is a title of External Device set with GP-Pro EX.(Initial value [PLC1])		
Series	Select the External Device series.		
Device Address	Enter the address of the External Device, using 0 to 99.		

Option

To display the setting screen, touch [Device/PLC Settings] from [Peripheral Settings]. Touch the External Device you want to set from the displayed list, and touch [Option].

Comm,	Device	Option		,
<i></i>	/		/	7
Temperature Con	troller RI / VCC In the case the 9th pin Power Suppl RS232C Isol it to VCC.	 RI of RS232C, you to RI(Input) or y). If you use th ation Unit, plea 	[COM1] o VCC can select VCC(5V e Digital's se select	Page 1/1
	Exit		Back	2006/03/09 16:59:02

Setup Items	Setup Description
RI/VCC	You can switch RI/VCC of the 9th pin when you select RS232C for SIO type. It is necessary to change RI/5V by changeover switch of IPC when connect with IPC. Please refer to the manual of the IPC for more detail.

5 Cable Diagram

The cable diagram shown below may be different from the cable diagram recommended by RKC INSTRUMENT INC. Please be assured there is no operational problem in applying the cable diagram shown in this manual.

- The FG pin of the External Device body must be D-class grounded. Please refer to the manual of the External Device for more details.
- SG and FG are connected inside the Display. When connecting SG to the External Device, design the system not to form short-circuit loop.
- Connect the isolation unit, when communication is not stabilized under the influence of a noise etc..
- When connecting with RS422/485 (2 wire) or RS422/485 (4 wire), up to 16 units of temperature controllers can be connected. However, when connecting FB400/900 series with RS422/485 (4 wire), only up to 15 units can be connected.

Cable Diagram 1

Display (Connection Port)		Cable	Notes
GP ^{*1} (COM1) AGP-3302B (COM2) ST ^{*2} (COM2)	А	COM port conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	
	В	Your own cable	
GP*3 (COM2)	С	Online adapter by Pro-face CA4-ADPONL-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	The cable length must be 600m or less.
	D	Online adapter by Pro-face CA4-ADPONL-01 + Your own cable	
IPC ^{*4}	Е	COM port conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	
	F	Your own cable	

*1 All GP models except AGP-3302B

*2 All ST models except AST-3211A

- *3 All GP models except GP-3200 series and AGP-3302B
- *4 Only the COM port which can communicate by RS-422/485 (2 wire) can be used.

COM Port of IPC (page 8)

- A) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection



1:n Connection



B) When using your own cable



1:n Connection



C) When using the online adapter (CA4-ADPONL-01), the terminal block conversion adapter (CA3-ADPTRM-

01) by Pro-face and your own cable

1:1 Connection



1:n Connection



D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable



• 1:n Connection



E) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable

• 1:1 Connection



1:n Connection



F) When using your own cable





Cable Diagram 2

Display (Connection Port)	Cable	Notes
GP (COM1) ST (COM1) IPC ^{*1}	Your own cable	The cable length must be 15m or less.



Cable Diagram 3

Display (Connection Port)	Cable		Notes
GP ^{*1} (COM1) AGP-3302B (COM2) ST ^{*2} (COM2) IPC ^{*3}	А	COM port conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	ace D-face
	В	Your own cable	
GP ^{*4} (COM2)	С	Online adapter by Pro-face CA4-ADPONL-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	The cable length must be 600m or less.
	D	Online adapter by Pro-face CA4-ADPONL-01 + Your own cable	

*1 All GP models except AGP-3302B

*2 All ST models except AST-3211A

- *3 Only the COM port which can communicate by RS-422/485 (4 wire) can be used.
 Image: Image COM Port of IPC (page 8)
- *4 All GP models except GP-3200 series and AGP-3302B

A) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter

(CA3-ADPTRM-01) by Pro-face and your own cable



• 1:n Connection



B) When using your own cable

• 1:1 Connection



1:n Connection



C) When using the online adapter (CA4-ADPONL-01), the terminal block conversion adapter (CA3-ADPTRM-

- 01) by Pro-face and your own cable
- 1:1 Connection



1:n Connection



D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable

1:1 Connection •



R(A)

SG

Your own cable

R(A)

SG

120Ω (1/2W)

SDB

SG

TERMTX

FG

8

5

9

Shell

Termination

120Ω (1/2W)

resistance

Cable Diagram 4

Display (Connection Port)		Cable	Notes
GP ^{*1} (COM1) AGP-3302B (COM2) ST ^{*2} (COM2) IPC ^{*3}	А	COM port conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	
	В	Your own cable	
GP ^{*4} (COM2)	С	Online adapter by Pro-face CA4-ADPONL-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	The cable length must be 5m or less.
	D	Online adapter by Pro-face CA4-ADPONL-01 + Your own cable	

*1 All GP models except AGP-3302B

*2 All ST models except AST-3211A

•

*3 Only the COM port which can communicate by RS-422/485 (4 wire) can be used.
 Image: Image COM Port of IPC (page 8)

*4 All GP models except GP-3200 series and AGP-3302B

A) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable

1:1 Connection



• 1:n Connection



NOTE

• Terminal resistance is not required.

B) When using your own cable

• 1:1 Connection



• 1:n Connection



NOTE • Terminal resistance is not required.

- C) When using the online adapter (CA4-ADPONL-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection



1:n Connection



- D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable
- 1:1 Connection





Cable Diagram 5

Display (Connection Port)		Cable	Notes
GP ^{*1} (COM1) AGP-3302B (COM2) ST ^{*2} (COM2)	A	COM port conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	
	В	Your own cable	
GP ^{*3} (COM2)	С	Online adapter by Pro-face CA4-ADPONL-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	The cable length must be 5m or less.
	D	Online adapter by Pro-face CA4-ADPONL-01 + Your own cable	
IPC ^{*4}	Е	COM port conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	
	F	Your own cable	

*1 All GP models except AGP-3302B

*2 All ST models except AST-3211A

*3 All GP models except GP-3200 series and AGP-3302B

*4 Only the COM port which can communicate by RS-422/485 (2 wire) can be used.

COM Port of IPC (page 8)

- A) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection




B) When using your own cable

• 1:1 Connection





- C) When using the online adapter (CA4-ADPONL-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection





D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable



```
NOTE • Terminal resistance is not required.
```

- E) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection





NOTE • Terminal resistance is not required.

F) When using your own cable

• 1:1 Connection



• 1:n Connection



NOTE • Terminal resistance is not required.

Display (Connection Port)		Cable	Notes
GP ^{*1} (COM1) AGP-3302B (COM2) ST ^{*2} (COM2) IPC ^{*3}	А	COM port conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	
	В	Your own cable	
GP ^{*4} (COM2)	С	Online adapter by Pro-face CA4-ADPONL-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	The cable length must be 5m or less.
	D	Online adapter by Pro-face CA4-ADPONL-01 + Your own cable	

*1 All GP models except AGP-3302B

*2 All ST models except AST-3211A

- *3 Only the COM port which can communicate by RS-422/485 (4 wire) can be used.
 Image: Image COM Port of IPC (page 8)
- *4 All GP models except GP-3200 series and AGP-3302B
 - A) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
 - 1:1 Connection



1:n Connection



B) When using your own cable

• 1:1 Connection



• 1:n Connection



NOTE

•

Terminal resistance is not required.

- C) When using the online adapter (CA4-ADPONL-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection





Terminal resistance is not required. NOTE

D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable

• 1:1 Connection



Your own cable



Display (Connection Port)		Cable	Notes
GP ^{*1} (COM1) AGP-3302B (COM2) ST ^{*2} (COM2)	А	COM port conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	
	В	Your own cable	
GP ^{*3} (COM2)	С	Online adapter by Pro-face CA4-ADPONL-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	The cable length must be 5m or less.
	D	Online adapter by Pro-face CA4-ADPONL-01 + Your own cable	
IPC ^{*4}	Е	COM port conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	
	F	Your own cable	

*1 All GP models except AGP-3302B

*2 All ST models except AST-3211A

*3 All GP models except GP-3200 series and AGP-3302B

*4 Only the COM port which can communicate by RS-422/485 (2 wire) can be used.

COM Port of IPC (page 8)

- A) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection





B) When using your own cable

• 1:1 Connection



1:n Connection ٠



NOTE

Terminal resistance is not required.

- C) When using the online adapter (CA4-ADPONL-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection





NOTE

٠

٠

Terminal resistance is not required.

- D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable
- 1:1 Connection





NOTE • Terminal resistance is not required.

- E) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection





NOTE • Terminal resistance is not required.

F) When using your own cable

• 1:1 Connection



• 1:n Connection



NOTE

٠

Terminal resistance is not required.

Display (Connection Port)		Cable	Notes
GP ^{*1} (COM1) AGP-3302B (COM2) ST ^{*2} (COM2) IPC ^{*3}	A Terminal block conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable		
	В	Your own cable	
GP ^{*4} (COM2)	С	Online adapter by Pro-face CA4-ADPONL-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	The cable length must be 500m or less.
	D	Online adapter by Pro-face CA4-ADPONL-01 + Your own cable	

*1 All GP models except AGP-3302B

*2 All ST models except AST-3211A

- *4 All GP models except GP-3200 series and AGP-3302B

- A) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection





B) When using your own cable

1:1 Connection



1:n Connection



- C) When using the online adapter (CA4-ADPONL-01), the terminal block conversion adapter (CA3-ADPTRM-
 - 01) by Pro-face and your own cable
- 1:1 Connection





D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable

• 1:1 Connection



Your own cable



Display (Connection Port)		Cable	Notes	
GP ^{*1} (COM1) AGP-3302B (COM2) ST ^{*2} (COM2)	A Terminal block conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable			
	В	Your own cable		
GP ^{*3} (COM2)	С	Online adapter by Pro-face CA4-ADPONL-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	The cable length must be 600m or less.	
	D	Online adapter by Pro-face CA4-ADPONL-01 + Your own cable		
IPC ^{*4}	Е	COM port conversion adapter by Pro-face CA3-ADPCOM-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable		
	F	Your own cable		

*1 All GP models except AGP-3302B

*2 All ST models except AST-3211A

*3 All GP models except GP-3200 series and AGP-3302B

*4 Only the COM port which can communicate by RS-422/485 (2 wire) can be used.

COM Port of IPC (page 8)

- A) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection





- B) When using your own cable
- 1:1 Connection





- C) When using the online adapter (CA4-ADPONL-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection





D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable

• 1:1 Connection





- E) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection





Your own cable

F) When using your own cable

• 1:1 Connection





Display (Connection Port)		Cable	Notes
GP ^{*1} (COM1) AGP-3302B (COM2) ST ^{*2} (COM2) IPC ^{*3}	A Terminal block conversion adapter by Pro-face CA3-ADPCOM-01 + A Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable		
	В	Your own cable	
GP ^{*4} (COM2)	С	Online adapter by Pro-face CA4-ADPONL-01 + Terminal block conversion adapter by Pro-face CA3-ADPTRM-01 + Your own cable	The cable length must be 600m or less.
	D	Online adapter by Pro-face CA4-ADPONL-01 + Your own cable	

*1 All GP models except AGP-3302B

*2 All ST models except AST-3211A

- *3 Only the COM port which can communicate by RS-422/485 (4 wire) can be used.
 Image: Image COM Port of IPC (page 8)
- *4 All GP models except GP-3200 series and AGP-3302B
 - A) When using the COM port conversion adapter (CA3-ADPCOM-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
 - 1:1 Connection



1:n Connection



B) When using your own cable

• 1:1 Connection



1:n Connection



- C) When using the online adapter (CA4-ADPONL-01), the terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable
- 1:1 Connection





Your own cable

- D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable
- 1:1 Connection



Your own cable



Display (Connection Port)	Cable	Notes
GP (COM1) ST (COM1) IPC ^{*1}	Your own cable	The cable length must be 15m or less.

*1 Only the COM port which can communicate by RS-232C can be used. ☞ ■ COM Port of IPC (page 8)



Display (Connection Port)	Cable	Notes
GP (COM1) ST (COM1) IPC ^{*1}	Your own cable	The cable length must be 15m or less.

*1 Only the COM port which can communicate by RS-232C can be used. ☞ ■ COM Port of IPC (page 8)



6 Supported Device

Range of supported device address is shown in the table below. Please note that the actually supported range of the devices varies depending on the External Device to be used. Please check the actual range in the manual of your connecting equipment.

Input address of external device in the dialog below.



 Channel number Select the channel number of external device. It can be selected when SR Mini HG(H-PCP-A/B) and SR Mini HG(H-PCP-J) are used.
 Reference The list of available identifiers is displayed. When clicking the identifier to be used and pressing "Select," the address is inputted.
 Address is set.

Combination of identifier and address differs per external device. Please refer to the list of identifiers.

- 4. Decimal digit number Decimal digit number of data is set.
 - When reading out:

Data read out from the temperature controller are dealt as integral number.

e.g. When the value of temperature controller is 100.0;

Value of temperature controller: 100.0 Value indicated by display: 1000

To display decimal points in value indication, set "decimal digit number" of "display data form." In the case of the example above, the decimal digit number is the first decimal place, so set "1."

- e.g. When the value of temperature controller is 100.0;
 - Value of temperature controller: 100.0

Value indicated by Diaplay: 100.0

The decimal point position is internally processed depending on the specified address. Specified same as the address on the device list: No decimal point Specified by adding 0x1000 to the address on the device list

: One digit after decimal point.

Specified by adding 0x2000 to the address on the device list

: Two digit after decimal point.

Specified by adding 0x3000 to the address on the device list

: Three digit after decimal point.

		Data of	display	
Data of temperature controller	Specified same as the address	Specified by adding 0x1000 to the address	Specified by adding 0x2000 to the address	Specified by adding 0x3000 to the address
123	123	1230	12300	23000
123.4	123	1234	12340	23400
12.34	12	123	1234	12340
1.234	1	12	123	1234

GP data are as follows depending on the address specifying method.

* When address specifying method does not match decimal point position of data of temperature controller, truncate the decimal digit number of the specified address or add a zero.

Data are indicated in decadal system and are 6 digits or more, upper level digits are truncated.

■ When writing:

When writing in the temperature controller, value is set in integral number. Decimal point position is internally processed depending on the specified address.

Specified same as the address on the device list: No decimal point Specified by adding 0x1000 to the address on the device list

: One digit after decimal point.

Specified by adding 0x2000 to the address on the device list

: Two digit after decimal point.

Specified by adding 0x3000 to the address on the device list

: Three digit after decimal point.

Example 1) When writing 100.0 in the first alarm setting (A1) of CB series; Address value set by indicator: 0x1007 Written value set by indicator: 1000

Example 2) When writing 100 in the first alarm setting (A1) of CB series; Address value set by indicator: 0x0007 Written value set by indicator: 100

Data written in the temperature controller are as follows depending on the address specifying method.

		Data written in the te	emperature controller	
Data of temperature controller	Specified same as the address	Specified by adding 0x1000 to the address	Specified by adding 0x2000 to the address	Specified by adding 0x3000 to the address
1	1	0.1	0.01	0.001
123	123	12.3	1.23	0.123
1234	1234	123.4	12.34	1.234

* When address specifying method does not match decimal point position of data of temperature controller, truncate the decimal digit number of the specified address or add a zero.

For details of the setting value range or decimal point position of each identifier, please refer to the communication manual of the temperature controller made by RKC INSTRUMENT INC.

CB Series 6.1

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.00-0038.F	0000-0038	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

<Communication identifier list>

Address	Identifier	Description
00	M1	Measured value (PV)
01	M2	Current transformer input 1
02	M3	Current transformer input 2
03	AA	Alarm 1 status
04	AB	Alarm 2 status
05	B1	Burnout
06	S1	Set value (SV)
07	A1	Alarm 1 setting
08	A2	Alarm 2 setting
09	A3	Heater break alarm 1 setting
0A	A4	Heater break alarm 2 setting
0B	A5	Control loop break alarm (LBA) setting
0C	A6	LBA deadband
0D	G1	Autotuning (AT)
0E	G2	Self-tuning (ST)
0F	P1	Heat-side proportional band
10	I1	Integral time
11	D1	Derivative time
12	W1	Anti-reset windup
13	TO	Heat-side proportioning cycle
14	P2	Cool-side proportional band
15	V1	Overlap/deadband
16	T1	Cool-side proportioning cycle
17	PB	PV bias
18	LK	Set data lock function
19	SR	RUN/STOP transfer
1A	ER	Error code
1B	IO	Initialization mode selection
1C	IP	Setting necessary code [Cod]
1D	XI	Input type selection [SL1]
1E	XQ	Engineering unit and cooling type selection [SL2]
1F	LV	Heater break alarm (HBA), control loop break alarm (LBA), special specification, or control loop break alarm (LBA) output selection [SL3]
20	XA	First alarm (ALM1) type or First alarm (ALM1) with hold action selection [SL4]
21	XB	Second alarm (ALM2) type or Second alarm (ALM2) with hold action selection [SL5]

Address	Identifier	Description
22	CA	Control action type selection [SL6]
23	Z1	Energized/de-energized alarm selection, special specification selection 1 [SL7]
24	Z2	Special specification selection 2 [SL8]
25	Z3	Special specification selection 3 [SL9]
26	DH	Option selection [SL10]
27	XC	SV alarm type selection [SL11]
28	XV	Setting limiter (high limit) [SLH]
29	XW	Setting limiter (low limit) [SLL]
2A	XU	Setting the position of decimal point [PGdP]
2B	MH	Differential gap setting of ON/OFF action [oH]
2C	HA	Differential gap setting of first alarm (ALM1) [AH1]
2D	HB	Differential gap setting of second alarm (ALM2) [AH2]
2E	XR	CT ratio setting [CTr]
2F	F1	Digital filter setting [dF]
30	GH	Time factor assumed to be safe [STTM]
31	PU	Factor to calculate proportional band [STPK]
32	IU	Factor to calculate integral time [STIK]
33	IL	Integral time limiter [ILIM]
34	HP	Holding peak ambient temperature [TCJ]
35	UT	Operating time display unit (Upper digits) [WTH]
36	UU	Operating time display unit (Lower digits) [WTL]
37	EB	EEPROM storage mode
38	EM	EEPROM storage state

IMPORT/

Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."

- **NOTE** System area setting that can be used for the temperature controller is reading area size only. Please refer to the GP-Pro EX Reference Manual for system data area.
 - Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
 - Please refer to the precautions on manual notation for icons in the table.

^(C) "Manual Symbols and Terminology"

• Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.2 **FB** Series

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.00-00CD.1F	0000-00CD	<u>[[] H</u>	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

<Communication identifier list>

Address	Identifier	Description		
0	M1	Measured value (PV) monitor		
1	M3	Current transformer 1 (CT1) input value monitor		
2	M4	Current transformer 2 (CT2) input value monitor		
3	MS	Set value (SV) monitor		
4	S2	Remote setting (RS) input value monitor		
5	B1	Burnout state monitor		
6	B2	Burnout state monitor of feedback resistance input		
7	AA	Event 1 state monitor		
8	AB	Event 2 state monitor		
9	AC	Event 3 state monitor		
0A	AD	Event 4 state monitor		
0B	AE	Heater break alarm 1 (HBA1) state monitor		
0C	AF	Heater break alarm 2 (HBA2) state monitor		
0D	01	Manipulated output value (MV1) monitor [heat-side]		
0E	O2	Manipulated output value (MV2) monitor [cool-side]		
0F	ER	Error code		
10	L1	Digital input (DI) state monitor		
11	Q1	Output state monitor		
12	L0	Operation mode state monitor		
13	TR	Memory area soak time monitor		
14	UT	Integrated operating time monitor		
15	Нр	Holding peak value ambient temperature monitor		
16	HM	Power feed forward input value monitor		
17	EM	Backup memory state monitor		
18	VR	ROM version monitor		
19	G1	PID/AT transfer		
1A	J1	Auto/Manual transfer		
1B	C1	Remote/Local transfer		
1C	SR	RUN/STOP transfer		
1D	ZA	Memory area transfer		
1E	IL	Interlock release		
1F	A1	Event 1 set value (EV1)		
20	A2	Event 2 set value (EV2)		
21	A3	Event 3 set value (EV3)		
22	A4	Event 4 set value (EV4)		

Address	Identifier	Description		
23	A5	Control loop break alarm (LBA) time		
24	N1	LBA deadband		
25	S1	Set value (SV)		
26	P1	Proportional band [heat-side]		
27	I1	Integral time [heat-side]		
28	D1	Derivative time [heat-side]		
29	CA	Control response parameter		
2A	P2	Proportional band [cool-side]		
2B	I2	Integral time [cool-side]		
2C	D2	Derivative time [cool-side]		
2D	V1	Overlap/Deadband		
2E	MR	Manual reset		
2F	НН	Setting change rate limiter (up)		
30	HL	Setting change rate limiter (down)		
31	ТМ	Area soak time		
32	LP	Link area number		
33	A7	Heater break alarm 1 (HBA1) set value		
34	NE	Heater break determination point 1		
35	NE	Heater melting determination point 1		
36	A8	Heater break alarm 2 (HBA2) set value		
37	NH	Heater break determination point 2		
38	NI	Heater melting determination point 2		
39	PB	PV bias		
34	F1	PV digital filter		
38	PR	PV ratio		
3C	DP	PV low input cut-off		
3D	RB	RS bias		
3E	F2	RS digital filter		
3F	PR	RS ratio		
40	ТО	Proportional cycle time [heat-side]		
41	T1	Proportional cycle time [cool-side]		
42	ON	Manual manipulated output value		
43	LK	Set lock level		
44	DX	STOP display		
45	DA	Bar graph display		
46	DE	Bar graph display resolution		
47	DK	Direct key 1		
48	DL	Direct key 2		
49	DM	Direct key 3		
4A	DN	Direct key type		
4B	XI	Input type		
40	PU	Display unit		
4D	XU	Decimal point position		
4E	XV	Input scale high		
4F	XW	Input scale low		
50	AV	Input error determination point (high)		
51	AW	Input error determination point (low)		
52	BS	TC input burnout direction		
53	ХН	Square root extraction		
54	JT	Power supply frequency		
55	TZ	Sampling cycle		
56	XR	Remote setting input type		
50				
Address	Identifier	Description		
----------	------------	---	--	--
57	H2	Digital input (DI) assignment		
58	E0	Output assignment		
59	TH	Timer 1		
5A	TI	Timer 2		
5B	TJ	Timer 3		
5C	ТК	Timer 4		
5D	NA	Energized/De-energized		
5E	LY	Alarm (ALM) lamp lighting condition 1		
5F		Alarm (ALM) lamp lighting condition 2		
60	SS	Output status at STOP mode		
61	LA	Transmission output type		
62	HV	Transmission output scale high		
63	HW	Transmission output scale low		
64	XA	Event 1 type		
65	WA	Event 1 hold action		
66	IF	Event 1 interlock		
67	НА	Event 1 differential gap		
68		Event 1 delay timer		
69		Event 1 action at input error		
64	XB	Event 2 type		
6B	WB	Event 2 hold action		
6C		Event 2 interlock		
60 6D	LO HR	Event 2 differential gap		
6E	TG	Event 2 delay timer		
6E	OB	Event 2 action at input amor		
70	OB VC	Event 2 type		
70	AC WC	Event 3 type		
71		Event 3 hold action		
72		Event 3 interiock		
73	те	Event 3 delev timer		
74		Event 3 detay times		
75		Event 5 action at input error		
70	AD WD	Event 4 hype		
70	WD	Event 4 induction		
70		Event 4 differential can		
79	HD TE	Event 4 differentiar gap		
7A 7D		Event 4 delay unler		
7B 7C	UD VS			
70	АЗ 7Е	CT1 assignment		
70		Unator break aloren 1 (UDA1) tree		
7E		Number of bester brock slows 1 (IDA1) delevatives		
/F	DH	Number of neater break alarm 1 (HBA1) delay times		
80				
81	ZG			
82	NG	Heater break alarm 2 (HBA2) type		
83	DF	Insumoer of neater oreak atarm 2 (HBA2) delay times		
84				
85	SX	Start determination point		
80	KM	External input type		
87	MC	Master channel selection		
88	XL OT	S v tracking		
89		MV transfer function		
8A	XE	Control action		

Address	Identifier	Description		
8B	РК	Integral/derivative time decimal point position		
8C	KA	Derivative term operating factor		
8D	KB	Undershoot suppression factor		
8E	DG	Derivative gain		
8F	IV	ON/OFF action differential gap (upper)		
90	IW	ON/OFF action differential gap (lower)		
91	WH	Action (high) at input error		
92	WL	Action (low) at input error		
93	OE	Manipulated output value at input error		
94	OF	Manipulated output value (MV1) at STOP mode		
95	OG	Manipulated output value (MV2) at STOP mode		
96	РН	Output change rate limiter (up) [MV1]		
97	PL	Output change rate limiter (down) [MV1]		
98	ОН	Output limiter (high) [MV1]		
99	OL	Output limiter (low) [MV1]		
9A	PX	Output change rate limiter (up) [MV2]		
9B	PY	Output change rate limiter (down) [MV2]		
9C	OX	Output limiter (high) [MV2]		
9D	OY	Output limiter (low) [MV2]		
9E	PF	Power feed forward selection		
9F	PZ	Power feed forward gain		
A0	GB	AT bias		
A1	G3	AT cycles		
A2	OP	Output value with AT turned on		
A3	OQ	Output value with AT turned off		
A4	GH	AT differential gap time		
A5	KC	Proportional band adjusting factor [heat-side]		
A6	KD	Integral time adjusting factor [heat-side]		
A7	KE	Derivative time adjusting factor [heat-side]		
A8	KF	Proportional band adjusting factor [cool-side]		
A9	KG	Integral time adjusting factor [cool-side]		
AA	КН	Derivative time adjusting factor [cool-side]		
AB	P6	Proportional band limiter (high) [heat-side]		
AC	P7	Proportional band limiter (low) [heat-side]		
AD	I6	Integral time limiter (high) [heat-side]		
AE	I7	Integral time limiter (low) [heat-side]		
AF	D6	Derivative time limiter (high) [heat-side]		
B0	D7	Derivative time limiter (low) [heat-side]		
B1	P8	Proportional band limiter (high) [cool-side]		
B2	P9	Proportional band limiter (low) [cool-side]		
B3	I8	Integral time limiter (high) [cool-side]		
B4	I9	Integral time limiter (low) [cool-side]		
B5	D8	Derivative time limiter (high) [cool-side]		
B6	D9	Derivative time limiter (low) [cool-side]		
B7	V2	Open/Close output neutral zone		
B8	VH	Open/Close output differential gap		
B9	SY	Action at feedback resistance (FBR) input error		
BA	FV	Feedback adjustment		
BB	TN	Control motor time		
BC	OI	Integrated output limiter		
BD	VS	Valve action at STOP		
BE	ST	Startup tuning (ST)		

Address	Identifier	Description
BF	KI	ST proportional band adjusting factor
C0	KJ	ST integral time adjusting factor
C1	KK	ST derivative time adjusting factor
C2	SU	ST start condition
C3	Y7	Automatic temperature rise group
C4	Y8	Automatic temperature rise learning
C5	RT	Automatic temperature rise dead time
C6	R2	Automatic temperature rise gradient data
C7	GQ	RUN/STOP group
C8	HU	Setting change rate limiter unit time
C9	RU	Soak time unit
CA	SH	Setting limiter (high)
CB	SL	Setting limiter (low)
CC	TS	PV transfer function
CD	DU	PV flashing display at input error

MPORTA • Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."

• System area setting that can be used for the temperature controller is reading area size only. Please refer to the GP-Pro EX Reference Manual for system data area.

- Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
- Please refer to the precautions on manual notation for icons in the table.
 "Manual Symbols and Terminology"
- Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.3 **HA Series**

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.00-00E6.1F	0000-00E6	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description		
00	M1	Input 1 measured value (PV1)		
01	M0	Input 2 measured value (PV2)		
02	M2	Feedback resistance input monitor		
03	M3	Current transformer 1 (CT1) input value monitor		
04	M4	Current transformer 2 (CT2) input value monitor		
05	MS	Input 1 setting-value(SV1) monitor		
06	MT	Input 2 setting-value(SV1) monitor		
07	S2	Remote setting (RS) input value monitor		
08	KH	Cascade monitor		
09	B1	Burnout state monitor of input 1		
0A	B0	Burnout state monitor of input 2		
0B	B2	Burnout state monitor of feedback resistance input		
0C	AA	Event 1 state monitor		
0D	AB	Event 2 state monitor		
0E	AC	Event 3 state monitor		
0F	AD	Event 4 state monitor		
10	AE	Heater break alarm 1 (HBA1) state		
11	AF	Heater break alarm 2 (HBA1) state		
12	01	Manipulated output value (MV1) of input 1		
13	00	Manipulated output value (MV2) of input 2		
14	ER	Error code		
15	L1	Event input(DI) state		
16	L0	Operation mode state		
17	TR	Memory area soak time monitor		
18	G1	PID/AT transfer of input 1		
19	G0	PID/AT transfer of input 2		
1A	J1	Auto/Manual transfer of input 1		
1B	J 0	Auto/Manual transfer of input 2		
1C	C1	Remote/Local transfer		
1D	SR	RUN/STOP transfer		
1E	ZA	Memory area transfer		
1F	A1	Event 1 set value		
20	A2	Event 2 set value		
21	A3	Event 3 set value		
22	A5	Control loop break alarm 1 (LBA1) time		
23	N1	LBA1 deadband		

Address	Identifier	Description
24	A4	Event 4 set value
25	A6	Control loop break alarm 2 (LBA2) time
26	N2	LBA2 deadband
27	S1	Set value (SV1) of input 1
28	P1	Proportional band of input 1
29	I1	Integral time of input 1
2A	D1	Derivative time of input 1
2B	CA	Control response parameter of input 1
2C	S 0	Set value (SV2) of input 2
2D	PO	Proportional band of input 2
2E	IO	Integral time of input 2
2F	D0	Derivative time of input 2
30	C9	Control response parameter of input 2
31	HH	Setting change rate limiter (up) of input 1
32	HL	Setting change rate limiter (down) of input 1
33	HX	Setting change rate limiter (up) of input 2
34	НҮ	Setting change rate limiter (down) of input 2
35	ТМ	Area soak time
36	LP	Link area number
37	A7	Heater break alarm 1 (HBA1) set value
38	A8	Heater break alarm 2 (HBA2) set value
39	PB	PV bias of input 1
3A	F1	PV digital filter of input 1
3B	PR	PV ratio of input 1
3C	DP	PV low input cut-off of input 1
3D	ТО	Proportional cycle of input 1
3E	ON	Manual output value of input 1
3F	PA	PV bias of input 2
40	F0	PV digital filter of input 2
41	PQ	PV ratio of input 2
42	DO	PV low input cut-off of input 2
43	T2	Proportional cycle of input 2
44	OM	Manual output value of input 2
45	LK	Set lock level
46	EM	EEPROM status
47	EB	EEPROM mode
48	NE	Heater break determination point 1
49	NF	Heater melting determination point 1
4A	NH	Heater break determination point 2
4B	NI	Heater melting determination point 2
4C	HP	Not used
4D	HQ	Not used
4E	HR	Not used
4F	FP	Not used
50	FQ	Not used
51	FR	Not used
52	IL	Not used
53	AZ	Not used
54	FS	Not used
55	DX	STOP display selection
56	DA	Bar graph display selection
57	DE	Bar graph display resolution

Address	Identifier	Description	
58	DK	Auto/manual change key operation selection (A/M)	
59	DL	Remote/local change key operation selection (R/L)	
5A	DM	RUN/STOP change key operation selection (R/S)	
5B	XI	Input type selection of input 1	
5C	PU	Display unit selection of input 1	
5D	XU	Decimal-point position selection of input 1	
5E	XV	Input scale high-limit of input 1	
5F	XW	Input scale low-limit of input 1	
60	AV	Input abnormality determination point (High limit) of input 1	
61	AW	Input abnormality determination point (Low limit) of input 1	
62	BS	Burnout direction of input 1	
63	XH	Square root extraction selection of input 1	
64	JT	Power supply frequency selection	
65	XJ	Input type selection of input 2	
66	РТ	Display unit selection of input 2	
67	XT	Decimal-point position selection of input 2	
68	XX	Input scale high-limit of input 2	
69	XY	Input scale low-limit of input 2	
6A	AX	Input abnormality determination point (High limit) of input 2	
6B	AY	Input abnormality determination point (Low limit) of input 2	
6C	BR	Burnout direction of input 2	
6D	XG	Square root extraction selection of input 2	
6E	H2	Event input logic selection	
6F	E0	Output logic selection	
70	TD	Output 1 timer setting	
70	TG	Output 2 timer setting	
72	ТН	Output 3 timer setting	
73	TI	Output 4 timer setting	
74	TI	Output 5 timer setting	
75	LA	Transmission output 1 type selection	
76	HV	Transmission output 1 scale high	
70	HW	Transmission output 1 scale low	
78	LB	Transmission output 1 scale for	
79	CV	Transmission output 2 syste orientian	
74	CW	Transmission output 2 scale low	
7R		Transmission output 2 scale for	
70	EV	Transmission output 3 scale high	
70	EW	Transmission output 3 scale low	
7 <u>E</u>	XA	Event 1 type selection	
7E	WA	Event 1 hold action	
80	НА	Event 1 differential can	
81	0A	Event 1 action at input error	
82	FA	Event 1 assignment	
83	XB	Event 2 type selection	
84	WB	Event 2 hold action	
85	HB	Event 2 differential gap	
86	OB	Event 2 action at input error	
87	FR	Event 2 assignment	
88	XC	Event 3 type selection	
89	WC	Event 3 hold action	
8A	НС	Event 3 differential gap	
8B	00	Event 3 action at input error	
05			

Address	Identifier	Description		
8C	FC	Event 3 assignment		
8D	XD	Event 4 type selection		
8E	WD	Event 4 hold action		
8F	HD	Event 4 differential gap		
90	OD	Event 4 action at input error		
91	FD	Event 4 assignment		
92	XR	CT1 ratio		
93	ZF	CT1 assignment		
94	XS	CT2 ratio		
95	ZG	CT2 assignment		
96	XN	Hot/Cold start selection		
97	KM	Usage selection of input 2		
98	RR	Cascade ratio		
99	RB	Cascade bias		
9A	XL	SV tracking selection		
9B	XE	Control action selection of input 1		
9C	РК	Integral/derivative time decimal point position selection of input 1		
9D	DG	Derivative gain of input 1		
9E	IV	ON/OFF action differential gap (upper) of input 1		
9F	IW	ON/OFF action differential gap (lower) of input 1		
A0	WH	Action (high) at input error of input 1		
A1	WL	Action (low) at input error of input 1		
A2	OE	Manipulated output value at input error of input 1		
A3	РН	Output change rate limiter (up) of input 1		
A4	PL	Output change rate limiter (down) of input 1		
A5	ОН	Output limiter (high) of input 1		
A6	OL	Output limiter (low) of input 1		
A7	PF	Power feed forward selection of input 1		
A8	XF	Control action selection of input 2		
A9	РJ	Integral/derivative time decimal point position selection of input 2		
AA	DJ	Derivative gain of input 2		
AB	IX	ON/OFF action differential gap (upper) of input 2		
AC	IY	ON/OFF action differential gap (lower) of input 2		
AD	WX	Action (high) at input error of input 2		
AE	WY	Action (low) at input error of input 2		
AF	OF	Manipulated output value at input error of input 2		
B0	PX	Output change rate limiter (up) of input 2		
B1	PY	Output change rate limiter (down) of input 2		
B2	OX	Output limiter (high) of input 2		
B3	OY	Output limiter (low) of input 2		
B4	PG	Power feed forward selection of input 2		
B5	GB	AT bias of input 1		
B6	G3	AT cycles of input 1		
B7	GH	AT differential gap time of input 1		
B8	GA	AT bias of input 2		
B9	G2	AT cycles of input 2		
BA	GG	AT differential gap time of input 2		
BB	V2	Open/Close output neutral zone		
BC	VH	Open/Close output differential gap		
BD	SY	Action at feedback resistance (FBR) input error		
BE	FV	Feedback adjustment		
BF	HU	Setting change rate limiter unit time		
<u> </u>				

Address	Identifier	Description
C0	RU	Soak time unit
C1	SH	Setting limiter (high) of input 1
C2	SL	Setting limiter (low) of input 1
C3	ST	Setting limiter (high) of input 2
C4	SU	Setting limiter (low) of input 2
C5	VR	ROM version
C6	UT	Integrated operating time
C7	Нр	Holding peak value ambient temperature
C8	HM	Power feed forward input value
C9	VG	Feedback resistance (FBR) input assignment
CA	PZ	Power feed forward gain of input 1
CB	PW	Power feed forward gain of input 2
CC	ND	Heater break alarm 1 (HBA1) type
CD	DH	Number of heater break alarm 1 (HBA1) delay times
CE	NG	Heater break alarm 2 (HBA2) type
CF	DF	Number of heater break alarm 2 (HBA2) delay times
D0	LY	Alarm (ALM) lamp lighting condition 1
D1	LZ	Alarm (ALM) lamp lighting condition 2
D2	HT	Not used
D3	FT	Not used
D4	OG	Not used
D5	LI	Not used
D6	OR	Not used
D7	TS	Not used
D8	US	Not used
D9	RH	Not used
DA	RL	Not used
DB	RP	Not used
DC	JI	Not used
DD	JJ	Not used
DE	OI	Not used
DF	OJ	Not used
E0	QA	Not used
E1	OT	Not used
E2	OU	Not used
E3	MY	Not used
E4	NY	Not used
E5	MZ	Not used
E6	NZ	Not used

IMPORT/ • Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."

NOTE

System area setting that can be used for the temperature controller is reading area size only. Please refer to the GP-Pro EX Reference Manual for system data area.

Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"

- Please refer to the precautions on manual notation for icons in the table.
 - "Manual Symbols and Terminology"
- Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.4 **MA Series**

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.0-002A.F	0000-002A	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description		
00	M1	Measured value (PV)		
01	M2	Current transformer 1 input value		
02	M3	Current transformer 2 input value		
03	MS	Set value monitor		
04	B1	Burnout		
05	AA	Alarm 1 status		
06	AB	Alarm 2 status		
07	AC	Alarm 3 status		
08	AJ	Output status		
09	01	Manipulated output value		
0A	O2	Cool-side manipulated output value		
0B	ER	Error code		
0C	L1	DI status		
0D	ZA	Memory area number selection		
0E	S1	Set value (SV)		
0F	A1	Alarm 1		
10	N1	Control loop break alarm deadband (LBD)		
11	A2	Alarm 2		
12	N2	Heater break alarm 2 (HBA2)		
13	A3	Alarm 3		
14	P1	Proportional band		
15	P2	Cool-side proportional band		
16	I1	Integral time		
17	D1	Derivative time		
18	W1	Anti-reset windup		
19	V1	Overlap/deadband		
1A	HH	Setting change rate limiter		
1B	EI	Used/unused of channels		
1C	SR	RUN/STOP transfer		
1D	G1	PID/AT selection		
1E	PB	PV bias		
1F	F1	Digital filter		
20	TO	Proportioning cycle time		
21	T1	Cool-side proportioning cycle time		
22	TL	Scan interval time		

Address	Identifier	Description
23	IP	Device address
24	IR	Communication speed
25	IQ	Data bit configuration
26	IT	Interval time
27	EB	EEPROM storage mode
28	EM	EEPROM storage status
29	LK	Lock level 1
2A	LL	Lock level 2

IMPORT	 Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."
NOTE	• System area setting that can be used for the temperature controller is reading area size only. Please
	refer to the GP-Pro EX Reference Manual for system data area.
	Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
	• Please refer to the precautions on manual notation for icons in the table.
	"Manual Symbols and Terminology"
	• Even if non-existing address is used, there are cases when read error is not indicated. In this case,
	zero (0) is kept for read out data. On the other hand, writing error is indicated.

SRV Series 6.5

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.0-0085.1F	0000-0085	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description
00	M1(ch1)	CH1 Measured-value (PV)
01	M1(ch2)	CH2 Measured-value (PV)
02	AJ(ch1)	CH1 Overall event status
03	AJ(ch2)	CH2 Overall event status
04	B1(ch1)	CH1 Burnout state
05	B1(ch2)	CH2 Burnout state
06	AA(ch1)	CH1 Event 1 state
07	AA(ch2)	CH2 Event 1 state
08	AB(ch1)	CH1 Event 2 state
09	AB(ch2)	CH2 Event 2 state
0A	AC(ch1)	CH1 Heater break alarm (HBA) state
0B	AC(ch2)	CH2 Heater break alarm (HBA) state
0C	AP(ch1)	CH1 Control loop break alarm (LBA) state
0D	AP(ch2)	CH2 Control loop break alarm (LBA) state
0E	O1(ch1)	CH1 Manipulated output value[heat-side]
0F	O1(ch2)	CH2 Manipulated output value[heat-side]
10	O2(ch1)	CH1 Manipulated output value[cool-side]
11	O2(ch2)	CH2 Manipulated output value[cool-side]
12	M3(ch1)	CH1 CT input measured value
13	M3(ch2)	CH2 CT input measured value
14	MS(ch1)	CH1 Set-value monitoring
15	MS(ch2)	CH2 Set-value monitoring
16	ER	Error code
17	HE(ch1)	CH1 Temperature rise completion status
18	HE(ch2)	CH2 Temperature rise completion status
19	S1(ch1)	CH1 Set value (SV)
1A	S1(ch2)	CH2 Set value (SV)
1B	P1(ch1)	CH1 Proportional band [heat-side]
1C	P1(ch2)	CH2 Proportional band [heat-side]
1D	P2(ch1)	CH1 Proportional band [cool-side]
1E	P2(ch2)	CH2 Proportional band [cool-side]
1F	I1(ch1)	CH1 Integral time
20	I1(ch2)	CH2 Integral time
21	D1(ch1)	CH1 Derivative time
22	D1(ch2)	CH2 Derivative time

Address	Identifier	Description		
23	CA(ch1)	CH1 Control response designation parameter		
24	CA(ch2)	CH2 Control response designation parameter		
25	V1(ch1)	CH1 Overlap/Deadband		
26	V1(ch2)	CH2 Overlap/Deadband		
27	HH(ch1)	CH1 Setting change rate limiter		
28	HH(ch2)	CH2 Setting change rate limiter		
29	PB(ch1)	CH1 PV bias		
2A	PB(ch2)	CH2 PV bias		
2B	A1(ch1)	CH1 Event 1 setting value		
2C	A1(ch2)	CH2 Event 1 setting value		
2D	A2(ch1)	CH1 Event 2 setting value		
2E	A2(ch2)	CH2 Event 2 setting value		
2F	EI(ch1)	CH1 Operation mode		
30	EI(ch2)	CH2 Operation mode		
31	G1(ch1)	CH1 PID/AT transfer		
32	G1(ch2)	CH2 PID/AT transfer		
33	J1(ch1)	CH1 Auto/Manual transfer		
34	J1(ch2)	CH2 Auto/Manual transfer		
35	ON(ch1)	CH1 Manual output value		
36	ON(ch2)	CH2 Manual output value		
37	OH(ch1)	CH1 Output limiter (high)		
38	OH(ch2)	CH2 Output limiter (high)		
39	OL(ch1)	CH1 Output limiter (low)		
3A	OL(ch2)	CH2 Output limiter (low)		
3B	T0(ch1)	CH1 Proportioning cycle (heat-side)		
3C	T0(ch2)	CH2 Proportioning cycle (heat-side)		
3D	T1(ch1)	CH1 Proportioning cycle (cool-side)		
3E	T1(ch2)	CH2 Proportioning cycle (cool-side)		
3F	F1(ch1)	CH1 digital filter		
40	F1(ch2)	CH2 digital filter		
41	A3(ch1)	CH1 Heater break alarm (HBA) set value		
42	A3(ch2)	CH2 Heater break alarm (HBA) set value		
43	DH(ch1)	CH1 Number of heater break alarm (HBA) delay times		
44	DH(ch2)	CH2 Number of heater break alarm (HBA) delay times		
45	SR	Control RUN/STOP transfer		
46	AV(ch1)	CH1 Input error determination point (high)		
47	AV(ch2)	CH2 Input error determination point (high)		
48	AW(ch1)	CH1 Input error determination point (low)		
49	AW(ch2)	CH2 Input error determination point (low)		
4A	WH(ch1)	CH1 Action (high) at input error		
4B	WH(ch2)	CH2 Action (high) at input error		
4C	WL(ch1)	CH1 Action (low) at input error		
4D	WL(ch2)	CH2 Action (low) at input error		
4E	OE(ch1)	CH1 Manipulated output value at input error		
4F	OE(ch2)	CH2 Manipulated output value at input error		
50	GH(ch1)	CH1 AT differential gap time		
51	GH(ch2)	CH2 AT differential gap time		
52	GB(ch1)	CH1 AT bias		
53	GB(ch2)	CH2 AT bias		
54	XH	Event LED mode set		
55	HP(ch1)	CH1 Control loop break alarm (LBA) usage selection		
56	HP(ch2)	CH2 Control loop break alarm (LBA) usage selection		

Address	Identifier	Description
57	C6(ch1)	CH1 Control loop break alarm (LBA) time
58	C6(ch2)	CH2 Control loop break alarm (LBA) time
59	V2(ch1)	CH1 Control loop break alarm (LBA) deadband
5A	V2(ch2)	CH2 Control loop break alarm (LBA) deadband
5B	E1	DI set
5C	L1	DI status
5D	QA	DO1 set
5E	QB	DO2 set
5F	Q1	DO status
60	AR	Event interlock release
61	HD(ch1)	CH1 Temperature rise completion range
62	HD(ch2)	CH2 Temperature rise completion range
63	T3(ch1)	CH1 Temperature rise completion soak time
64	T3(ch2)	CH2 Temperature rise completion soak time
65	IN	Initial set mode
66	XI(ch1)	CH1 Input range number
67	XI(ch2)	CH2 Input range number
68	XV(ch1)	CH1 Input scale high
69	XV(ch2)	CH2 Input scale high
6A	XW(ch1)	CH1 Input scale low
6B	XW(ch2)	CH2 Input scale low
6C	XU(ch1)	CH1 Input range decimal point position
6D	XU(ch2)	CH2 Input range decimal point position
6E	PU(ch1)	CH1 Temperature unit selection
6F	PU(ch2)	CH2 Temperature unit selection
70	XE(ch1)	CH1 Control type
71	XE(ch2)	CH2 Control type
72	IV(ch1)	CH1 ON/OFF action differential gap (upper)
73	IV(ch2)	CH2 ON/OFF action differential gap (upper)
74	IW(ch1)	CH1 ON/OFF action differential gap (lower)
75	IW(ch2)	CH2 ON/OFF action differential gap (lower)
76	HA(ch1)	CH1 Event 1 differential gap
77	HA(ch2)	CH2 Event 1 differential gap
78	HB(ch1)	CH1 Event 2 differential gap
79	HB(ch2)	CH2 Event 2 differential gap
7A	XA(ch1)	CH1 Event 1 type
7B	XA(ch2)	CH2 Event 1 type
7C	XB(ch1)	CH1 Event 2 type
7D	XB(ch2)	CH2 Event 2 type
7E	WA(ch1)	CH1 Event 1 action
7F	WA(ch2)	CH2 Event 1 action
80	WB(ch1)	CH1 Event 2 action
81	WB(ch2)	CH2 Event 2 action
82	TD(ch1)	CH1 Event delay timer
83	TD(ch2)	CH2 Event delay timer
84	ZX	Transmission transfer time setting
85	X2	Transfer mode hold setting

IMPORT/ • Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."

- **NOTE** System area setting that can be used for the temperature controller is reading area size only. Please refer to the GP-Pro EX Reference Manual for system data area.
 - Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
 - Please refer to the precautions on manual notation for icons in the table.
 - "Manual Symbols and Terminology"
 - Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.6 **SRX Series**

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.00-008C.1F	0000-008C	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description
00	M1(ch1)	CH1 Measured-value (PV)
01	M1(ch2)	CH2 Measured-value (PV)
02	AJ(ch1)	CH1 Overall event status
03	AJ(ch2)	CH2 Overall event status
04	B1(ch1)	CH1 Burnout state
05	B1(ch2)	CH2 Burnout state
06	AA(ch1)	CH1 Event 1 state
07	AA(ch2)	CH2 Event 1 state
08	AB(ch1)	CH1 Event 2 state
09	AB(ch2)	CH2 Event 2 state
0A	AC(ch1)	CH1 Heater break alarm (HBA) state
0B	AC(ch2)	CH2 Heater break alarm (HBA) state
0C	AP(ch1)	CH1 Control loop break alarm (LBA) state
0D	AP(ch2)	CH2 Control loop break alarm (LBA) state
0E	O1(ch1)	CH1 Manipulated output value
0F	O1(ch2)	CH2 Manipulated output value
10	M3(ch1)	CH1 CT input measured value
11	M3(ch2)	CH2 CT input measured value
12	MS(ch1)	CH1 Set-value monitoring
13	MS(ch2)	CH2 Set-value monitoring
14	ER	Error code
15	S1(ch1)	CH1 Set value (SV)
16	S1(ch2)	CH2 Set value (SV)
17	P1(ch1)	CH1 Proportional band
18	P1(ch2)	CH2 Proportional band
19	I1(ch1)	CH1 Integral time
1A	I1(ch2)	CH2 Integral time
1B	D1(ch1)	CH1 Derivative time
1C	D1(ch2)	CH2 Derivative time
1D	CA(ch1)	CH1 Control response designation parameter
1E	CA(ch2)	CH2 Control response designation parameter
1F	PB(ch1)	CH1 PV bias
20	PB(ch2)	CH2 PV bias
21	A1(ch1)	CH1 Event 1 setting value
22	A1(ch2)	CH2 Event 1 setting value

Address	Identifier	Description
23	A2(ch1)	CH1 Event 2 setting value
24	A2(ch2)	CH2 Event 2 setting value
25	EI(ch1)	CH1 Operation mode
26	EI(ch2)	CH2 Operation mode
27	G1(ch1)	CH1 PID/AT transfer
28	G1(ch2)	CH2 PID/AT transfer
29	J1(ch1)	CH1 Auto/Manual transfer
2A	J1(ch2)	CH2 Auto/Manual transfer
2B	ON(ch1)	CH1 Manual output value
2C	ON(ch2)	CH2 Manual output value
2D	OH(ch1)	CH1 Output limiter (high)
2E	OH(ch2)	CH2 Output limiter (high)
2E	OL(ch1)	CH1 Output limiter (low)
30	OL(ch2)	CH2 Output limiter (low)
31	T0(ch1)	CH1 Proportioning cycle
32	T0(ch2)	CH2 Proportioning cycle
33	F1(ch1)	CH1 digital filter
34	F1(ch2)	CH2 digital filter
35	A3(ch1)	CH1 Heater break alarm (HBA) set value
36	A3(ch2)	CH2 Heater break alarm (HBA) set value
37	DH(ch1)	CH1 Number of heater break alarm (HBA) delay times
38	DH(ch2)	CH2 Number of heater break alarm (HBA) delay times
39	XN(ch1)	CH1 Hot/Cold start selection
34	XN(ch2)	CH2 Hot/Cold start selection
38	SX(ch1)	CH1 Start determination point
30	SX(ch2)	CH2 Start determination point
3D	SR(cli2)	Control RUN/STOP transfer
3E	AV(ch1)	CH1 Input error determination point (high)
3E 3F	AV(ch2)	CH2 Input error determination point (high)
40	AW(ch1)	CH1 Input error determination point (low)
41	AW(ch2)	CH2 Input error determination point (low)
42	WH(ch1)	CH1 Action (high) at input error
43	WH(ch2)	CH2 Action (high) at input error
44	WI (ch1)	CH1 Action (low) at input error
45	WL(ch2)	CH2 Action (low) at input error
46	OE(ch1)	CH1 Manipulated output value at input error
47	OE(ch2)	CH2 Manipulated output value at input error
48	GH(ch1)	CH1 AT differential gap time
49	GH(ch2)	CH2 AT differential gap time
4A	GB(ch1)	CH1 AT bias
4B	GB(ch2)	CH2 AT bias
4C	C1	Remote/Local transfer
4D	XH	Event LED mode set
4E	E1(ch1)	CH1 Digital input setting 1 (RESET)
4F	E1(ch2)	CH2 Digital input setting 1 (RESET)
50	E2(ch1)	CH1 Digital input setting 2 (RUN)
51	E2(ch2)	CH2 Digital input setting 2 (RUN)
52	E3(ch1)	CH1 Digital input setting 3 (FIX)
53	E3(ch2)	CH2 Digital input setting 3 (FIX)
54	E4(ch1)	CH1 Digital input setting 4 (MAN)
55	E4(ch2)	CH2 Digital input setting 4 (MAN)
56	E5(ch1)	CH1 Digital input setting 5 (HOLD)

Address	Identifier	Description
57	E5(ch2)	CH2 Digital input setting 5 (HOLD)
58	E6(ch1)	CH1 Digital input setting 6 (STEP)
59	E6(ch2)	CH2 Digital input setting 6 (STEP)
5A	E7(ch1)	CH1 Digital input setting 7 (Program pattern selection)
5B	E7(ch2)	CH2 Digital input setting 7 (Program pattern selection)
5C	E8(ch1)	CH1 Digital input setting 8 (AT/PID)
5D	E8(ch2)	CH2 Digital input setting 8 (AT/PID)
5E	HP(ch1)	CH1 Control loop break alarm (LBA) usage selection
5F	HP(ch2)	CH2 Control loop break alarm (LBA) usage selection
60	C6(ch1)	CH1 Control loop break alarm (LBA) time
61	C6(ch2)	CH2 Control loop break alarm (LBA) time
62	V2(ch1)	CH1 Control loop break alarm (LBA) deadband
63	V2(ch2)	CH2 Control loop break alarm (LBA) deadband
64	PK(ch1)	CH1 Integral/Derivative time decimal point position
65	PK(ch2)	CH2 Integral/Derivative time decimal point position
66	IN	Initial set mode
67	XI(ch1)	CH1 Input range number
68	XI(ch2)	CH2 Input range number
69	XV(ch1)	CH1 Input scale high
6A	XV(ch2)	CH2 Input scale high
6B	XW(ch1)	CH1 Input scale low
6C	XW(ch2)	CH2 Input scale low
6D	XU(ch1)	CH1 Input range decimal point position
6E	XU(ch2)	CH2 Input range decimal point position
6F	PU(ch1)	CH1 Temperature unit selection
70	PU(ch2)	CH2 Temperature unit selection
71	XE(ch1)	CH1 Control type
72	XE(ch2)	CH2 Control type
73	IV(ch1)	CH1 ON/OFF action differential gap (upper)
74	IV(ch2)	CH2 ON/OFF action differential gap (upper)
75	IW(ch1)	CH1 ON/OFF action differential gap (lower)
76	IW(ch2)	CH2 ON/OFF action differential gap (lower)
77	HA(ch1)	CH1 Event 1 differential gap
78	HA(ch2)	CH2 Event 1 differential gap
79	HB(ch1)	CH1 Event 2 differential gap
7A	HB(ch2)	CH2 Event 2 differential gap
7B	XA(ch1)	CH1 Event 1 type
7C	XA(ch2)	CH2 Event 1 type
7D	XB(ch1)	CH1 Event 2 type
7E	XB(ch2)	CH2 Event 2 type
7F	WA(ch1)	CH1 Event 1 action
80	WA(ch2)	CH2 Event 1 action
81	WB(ch1)	CH1 Event 2 action
82	WB(ch2)	CH2 Event 2 action
83	DF(ch1)	CH1 Event delay frequency
84	DF(ch2)	CH2 Event delay frequency
85	ZX	Transmission transfer time setting
86	XP(ch1)	CH1 Segment time unit setting
87	XP(ch2)	CH2 Segment time unit setting
88	X2	Transfer mode hold setting
89	PH(ch1)	CH1 Change rate limiter(up) of output
8A	PH(ch2)	CH2 Change rate limiter(up) of output

Address	Identifier	Description
8B	PL(ch1)	CH1 Change rate limiter(down) of output
8C	PL(ch2)	CH2 Change rate limiter(down) of output

IMPORT	 Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."
NOTE	• System area setting that can be used for the temperature controller is reading area size only. Please
	refer to the GP-Pro EX Reference Manual for system data area.
	Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
	• Please refer to the precautions on manual notation for icons in the table.
	"Manual Symbols and Terminology"
	• Even if non-existing address is used, there are cases when read error is not indicated. In this case,
	zero (0) is kept for read out data. On the other hand, writing error is indicated.

SA Series 6.7

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.0-001E.F	0000-001E	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description
00	M1	Measured value(PV)
01	B1	Burnout
02	AA	Alarm 1 status
03	AB	Alarm 2 status
04	01	Heat-side manipulated output value
05	O2	Cool-side manipulated output value
06	ER	Error code
07	SR	RUN/STOP function
08	G1	Autotuning
09	G2	Self-tuning
0A	S1	Set value (SV)
0B	A1	Alarm 1 set value
0C	A2	Alarm 2 set value
0D	A5	Control loop break alarm
0E	A6	Control loop break alarm deadband
0F	P1	Heat-side proportional band (P)
10	I1	Integral time (I)
11	D1	Derivative time (D)
12	W1	Anti-reset windup
13	TO	Heat-side proportioning cycle time
14	P2	Cool-side proportional band
15	V1	Overlap/deadband
16	T1	Cool-side proportioning cycle time
17	PB	PV bias
18	F1	Digital filter
19	LK	Set data lock function
1A	EB	EEPROM storage mode
1B	EM	EEPROM storage status
1C	LA	Analog output specification selection
1D	HV	Analog output scale high
1E	HW	Analog output scale low

IMPORT/	Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."
NOTE	System area setting that can be used for the temperature controller is reading area size only. Please
	refer to the GP-Pro EX Reference Manual for system data area.
	Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
•	Please refer to the precautions on manual notation for icons in the table.
	"Manual Symbols and Terminology"
•	Even if non-existing address is used, there are cases when read error is not indicated. In this case,
	zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.8 SR Mini HG(H-PCP-A/B) Series

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
	01/0000.0-01/0055.F	01/0000-01/0055		
	02/0000.0-02/0055.F	02/0000-02/0055		
	03/0000.0-03/0055.F	03/0000-03/0055		
	04/0000.0-04/0055.F	04/0000-04/0055		*1 *2 *3
	05/0000.0-05/0055.F	05/0000-05/0055		
	06/0000.0-06/0055.F	06/0000-06/0055		
	07/0000.0-07/0055.F	07/0000-07/0055	τ <u>ΓΓ/Η</u>	
	08/0000.0-08/0055.F	08/0000-08/0055		
	09/0000.0-09/0055.F	09/0000-09/0055		
Communication identifier	10/0000.0-10/0055.F	10/0000-10/0055		
Communication identifier	11/0000.0-11/0055.F	11/0000-11/0055		
	12/0000.0-12/0055.F	12/0000-12/0055		
	13/0000.0-13/0055.F	13/0000-13/0055		
	14/0000.0-14/0055.F	14/0000-14/0055		
	15/0000.0-15/0055.F	15/000-15/0055		
	16/0000.0-16/0055.F	0-16/0055.F 16/0000-16/0055		
	17/0000.0-17/0055.F	17/0000-17/0055		
	18/0000.0-18/0055.F	18/0000-18/0055		
	19/0000.0-19/0055.F	19/0000-19/0055		
	20/0000.0-20/0055.F	20/0000-20/0055		

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

*3 It is necessary to specify the channel number for a module supported by the identifier about SR-Mini-HG (H-PCP-A/B) and SR-Mini-HG (H-PCP-J) Series.

01/0000 Channel number (Setting range: 01 to 20)

Address	Identifier	Description
00	M1	Temperature measured value
01	AA	Alarm 1 status
02	AB	Alarm 2 status
03	B1	Burnout status
04	01	Heat-side manipulated output value
05	O2	Cool-side manipulated output value
06	AC	Heater break alarm status
07	M3	Current transformer input measured value 1
08	M4	Current transformer input measured value 2
09	MS	Set value monitor
0A	HE	Temperature rise completion status
0B	ER	Error code
0C	G1	PID/AT transfer
0D	S1	Temperature set value
0E	P1	Heat-side proportional band
0F	P2	Cool-side proportional band
10	I1	Integral time
11	D1	Derivative time
12	V1	Overlap/deadband
13	CA	Control response parameters
14	A1	Alarm 1 set value
15	A2	Alarm 2 set value
16	A3	Heater break alarm set value 1
17	A4	Heater break alarm set value 2
18	EI	Operation mode transfer
19	Т0	Heat-side proportioning cycle time
1A	T1	Cool-side proportioning cycle time
1B	PB	PV bias
1C	SR	Control RUN/STOP transfer
1D	IN	Initial setting mode
1E	ZA	Memory area number
1F	AR	Alarm interlock release
20	J1	Auto/Manual transfer
21	ON	Manual output value
22	HD	Temperature rise completion range
23	HS	Temperature rise completion trigger
24	T3	Temperature rise completion soak time
25	M5	AI measured value
26	AD	AI alarm 1 status
27	AE	AI alarm 2 status
28	A5	AI alarm 1 set value
29	A6	AI alarm 2 set value
2A	JI	AI zero point correction
2B	JJ	AI full scale correction
2C	NJ	AI operation mode transfer
2D	AP	Control loop break alarm (LBA) status
2E	HP	LBA use selection
2F	C6	LBA time
30	V2	LBA deadband
31	M6	AO output value monitor
32	S6	AO output set value

Address	Identifier	Description
33	XO	AO function selection
34	OY	AO corresponding channel setting
35	CV	AO zooming high limit
36	CW	AO zooming low limit
37	JK	AO zero point correction
38	JL	AO full scale correction
39	L1	DI module input status (DI-A module)
3A	C2	CC-Link selecting flag
3B	Q3	Event DO status (DO-C module)
3C	Q4	Event DO manual output value (DO-C module)
3D	A7	Event DO extension alarm set value
3E	KH	Cascade monitor
3F	KF	Cascade ON/OFF
40	KG	Cascade gain
41	KI	Cascade bias
42	M7	TI measured value
43	AF	TI alarm 1 status
44	AG	TI alarm 2 status
45	B2	TI burnout status
46	A8	TI alarm 1 set value
47	A9	TI alarm 2 set value
48	PC	TI PV bias
49	EJ	TI operation mode transfer
4A	L3	PCP module DI status
4B	L4	Event DI contact input monitor (DI-B module)
4C	L5	Event DI logic input monitor
4D	Q5	Event DI logic output monitor
4E	AH	CT module heater break alarm status
4F	AJ	Comprehensive alarm status
50	M8	Positioning monitor
51	V3	Positioning output neutral zone
52	TJ	Motor time
53	OS	Integrated output limite
54	00	Manual positioning output value
55	C1	Local/Computer transfer

IMPORT

Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."

NOTE • System area setting that can be used for the temperature controller is reading area size only. Please refer to the GP-Pro EX Reference Manual for system data area.

- Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
- Please refer to the precautions on manual notation for icons in the table.
 "Manual Symbols and Terminology"
- Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

SR Mini HG(H-PCP-J) Series 6.9

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
	01/0000.0-01/0055.F	01/0000-01/0055		
	02/0000.0-02/0055.F	02/0000-02/0055		
	03/0000.0-03/0055.F	03/0000-03/0055		
	04/0000.0-04/0055.F	04/0000-04/0055	=	*1 *2 *3
	05/0000.0-05/0055.F	05/0000-05/0055		
	06/0000.0-06/0055.F	06/0000-06/0055		
	07/0000.0-07/0055.F	07/0000-07/0055		
	08/0000.0-08/0055.F	08/0000-08/0055		
	09/0000.0-09/0055.F	09/0000-09/0055		
Communication identifier	10/0000.0-10/0055.F	10/0000-10/0055		
Communication identifier	11/0000.0-11/0055.F	11/0000-11/0055		
	12/0000.0-12/0055.F	12/0000-12/0055		
	13/0000.0-13/0055.F	13/0000-13/0055		
	14/0000.0-14/0055.F	14/0000-14/0055		
	15/0000.0-15/0055.F	15/0000-15/0055		
	16/0000.0-16/0055.F	16/0000-16/0055		
	17/0000.0-17/0055.F	17/0000-17/0055		
	18/0000.0-18/0055.F	18/0000-18/0055		
	19/0000.0-19/0055.F	19/0000-19/0055		
	20/0000.0-20/0055.F	20/0000-20/0055		

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

*3 It is necessary to specify the channel number for a module supported by the identifier about SR-Mini-HG (H-PCP-A/B) and SR-Mini-HG (H-PCP-J) Series.

> 01/0000 - Channel number (Setting range: 01 to 20)

00M1Temperature measured value (PV) [H-TIO- \Box , H-CIO-A] / Motor speed measured value [H-SIO-A]01AAAlarn 1 status [H-TIO- \Box , H-CIO-A, H-SIO-A]02ABAlarn 2 status [H-TIO- \Box , H-CIO-A, H-SIO-A]03B1Burnout status [H-TIO- \Box , H-CIO-A, H-SIO-A]04O1Heat-side manipulated output value [H-TIO- \Box , H-CIO-A]05O2Cool-side manipulated output value [H-TIO- \Box , H-CIO-A]06ACHeater break alarn status [H-TIO- \Box , H-CIO-A]07M3Current transformer input measured value 2 [H-CT-A]09MSSet value monitor [H-TIO- \Box , H-CIO-A, H-SIO-A]0AHETemperature rise completion status [H-TIO- \Box , H-CIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO- \Box , H-CIO-A, H-SIO-A]0DS1Temperature set value (SV) [H-TIO- \Box , H-CIO-A, H-SIO-A]10I1Integral time [H-TIO- \Box , H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO- \Box , H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO- \Box , H-CIO-A, H-SIO-A]13CAControl response parameters [H-TIO- \Box , H-CIO-A, H-SIO-A]14A1Alarn 1 set value [H-TIO- \Box , H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO- \Box , H-CIO-A, H-SIO-A]16A3Heater break alar
01AAAlarm 1 status [H-TIO- \Box , H-CIO-A, H-SIO-A]02ABAlarm 2 status [H-TIO- \Box , H-CIO-A, H-SIO-A]03B1Burnout status [H-TIO- \Box , H-CIO-A, H-SIO-A]04O1Heat-side manipulated output value [H-TIO- \Box , H-CIO-A]05O2Cool-side manipulated output value [H-TIO- \Box , H-CIO-A]06ACHeater break alarm status [H-TIO- \Box , H-CIO-A]07M3Current transformer input measured value 1 [H-TIO-A/C/D]08M4Current transformer input measured value 2 [H-CT-A]09MSSet value monitor [H-TIO- \Box , H-CIO-A, H-SIO-A]0AHETemperature rise completion status [H-TIO- \Box , H-CIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO- \Box , H-CIO-A, H-SIO-A]0BS1Temperature set value (SV) [H-TIO- \Box , H-CIO-A]0FP2Cool-side proportional band [H-TIO- \Box , H-CIO-A]10I1Integral time [H-TIO- \Box , H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO- \Box , H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO- \Box , H-CIO-A, H-SIO-A]13CAControl response parameters [H-TIO- \Box , H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO- \Box , H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO- \Box , H-CIO-A, H-SIO-A]16A3Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO- \Box , H-CIO-A, H-SIO-A]
02ABAlarm 2 status [H-TIO- \Box , H-CIO-A, H-SIO-A]03B1Burnout status [H-TIO- \Box , H-CIO-A, H-SIO-A]04O1Heat-side manipulated output value [H-TIO- \Box , H-CIO-A]05O2Cool-side manipulated output value [H-TIO- \Box , H-CIO-A]06ACHeater break alarm status [H-TIO- $\Delta/C/D$, H-CIO-A]07M3Current transformer input measured value 1 [H-TIO- $\Delta/C/D$]08M4Current transformer input measured value 2 [H-CT-A]09MSSet value monitor [H-TIO- \Box , H-CIO-A, H-SIO-A]0AHETemperature rise completion status [H-TIO- \Box , H-CIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO- \Box , H-CIO-A, H-SIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO- \Box , H-CIO-A, H-SIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO- \Box , H-CIO-A, H-SIO-A]0DS1Temperature set value (SV) [H-TIO- \Box , H-CIO-A, H-SIO-A]0EP1Heat-side proportional band [H-TIO- \Box , H-CIO-A, H-SIO-A]10I1Integral time [H-TIO- \Box , H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO- \Box , H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO- \Box , H-CIO-A, H-SIO-A]13CAControl response parameters [H-TIO- \Box , H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO- \Box , H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO- \Box , H-CIO-A, H-SIO-A]16A3Heater break alarm set value 2 [H-C
03 B1 Burnout status [H-TIO-□, H-CIO-A, H-SIO-A] 04 01 Heat-side manipulated output value [H-TIO-□, H-CIO-A] 05 02 Cool-side manipulated output value [H-TIO-□, H-CIO-A] 06 AC Heater break alarn status [H-TIO-A/C/D, H-CIO-A] 07 M3 Current transformer input measured value 1 [H-TIO-A/C/D] 08 M4 Current transformer input measured value 2 [H-CT-A] 09 MS Set value monitor [H-TIO-□, H-CIO-A, H-SIO-A] 0A HE Temperature rise completion status [H-TIO-□, H-CIO-A] 0B ER Error code [H-PCP-J] 0C G1 PID/AT transfer [H-TIO-□, H-CIO-A, H-SIO-A] 0D S1 Temperature set value (SV) [H-TIO-□, H-CIO-A, H-SIO-A] 0E P1 Heat-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A] 0F P2 Cool-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A] 10 I1 Integral time [H-TIO-□, H-CIO-A, H-SIO-A] 11 D1 Derivative time [H-TIO-□, H-CIO-A, H-SIO-A] 12 V1 Overlap/deadband [H-TIO-□, H-CIO-A, H-SIO-A] 13 CA Control response parameters [H-TIO-□, H-CIO-A, H-SIO-A] <
0401Heat-side manipulated output value [H-TIO- \Box , H-CIO-A]0502Cool-side manipulated output value [H-TIO- \Box , H-CIO-A]06ACHeater break alarm status [H-TIO- \Box , H-CIO-A]07M3Current transformer input measured value 1 [H-TIO-A/C/D]08M4Current transformer input measured value 2 [H-CT-A]09MSSet value monitor [H-TIO- \Box , H-CIO-A, H-SIO-A]0AHETemperature rise completion status [H-TIO- \Box , H-CIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO- \Box , H-CIO-A, H-SIO-A]0DS1Temperature set value (SV) [H-TIO- \Box , H-CIO-A, H-SIO-A]0EP1Heat-side proportional band [H-TIO- \Box , H-CIO-A, H-SIO-A]0FP2Cool-side proportional band [H-TIO- \Box , H-CIO-A, H-SIO-A]10I1Integral time [H-TIO- \Box , H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO- \Box , H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO- \Box , H-CIO-A, H-SIO-A]13CAControl response parameters [H-TIO- \Box , H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO- \Box , H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO- \Box , H-CIO-A, H-SIO-A]16A3Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO- \Box , H-CIO-A, H-SIO-A]
0502Cool-side manipulated output value [H-TIO-□, H-CIO-A]06ACHeater break alarm status [H-TIO-A/C/D, H-CIO-A]07M3Current transformer input measured value 1 [H-TIO-A/C/D]08M4Current transformer input measured value 2 [H-CT-A]09MSSet value monitor [H-TIO-□, H-CIO-A, H-SIO-A]0AHETemperature rise completion status [H-TIO-□, H-CIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO-□, H-CIO-A, H-SIO-A]0DS1Temperature set value (SV) [H-TIO-□, H-CIO-A, M-SIO-A]0EP1Heat-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]0FP2Cool-side proportional band [H-TIO-□, H-CIO-A]1011Integral time [H-TIO-□, H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A, H-SIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 1 [H-TIO-A, H-SIO-A]17A4Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
06ACHeater break alarm status [H-TIO-A/C/D, H-CIO-A]07M3Current transformer input measured value 1 [H-TIO-A/C/D]08M4Current transformer input measured value 2 [H-CT-A]09MSSet value monitor [H-TIO-□, H-CIO-A, H-SIO-A]0AHETemperature rise completion status [H-TIO-□, H-CIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO-□, H-CIO-A, H-SIO-A]0DS1Temperature set value (SV) [H-TIO-□, H-CIO-A, H-SIO-A]0EP1Heat-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]0FP2Cool-side proportional band [H-TIO-□, H-CIO-A]1011Integral time [H-TIO-□, H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A, H-SIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
07M3Current transformer input measured value 1 [H-TIO-A/C/D]08M4Current transformer input measured value 2 [H-CT-A]09MSSet value monitor [H-TIO-], H-CIO-A, H-SIO-A]0AHETemperature rise completion status [H-TIO-], H-CIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO-], H-CIO-A, H-SIO-A]0DS1Temperature set value (SV) [H-TIO-], H-CIO-A, H-SIO-A]0EP1Heat-side proportional band [H-TIO-], H-CIO-A, H-SIO-A]0FP2Cool-side proportional band [H-TIO-], H-CIO-A, I10I1Integral time [H-TIO-], H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-], H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-], H-CIO-A, H-SIO-A]13CAControl response parameters [H-TIO-], H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-], H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-], H-CIO-A, H-SIO-A]16A3Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-], H-CIO-A, H-SIO-A]
08M4Current transformer input measured value 2 [H-CT-A]09MSSet value monitor [H-TIO-□, H-CIO-A, H-SIO-A]0AHETemperature rise completion status [H-TIO-□, H-CIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO-□, H-CIO-A, H-SIO-A]0DS1Temperature set value (SV) [H-TIO-□, H-CIO-A] / Motor speed set value [H-SIO-A]0EP1Heat-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]0FP2Cool-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]10I1Integral time [H-TIO-□, H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
09MSSet value monitor [H-TIO-□, H-CIO-A, H-SIO-A]0AHETemperature rise completion status [H-TIO-□, H-CIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO-□, H-CIO-A, H-SIO-A]0DS1Temperature set value (SV) [H-TIO-□, H-CIO-A] / Motor speed set value [H-SIO-A]0EP1Heat-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]0FP2Cool-side proportional band [H-TIO-□, H-CIO-A]10I1Integral time [H-TIO-□, H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A, H-SIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 1 [H-TIO-A/C/D]17A4Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
0AHETemperature rise completion status [H-TIO-□, H-CIO-A]0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO-□, H-CIO-A, H-SIO-A]0DS1Temperature set value (SV) [H-TIO-□, H-CIO-A] / Motor speed set value [H-SIO-A]0EP1Heat-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]0FP2Cool-side proportional band [H-TIO-□, H-CIO-A]10I1Integral time [H-TIO-□, H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 1 [H-TIO-A/C/D]17A4Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
0BERError code [H-PCP-J]0CG1PID/AT transfer [H-TIO-□, H-CIO-A, H-SIO-A]0DS1Temperature set value (SV) [H-TIO-□, H-CIO-A, H-SIO-A]0EP1Heat-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]0FP2Cool-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]10I1Integral time [H-TIO-□, H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 1 [H-TIO-A, H-SIO-A]17A4Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
OCG1PID/AT transfer [H-TIO-□, H-CIO-A, H-SIO-A]0DS1Temperature set value (SV) [H-TIO-□, H-CIO-A, M-SIO-A] / Motor speed set value [H-SIO-A]0EP1Heat-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]0FP2Cool-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]10I1Integral time [H-TIO-□, H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 1 [H-TIO-A/C/D]17A4Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
0DS1Temperature set value (SV) [H-TIO-□, H-CIO-A] / Motor speed set value [H-SIO-A]0EP1Heat-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]0FP2Cool-side proportional band [H-TIO-□, H-CIO-A]10I1Integral time [H-TIO-□, H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 1 [H-TIO-A/C/D]17A4Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
0EP1Heat-side proportional band [H-TIO-□, H-CIO-A, H-SIO-A]0FP2Cool-side proportional band [H-TIO-□, H-CIO-A]1011Integral time [H-TIO-□, H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 1 [H-TIO-A/C/D]17A4Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
0FP2Cool-side proportional band [H-TIO-□, H-CIO-A]1011Integral time [H-TIO-□, H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 1 [H-TIO-A/C/D]17A4Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
10I1Integral time [H-TIO-□, H-CIO-A, H-SIO-A]11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 1 [H-TIO-A/C/D]17A4Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
11D1Derivative time [H-TIO-□, H-CIO-A, H-SIO-A]12V1Overlap/deadband [H-TIO-□, H-CIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 1 [H-TIO-A]17A4Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
12V1Overlap/deadband [H-TIO-□, H-CIO-A]13CAControl response parameters [H-TIO-□, H-CIO-A, H-SIO-A]14A1Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A]15A2Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A]16A3Heater break alarm set value 1 [H-TIO-A/C/D]17A4Heater break alarm set value 2 [H-CT-A]18EIOperation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
13 CA Control response parameters [H-TIO-□, H-CIO-A, H-SIO-A] 14 A1 Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A] 15 A2 Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A] 16 A3 Heater break alarm set value 1 [H-TIO-Δ/C/D] 17 A4 Heater break alarm set value 2 [H-CT-A] 18 EI Operation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
14 A1 Alarm 1 set value [H-TIO-□, H-CIO-A, H-SIO-A] 15 A2 Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A] 16 A3 Heater break alarm set value 1 [H-TIO-A/C/D] 17 A4 Heater break alarm set value 2 [H-CT-A] 18 EI Operation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
15 A2 Alarm 2 set value [H-TIO-□, H-CIO-A, H-SIO-A] 16 A3 Heater break alarm set value 1 [H-TIO-A/C/D] 17 A4 Heater break alarm set value 2 [H-CT-A] 18 EI Operation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
16 A3 Heater break alarm set value 1 [H-TIO-A/C/D] 17 A4 Heater break alarm set value 2 [H-CT-A] 18 EI Operation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
17 A4 Heater break alarm set value 2 [H-CT-A] 18 EI Operation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
18 EI Operation mode transfer [H-TIO-□, H-CIO-A, H-SIO-A]
19 TO Heat-side proportioning cycle time [H-TIO-□, H-CIO-A]
1A T1 Cool-side proportioning cycle time [H-TIO-D, H-CIO-A]
1B PB PV bias [H-TIO-□, H-CIO-A, H-SIO-A]
1C SR Control RUN/STOP transfer [H-PCP-J]
1D IN Initial setting mode [H-PCP-J]
1E ZA Memory area number [H-TIO-□, H-CIO-A, H-SIO-A]
1F AR Alarm interlock release [H-TIO-]. H-CIO-A. H-TI-]. H-AI-]
20 J1 Auto/Manual transfer [H-TIO-□, H-CIO-A]
21 ON Manual output value [H-TIO-], H-CIO-A]
22 HD Temperature rise completion range [H-TIO-]. H-CIO-A]
23 HS Temperature rise completion trigger [H-TIO-]. H-CIO-A]
24 T3 Temperature rise completion soak time [H-TIO- \Box , H-CIO-A]
25 M5 AI measured value [H-AI-A/B]
26 AD AI alarm 1 status [H-AI-A/B]
27 AE AI alarm 2 status [H-AI-A/B]
28 A5 AI alarm 1 set value [H-AI-A/B]
29 A6 AI alarm 2 set value [H-AI-A/B]
2A JI AI zero point correction [H-AI-A/B]
2B JJ AI full scale correction [H-AI-A/B]
2C NJ AI operation mode transfer [H-AI-A/B]
2D AP Control loop break alarm (LBA) status [H-TIO-]. H-CIO-A1
$2E$ HP LBA use selection [H-TIO- \Box H-CIO-A]
$2F$ C6 LBA time [H-TIO- \Box , H-CIO-A]
30 V2 LBA deadband [H-TIO- \Box . H-CIO-A]
31 M6 AO output value monitor [H-AO-A/B]
32 S6 AO output set value [H-AO-A/B]

Address	Identifier	Description
33	XO	AO function selection [H-AO-A/B]
34	OY	AO corresponding channel setting [H-AO-A/B]
35	CV	AO zooming high limit [H-AO-A/B]
36	CW	AO zooming low limit [H-AO-A/B]
37	JK	AO zero point correction [H-AO-A/B]
38	JL	AO full scale correction [H-AO-A/B]
39	L1	H-DI-A module input status [H-DI-A]
3A	C2	CC-Link selecting flag
3B	Q3	Event DO status [H-DO-C]
3C	Q4	Event DO manual output value [H-DO-C]
3D	A7	Event DO extension alarm set value [H-DO-C]
3E	KH	Cascade monitor [H-CIO-A]
3F	KF	Cascade ON/OFF [H-CIO-A]
40	KG	Cascade gain [H-CIO-A]
41	KI	Cascade bias [H-CIO-A]
42	M7	TI measured value [H-TI-A/B/C]
43	AF	TI alarm 1 status [H-TI-A/B/C]
44	AG	TI alarm 2 status [H-TI-A/B/C]
45	B2	TI burnout status [H-TI-A/B/C]
46	A8	TI alarm 1 set value [H-TI-A/B/C]
47	A9	TI alarm 2 set value [H-TI-A/B/C]
48	PC	TI PV bias [H-TI-A/B/C]
49	EJ	TI operation mode transfer [H-TI-A/B/C]
4A	L3	PCP module DI status
4B	L4	Event DI contact input monitor [H-DI-B]
4C	L5	Event DI logic input monitor [H-DI-B]
4D	Q5	Event DI logic output monitor [H-DI-B]
4E	AH	H-CT-A module heater break alarm status [H-CT-A]
4F	AJ	Comprehensive alarm status [H-PCP-J]
50	M8	Positioning monitor [H-TIO-K]
51	V3	Positioning output neutral zone [H-TIO-K]
52	TJ	Motor time [H-TIO-K]
53	OS	Integrated output limiter [H-TIO-K]
54	00	Manual positioning output value [H-TIO-K]
55	C1	Local/Computer transfer

IMPORT

Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."

NOTE • System area setting that can be used for the temperature controller is reading area size only. Please refer to the GP-Pro EX Reference Manual for system data area.

- Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
- Please refer to the precautions on manual notation for icons in the table.
 "Manual Symbols and Terminology"
- Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.10 **REX-F9000 Series**

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.00-002F.1F	0000-002F	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description
00	M1	Measured-value(PV)
01	AA	First alarm output
02	AB	Second alarm output
03	01	Manipulated output value(MV)
04	B1	Burnout
05	ER	Error code
06	G1	PID/AT transferPID control/auto-tuning transfer
07	J1	Auto/Manual transfer
08	SR	Operation execution (RUN)/STOP transfer
09	S1	Set value (SV)
0A	A1	First alarm setting
0B	A2	Second alarm setting
0C	P1	Proportional band
0D	I1	Integral time
0E	D1	Derivative time
0F	CA	Control response designation parameter
10	PB	PV bias
11	PC	Sensor bias
12	F1	digital filter
13	OH	Output limit (High limit)
14	OL	Output limit (Low limit)
15	GB	AT bias
16	HA	First alarm differential gap
17	TD	First alarm timer setting
18	HB	Second alarm differential gap
19	TG	Second alarm timer setting
1A	LA	Analog output Specification selection
1B	HV	Analog output Scale high limit
1C	HW	Analog output Scale low limit
1D	DA	Bar-graph display selection
1E	XI	Input type selection
1F	XU	Decimal-point position selection
20	JT	Power supply frequency
21	SH	Setting limit (High limit)
22	SL	Setting limit (Low limit)

Address	Identifier	Description
23	то	Proportioning cycle(OUT1)
24	XE	Direct/reverse action selection
25	PF	Power feed forward
26	XA	Alarm 1 type selection
27	NA	First alarm Energized/de-energized selection
28	OA	First alarm Action selection at input abnormality
29	WA	First alarm Hold action selection
2A	XB	Alarm 2 type selection
2B	NB	Second alarm Energized/de-energized selection
2C	OB	Second alarm Action selection at input abnormality
2D	WB	Second alarm Hold action selection
2E	LK	Set data lock level
2F	LM	Mode lock level selection

IMPORT/

• Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."

- System area setting that can be used for the temperature controller is reading area size only. Please refer to the GP-Pro EX Reference Manual for system data area.
 - Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
 - Please refer to the precautions on manual notation for icons in the table.

"Manual Symbols and Terminology"

• Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.11 **REX-F Series**

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.0-0055.F	0000-0055	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description
00	M1	Measured-value (PV) input
01	AA	First alarm output
02	AB	Second alarm output
03	AC	Heater break alarm output
04	01	Manipulated output (Heating-side)
05	02	Manipulated output (Cooling-side)
06	B1	Burnout
07	B2	Feedback resistance (FBR) input burnout
08	S2	Remote setting value (RS)
09	M2	Feedback resistance input value (POS)
0A	M3	Current transformer input value
0B	MS	Set-value (SV) monitoring
0C	J1	Auto/manual transfer
0D	C1	Local/remote transfer
0E	E1	Local/external memory area transfer
0F	ZA	Control area No. transfer
10	G1	PID control/auto-tuning transfer
11	RA	Local mode/computer mode identification
12	SR	Operation execution (RUN)/STOP transfer
13	ON	Manipulated output value (MV)
14	S1	Set-value (SV)
15	A1	First alarm setting
16	A2	Second alarm setting
17	P1	Proportional band (Heating-side)
18	I1	Integral time
19	D1	Derivative time
1A	CA	Control response designation parameter
1B	P2	Cooling-side proportional band
1C	V1	Deadband
1D	HH	Setting change rate limit
1E	PB	PV bias
1F	F1	PV digital filter
20	DP	PV low input cut-off
21	RR	RS ratio
22	RB	RS bias

Address	Identifier	Description
23	F2	RS digital filter
24	OH	Output limit (High limit)
25	OL	Output limit (Low limit)
26	OQ	Cooling output Min. ON time
27	PH	Increase in output change rate limit
28	PL	Decrease in output change rate limit
29	IV	Upper ON/OFF action (A) differential gap
2A	IW	Lower ON/OFF action (A) differential gap
2B	OE	Manual output at abnormality
2C	GB	AT bias
2D	HA	First alarm differential gap
2E	TD	First alarm timer setting
2F	A3	Heater break alarm
30	HB	Second alarm differential gap
31	TG	Second alarm timer setting
32	LA	Analog output (AO) Specification selection
33	HV	Analog output (AO) Scale high limit
34	HW	Analog output (AO) Scale low limit
35	V2	Neutral zone
36	VH	Open/close output differential gap
37	SY	Action selection at feedback resistance (FBR) input break
38	DA	Bar-graph display selection
39	XI	PV input type selection
3A	AV	Input abnormality determination point (High limit)
3B	AW	Input abnormality determination point (Low limit)
3C	WH	Action selection at input abnormality (High limit)
3D	WL	Action selection at input abnormality (Low limit)
3E	XV	Input programmable range (High limit)
3F	XW	Input programmable range (Low limit)
40	XU	Decimal-point position selection
41	XH	Square root extraction selection
42	SH	Setting limit (High limit)
43	SL	Setting limit (Low limit)
44	XR	RS input type selection
45	XL	SV tracking selection
46	T0	Proportioning cycle (Heating-side)
47	T1	Cooling-side proportioning cycle
48	XE	Direct/reverse action selection
49	XN	Hot/cold start selection
4A	SX	Start determination point
4B	XA	First alarm Action selection
4C	NA	First alarm Energized/de-energized selection
4D	OA	First alarm Action selection at input abnormality
4E	WA	First alarm Hold action selection
4F	XB	Second alarm Action selection
50	NB	Second alarm Energized/de-energized selection
51	OB	Second alarm Action selection at input abnormality
52	WB	Second alarm Hold action selection
53	LK	Set data lock level
54	LL	area lock
55	DH	Operation RUN/STOP display lock

IMPORT/	Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."
NOTE	System area setting that can be used for the temperature controller is reading area size only. Please
	refer to the GP-Pro EX Reference Manual for system data area.
	Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
•	Please refer to the precautions on manual notation for icons in the table.
	"Manual Symbols and Terminology"
•	Even if non-existing address is used, there are cases when read error is not indicated. In this case,
	zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.12 **REX-D Series**

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.0-003E.F	0000-003E	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description
00	M1	Measured-value(PV)
01	M2	First current transformer input value(CT1)
02	M3	Second current transformer input value(CT2)
03	AA	First alarm output
04	AB	Second alarm output
05	AC	Heater break alarm output 1
06	AD	Heater break alarm output 2
07	AE	Control loop break alarm
08	B1	Burnout
09	01	Manipulated output 1(Heating-side)
0A	O2	Manipulated output 2(Cooling-side)
0B	MS	Set-value(SV)monitoring
0C	ER	Error data
0D	J1	AUTO/MAN transfer
0E	SR	RUN/STOP transfer
0F	G1	PID/Auto-tuning transfer
10	S1	Set-value(SV1)
11	ON	Manipulated output value(MV)
12	S2	Step set-value(SV2)
13	A1	First alarm setting
14	A2	Second alarm setting
15	A3	First heater break alarm setting
16	A4	Second heater break alarm setting
17	PB	PV bias
18	HH	SV change rate limit
19	XA	First alarm action selection
1A	HA	First alarm differential gap
1B	TD	First alarm timer setting
1C	A5	Control loop break alarm setting
1D	V3	LBA deadband
1E	XB	Second alarm action selection
1F	HB	Second alarm differential gap setting
20	TG	Second alarm timer setting
21	TH	HBA delay timer
22	P1	Proportional band(Heating-side)

Address	Identifier	Description
23	I1	Integral time
24	D1	Derivative time
25	W1	Anti-reset windup(ARW)
26	P2	Cooling-side proportional band
27	V1	Overlap/deadband
28	MH	ON/OFF action differential gap
29	MR	Manual reset
2A	XP	Fazzy
2B	то	Proportioning cycle(OUT1)
2C	OH	Output limit(High-limit)
2D	OL	Output limit(Low-limit)
2E	XE	Direct/reverse action selection
2F	T1	Proportioning cycle(OUT2)
30	OI	Output limit(high-limit)(OUT2)
31	LA	Analog output specification selection
32	HV	High limit analog output range
33	HW	Low limit analog output range
34	XI	Input type selection
35	XV	Scaling high-limit
36	XW	Scaling low-limit
37	XU	Decimal-point position selection
38	PQ	AUTO/MAN function selection
39	DH	Control RUN/STOP display selection
3A	XR	Current transformer type selection
3B	XQ	Air cooling/water cooling selection
3C	GH	Auto-tuning(AT)differential gap
3D	WH	Action selection at input abnormality
3E	XO	Universal output selection

MPORT/ • Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."

• System area setting that can be used for the temperature controller is reading area size only. Please refer to the GP-Pro EX Reference Manual for system data area.

Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"

• Please refer to the precautions on manual notation for icons in the table.

"Manual Symbols and Terminology"

• Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.13 **REX-G9** Series

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.00-005E.1F	0000-005E	<u>[[] H</u>	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description
00	M1	Measured-value (PV) input
01	AA	First alarm output
02	AB	Second alarm output
03	AC	Third alarm output
04	01	Manipulated output1
05	B1	Burnout
06	B2	Feedback resistance (FBR) input burnout
07	S2	Remote setting value
08	M2	Feedback display
09	MS	Set-value (SV) monitoring
0A	J1	Auto/Manual transfer
0B	C1	Remote/Local transfer
0C	E1	Local/external memory area transfer
0D	ZA	Control area No. transfer
0E	G1	PID control/auto-tuning transfer
0F	RA	Computer mode/local mode identification
10	SR	Operation execution (RUN)/STOP transfer
11	ON	Manipulated output value
12	S1	Set-value (SV)
13	A1	First alarm setting
14	A2	Second alarm setting
15	A3	Third alarm setting
16	P1	Proportional band
17	I1	Integral time
18	D1	Derivative time
19	CA	Control response designation parameter
1A	PB	PV bias
1B	F1	PV digital filter
1C	VA	PV Moving average
1D	DP	PV low input cut-off
1E	HH	Setting change rate limiter (up)
1F	HL	Setting change rate limiter (down)
20	RR	RS ratio
21	RB	RS bias
22	F2	RS digital filter

Address	Identifier	Description
23	VB	RS Moving average
24	OH	Output limit (High limit)
25	OL	Output limit (Low limit)
26	PH	Increase in output change rate limit
27	PL	Decrease in output change rate limit
28	IV	Upper ON/OFF action (A) differential gap
29	IW	Lower ON/OFF action (A) differential gap
2A	DG	Derivative gain
2B	OE	Manual output at abnormality
2C	GB	AT bias
2D	G2	AT cycles
2E	НА	Alarm 1 hysteresis
2F	HB	Alarm 2 hysteresis
30	НС	Alarm 3 hysteresis
31	LA	Analog output 1 Specification selection
32	HV	Analog output 1 Scale high limit
33	HW	Analog output 1 Scale low limit
34	LB	Analog output 2 Specification selection
35	CV	Analog output 2 Scale high limit
36	CW	Analog output 2 Scale low limit
37	V2	Neutral zone
38	VH	Open/close hysteresis
39	SY	Action selection at feedback resistance (FBR) input break
3A	TL	Display update cycle
3B	DA	Deflection bar graph(display/non-display)
3C	DB	RS bar graph(display/non-display)
3D	DC	PV bar graph(display/non-display)
3E	DE	Range of display in deflection bar graph
3F	XI	PV input type selection
40	AV	Input abnormality determination point (High limit)
41	AW	Input abnormality determination point (Low limit)
42	WH	Action selection at input abnormality (High limit)
43	WL	Action selection at input abnormality (Low limit)
44	XV	Input programmable range (High limit)
45	XW	Input programmable range (Low limit)
46	PU	PV input unit
47	XU	Decimal-point position selection
48	XH	Square root extraction selection
49	SH	Setting limit (High limit)
4A	SL	Setting limit (Low limit)
4B	XR	RS input type selection
4C	XL	SV tracking selection
4D	TO	Output cycles
4E	XE	Direct/reverse action selection
4F	DT	Derivative cycle
50	XN	Hot/Cold start selection
51	XA	First alarm Action selection
52	NA	First alarm Energized/de-energized selection
53	OA	First alarm Action selection at input abnormality
54	WA	First alarm Hold action selection
55	XB	Second alarm Action selection
56	NB	Second alarm Energized/de-energized selection

Address	Identifier	Description
57	OB	Second alarm Action selection at input abnormality
58	WB	Second alarm Hold action selection
59	XC	Third alarm Action selection
5A	NC	Third alarm Energized/de-energized selection
5B	OC	Third alarm Action selection at input abnormality
5C	WC	Third alarm Hold action selection
5D	JT	Power supply frequency
5E	LK	Setting lock No.

IMPORT	 Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."
NOTE	• System area setting that can be used for the temperature controller is reading area size only. Please
	refer to the GP-Pro EX Reference Manual for system data area.
	Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
	• Please refer to the precautions on manual notation for icons in the table.
	"Manual Symbols and Terminology"
	• Even if non-existing address is used, there are cases when read error is not indicated. In this case,
	zero (0) is kept for read out data. On the other hand, writing error is indicated.
6.14 **REX-P300 Series**

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.00-0078.1F	0000-0078	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description
00	M1	Measured value(PV)monitoring
01	S1	Set value(SV)monitoring
02	01	Manipulated output monitoring 1 (Heat side)
03	02	Manipulated output monitoring 2 (Cool side)
04	AA	First alarm monitoring
05	AB	Second alarm monitoring
06	B1	Burnout
07	PS	Pattern No.
08	SN	Segment No.
09	T1	Time signal output No.1 status
0A	T2	Time signal output No.2 status
0B	T3	Time signal output No.3 status
0C	T4	Time signal output No.4 status
0D	T5	Time signal output No.5 status
0E	T6	Time signal output No.6 status
0F	T7	Time signal output No.7 status
10	Т8	Time signal output No.8 status
11	EO	Program end output
12	AC	OUT2 action output
13	AD	OUT3 action output
14	AE	OUT4 action output
15	ER	Error
16	TR	Segment remaining time
17	RT	No. of repeat execution times
18	ON	Manipulated output value(MV)
19	G1	PID/AT transfer
1A	XM	Operation mode
1B	EN	Program end status
1C	WT	Wait status
1D	НО	Hold status
1E	SK	Step function
1F	SM	Search function
20	LE	Segment level setting
21	TM	Segment time setting
22	PE	Program end No.

Address	Identifier	Description
23	RR	Setting of the number of program execution times
24	LP	Link pattern No.
25	ZW	Wait zone (For fall)
26	ZX	Wait zone (For rise)
27	ET	Pattern end output time
28	RE	Time signal output No.
29	SO	Start segment
2A	ТО	ON time
2B	SF	End Segment
2C	TF	OFF time
2D	S2	FIX set value
2E	PB	PV bias
2F	PR	PV ratio
30	PW	Level PID setting1
31	PX	Level PID setting2
32	PY	Level PID setting3
33	F1	Digital filter
34	DP	Low level cut-off point
35	A1	First alarm setting
36	A2	Second alarm setting
37	XA	First alarm action selection
38	XB	Second alarm action selection
39	HA	First alarm differential gap
3A	HB	Second alarm differential gap
3B	TD	First alarm timer
3C	TG	Second alarm timer
3D	NA	First alarm energized/de-energized selection
3E	NB	Second alarm energized/de-energized selection
3F	P1	Proportional band 1
40	P3	Proportional band 2
41	P5	Proportional band 3
42	P7	Proportional band 4
43	I1	Integral time 1
44	I2	Integral time 2
45	I3	Integral time 3
46	I4	Integral time 4
47	D1	Derivative time 1
48	D2	Derivative tiem 2
49	D3	Derivative tiem 3
4A	D4	Derivative tiem 4
4B	W1	Anti-reset windup 1(ARW)
4C	W2	Anti-reset windup 2(ARW)
4D	W3	Anti-reset windup 3(ARW)
4E	W4	Anti-reset windup 4(ARW)
4F	P2	Cool side proportional band 1
50	P4	Cool side proportional band 2
51	P6	Cool side proportional band 3
52	P8	Cool side proportional band 4
53	V1	Deadband/Overlap 1 / Control motor neutral zone 1
54	V2	Deadband/Overlap 2 / Control motor neutral zone 2
55	V3	Deadband/Overlap 3 / Control motor neutral zone 3
56	V4	Deadband/Overlap 4 / Control motor neutral zone 4

Address	Identifier	Description
57	XP	Fuzzy function 1
58	FW	Fuzzy function 2
59	FX	Fuzzy function 3
5A	FY	Fuzzy function 4
5B	TC	Output cycle 1 / Control motor time
5C	TO	Output cycle 2
5D	OH	Output limit(High limit) / Integrated output limit
5E	OL	Output limit(Low limit)
5F	XE	Direct/reverse action selection
60	KB	OUT2 action selection
61	A3	OUT2 set value
62	XC	OUT3 action selection
63	A4	OUT3 set value
64	XD	OUT4 action selection
65	A5	OUT4 set value
66	LA	Analog output selection
67	HV	Analog output scaling high limit
68	HW	Analog output scaling low limit
69	XI	Input type selection
6A	XV	Scale high limit
6B	XW	Scale low limit
6C	XU	Decimal point position
6D	SS	SV at program start
6E	X1	Control state at program end
6F	XN	Control output value during reset / Control state selection during reset
70	XK	Control input pattern entry method
71	XQ	Water cooling/air cooling selection at heat/cool control
72	PD	Start mode selection
73	GH	Autotuning(AT) differential gap
74	JT	Power frequency
75	B2	Action selection at burnout occurrence
76	WH	Action selection for abnormal PV input
77	XH	Selection of Use/Non-use of square root extraction function
78	PU	Setting time unit selection

MPORT/ • Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."

NOTE

• System area setting that can be used for the temperature controller is reading area size only. Please refer to the GP-Pro EX Reference Manual for system data area.

- Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
- Please refer to the precautions on manual notation for icons in the table.

"Manual Symbols and Terminology"

• Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.15 **REX-P250 Series**

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.0-0024.F	0000-0024	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description		
00	M1	Measured-value(PV)		
01	S1	Set-value(SV)during operation		
02	ON	Manipulated-value(MV)or Manual control output set-value		
03	TR	Segment remaining time		
04	RT	The number of program execution times		
05	M2	Opening feedback input value or Current transformer input value		
06	AA	Alarm 1 output		
07	AB	Alarm 2 output		
08	B1	Burnout		
09	НО	Hold status		
0A	EN	End status		
0B	WT	Wait status		
0C	T1	Time signal No.1 status		
0D	T2	Time signal No.2 status		
0E	Т3	Time signal No.3 status		
0F	T4	Time signal No.4 status		
10	XM	Operation mode		
11	PS	Execution pattern		
12	SN	Execution segment		
13	RA	COMP/LOC identification		
14	G1	AT/PID identification		
15	TT	AT learning function		
16	SK	Step function		
17	S2	Set-value(SV)		
18	PP	PID memory NO.		
19	AP	Alarm memory NO.		
1A	PQ	PID memory NO.		
1B	AQ	Alarm memory NO.		
1C	PB	PV bias		
1D	HA	Alarm 1 hysteresis band		
1E	HB	Alarm 2 hysteresis band		
1F	TC	Proportional cycle setting		
20	F1	Digital filter		
21	XN	Start mode selection		
22	SS	Set-value(SV)selection at start[Program control]		

Address	Identifier	Description
23	ER	Error code
24	CL	Data all clear

IMPORT/	 Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."
NOTE	• System area setting that can be used for the temperature controller is reading area size only. Please
	refer to the GP-Pro EX Reference Manual for system data area.
	Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
	• Please refer to the precautions on manual notation for icons in the table.
	"Manual Symbols and Terminology"
	• Even if non-existing address is used, there are cases when read error is not indicated. In this case,
	zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.16 **REX-AD Series**

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.0-003B.F	0000-003B	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description
00	M1	Measured-value(PV)
01	AA	First alarm monitor
02	AB	Second alarm monitor
03	AC	Third alarm monitor
04	AD	Fourth alarm monitor
05	AE	Fifth alarm monitor
06	AF	Sixth alarm monitor
07	AG	EXCEED monitor
08	B1	Burnout
09	ER	Error data
0A	HP	Peak hold monitor
0B	HQ	Bottom hold monitor
0C	TM	Time duration monitor
0D	HR	Hold reset
0E	IR	Interlock release
0F	A1	First alarm setting
10	A2	Second alarm setting
11	A3	Third alarm setting
12	A4	Fourth alarm setting
13	A5	Fifth alarm setting
14	A6	Sixth alarm setting
15	PB	PV bias
16	F1	Digital filter
17	XA	First alarm action selection
18	QA	First alarm interlock
19	NA	First alarm Energized/De-energized
1A	HA	First alarm differential gap
1B	TD	First alarm timer setting selection
1C	XB	Second alarm action selection
1D	QB	Second alarm interlock
1E	NB	Second alarm Energized/De-energized
1F	HB	Second alarm differential gap
20	TG	Second alarm timer setting selection
21	XC	Third alarm action selection
22	QC	Third alarm interlock

Address	Identifier	Description
23	NC	Third alarm Energized/De-energized
24	НС	Third alarm differential gap
25	TH	Third alarm timer setting selection
26	XD	Fourth alarm action selection
27	QD	Fourth alarm interlock
28	ND	Fourth alarm Energized/De-energized
29	HD	Fourth alarm differential gap
2A	TI	Fourth alarm timer setting selection
2B	XE	Fifth alarm action selection
2C	QE	Fifth alarm interlock
2D	NE	Fifth alarm Energized/De-energized
2E	HE	Fifth alarm differential gap
2F	TJ	Fifth alarm timer setting selection
30	XF	Sixth alarm action selection
31	QF	Sixth alarm interlock
32	NF	Sixth alarm Energized/De-energized
33	HF	Sixth alarm differential gap
34	TK	Sixth alarm timer setting selection
35	HV	Analog output high-limit set-value
36	HW	Analog output low-limit set-value
37	XI	Input type selection
38	XV	Scaling high-limit setting
39	XW	Scaling low-limit setting
3A	XU	Decimal point position selection
3B	TS	Time unit selection setting

MPORT/ • Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."

- **NOTE** System area setting that can be used for the temperature controller is reading area size only. Please refer to the GP-Pro EX Reference Manual for system data area.
 - Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
 - Please refer to the precautions on manual notation for icons in the table.

"Manual Symbols and Terminology"

• Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.17 **REX-PG Series**

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.0-0021.F	0000-0021	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description		
00	M1	Measured-value (PV)		
01	AA	Alarm 1 monitor		
02	AB	Alarm 2 monitor		
03	B1	Burnout		
04	ER	Error data		
05	HP	Peak hold monitor		
06	HQ	Bottom hold monitor		
07	AZ	Auto 0		
08	HR	Hold reset		
09	IR	Alarm interlock release		
0A	A1	First alarm setting		
0B	A2	Second alarm setting		
0C	IB	Operation selection when input break		
0D	TL	Display time setting		
0E	XA	First alarm Action selection		
0F	QA	First alarm interlock function		
10	NA	First alarm Energized/de-energized selection		
11	HA	First alarm differential gap		
12	TD	First alarm timer setting		
13	XB	Second alarm Action selection		
14	QB	Second alarm interlock function		
15	NB	Second alarm Energized/de-energized selection		
16	HB	Second alarm differential gap		
17	TG	Second alarm timer setting		
18	HW	Low limit analog output range		
19	HV	High limit analog output range		
1A	ТО	Analog output time setting		
1B	XI	Input type selection		
1C	GA	Gain setting		
1D	PU	Pressure unit setting		
1E	XU	Decimal-point position selection		
1F	XW	Pressure display low limit setting		
20	XV	Pressure display high limit setting		
21	LI	Linearizing type selection		

IMPORT/	Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."
NOTE	System area setting that can be used for the temperature controller is reading area size only. Please
	refer to the GP-Pro EX Reference Manual for system data area.
	Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
•	Please refer to the precautions on manual notation for icons in the table.
	"Manual Symbols and Terminology"
•	Even if non-existing address is used, there are cases when read error is not indicated. In this case,
	zero (0) is kept for read out data. On the other hand, writing error is indicated.

6.18 AE500 Series

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.0-0012.F	0000-0012	[L/H]	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description
00	M1	Measured value (PV)
01	AA	Alarm 1 monitor
02	AB	Alarm 2 monitor
03	AC	Alarm 3 monitor
04	AD	Alarm 4 monitor
05	B1	Burnout
06	ER	Error code
07	A1	Alarm 1 setting
08	A2	Alarm 2 setting
09	A3	Alarm 3 setting
0A	A4	Alarm 4 setting
0B	HA	Alarm 1 differential gap setting
0C	HB	Alarm 2 differential gap setting
0D	HC	Alarm 3 differential gap setting
0E	HD	Alarm 4 differential gap setting
0F	PB	PV bias
10	HV	Analog output scale high
11	HW	Analog output scale low
12	LK	Set data lock function

<Communication identifier list>

IMPORT/	Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."
NOTE	System area setting that can be used for the temperature controller is reading area size only. Please
•	refer to the GP-Pro EX Reference Manual for system data area.

- Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
- Please refer to the precautions on manual notation for icons in the table.

"Manual Symbols and Terminology"

• Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

LE100 Series 6.19

This address can be specified as system data area.

Device	Bit Address	Word Address	32 bits	Notes
Communication identifier	0000.0-0072.F	0000-0072	<u>[[] H</u>	*1 *2

*1 There are cases for which writing is not available depending on the device address. Check the identifying attributes of the external device's manual before use.

*2 When bit is written, the indicator reads the corresponding word address of external device, assign a bit to the read word address, and return to the external device. There are cases when correct data cannot be written if the word address is written using a ladder program, while the indicator reads data of the external device and sends it back.

Address	Identifier	Description		
00	M1	Measured value (PV)		
01	AA	Output 1 status		
02	AB	Output 2 status		
03	AC	Output 3 status		
04	AD	Output 4 status		
05	AE	Output 5 status		
06	AF	Output 6 status		
07	AG	Output 7 status		
08	AH	Output 8 status		
09	B1	Burnout		
0A	ER	Error code		
0B	ID	ID data		
0C	ID	ID data		
0D	ID	ID data		
0E	MS	Specific gravity monitor		
0F	ML	Scale low monitor		
10	MH	Scale high monitor		
11	HP	Peak hold monitor		
12	HQ	Bottom hold monitor		
13	MW	Number of wafer processing times monitor		
14	MZ	Amount of emptiness correction monitor		
15	A1	Output 1 set value		
16	A2	Output 2 set value		
17	A3	Output 3 set value		
18	A4	Output 4 set value		
19	A5	Output 5 set value		
1A	A6	Output 6 set value		
1B	A7	Output 7 set value		
1C	A8	Output 8 set value		
1D	A9	Actual liquid output setting		
1E	AZ	Emptiness adjustment		
1F	WT	Number of wafer processing times		
20	CW	Initializing the number of wafer processing times		
21	HR	Hold reset		
22	IR	Interlock release		

Address	Identifier	Description		
23	LK	Set data lock		
24	IS	Default setting		
25	EC	Error release		
26	LU	Decimal point position selection		
27	LT	Number of linearizing table setting		
28	L0	Linearizing table setting 0		
29	L1	Linearizing table setting 1		
2A	L2	Linearizing table setting 2		
2B	L3	Linearizing table setting 3		
2C	L4	Linearizing table setting 4		
2D	L5	Linearizing table setting 5		
2E	L6	Linearizing table setting 6		
2F	L7	Linearizing table setting 7		
30	L8	Linearizing table setting 8		
31	L9	Linearizing table setting 9		
32	LA	Linearizing table setting 10		
33	F1	Digital filter		
34	XA	Output 1 type selection		
35	DA	Output 1 deviation value setting		
36	QA	Output 1 interlocking function selection		
37	NA	Output 1 a/b contact selection		
38	HA	Output 1 differential gap		
39	TA	Output 1 timer setting		
3A	XB	Output 2 type selection		
3B	DB	Output 2 deviation value setting		
3C	QB	Output 2 interlocking function selection		
3D	NB	Output 2 a/b contact selection		
3E	HB	Output 2 differential gap		
3F	TB	Output 2 timer setting		
40	XC	Output 3 type selection		
41	DC	Output 3 deviation value setting		
42	QC	Output 3 interlocking function selection		
43	NC	Output 3 a/b contact selection		
44	HC	Output 3 differential gap		
45	TC	Output 3 timer setting		
46	XD	Output 4 type selection		
47	DD	Output 4 deviation value setting		
48	QD	Output 4 interlocking function selection		
49	ND	Output 4 a/b contact selection		
4A	HD	Output 4 differential gap		
4B	TD	Output 4 timer setting		
4C	XE	Output 5 type selection		
4D	DE	Output 5 deviation value setting		
4E	QE	Output 5 interlocking function selection		
4F	NE	Output 5 a/b contact selection		
50	HE	Output 5 differential gap		
51	TE	Output 5 timer setting		
52	XF	Output 6 type selection		
53	DF	Output 6 deviation value setting		
54	QF	Output 6 interlocking function selection		
55	NF	Output 6 a/b contact selection		
56	HF	Output 6 differential gap		

Address	Identifier	Description		
57	TF	Output 6 timer setting		
58	XG	Output 7 type selection		
59	DG	Output 7 deviation value setting		
5A	QG	Output 7 interlocking function selection		
5B	NG	Output 7 a/b contact selection		
5C	HG	Output 7 differential gap		
5D	TG	Output 7 timer setting		
5E	XH	Output 8 type selection		
5F	DH	Output 8 deviation value setting		
60	QH	Output 8 interlocking function selection		
61	NH	Output 8 a/b contact selection		
62	HH	Output 8 differential gap		
63	TH	Output 8 timer setting		
64	HV	Monitor output high		
65	HW	Monitor output low		
66	EG	End specific gravity setting		
67	SW	Number of wafer processing times setting		
68	XX	Scale low		
69	SG	Specific gravity setting		
6A	J1	Scale 1 actual liquid setting		
6B	J2	Scale 2 actual liquid setting		
6C	J3	Correction on the low limit side by actual liquid 2		
6D	J4	Correction on the high limit side by actual liquid 2		
6E	UN	Unit setting		
6F	SP	Specific gravity setting transfer		
70	SS	Specific gravity correction function selection		
71	DS	DI function selection		
72	MM	Volume/level display selection		

IMPORT/ • Setting "Use system data area" to GP-Pro EX system area result in improper operation. Do not set "Use system data area."

• System area setting that can be used for the temperature controller is reading area size only. Please refer to the GP-Pro EX Reference Manual for system data area.

- Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
- Please refer to the precautions on manual notation for icons in the table.

"Manual Symbols and Terminology"

• Even if non-existing address is used, there are cases when read error is not indicated. In this case, zero (0) is kept for read out data. On the other hand, writing error is indicated.

7 Device Code and Address Code

Use device code and address code when you select "Device Type & Address" for the address type in data displays.

7.1 CB Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.2 FB Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.3 HA Series

Device	Device Name	Device Code (HEX)	Address Code	
Communication identifier	-	0080	Word Address	

7.4 MA Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.5 SRV Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.6 SRX Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.7 SA Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.8 SR Mini HG(H-PCP-A/B) Series

Device	Device Name	Device Code (HEX)	Address Code
	-	0080	
	-	0180	
	-	0280	
	-	0380	
	-	0480	
	-	0580	
	-	0680	
	-	0780	
	-	0880	
Communication identifier	-	0980	Word Address
Communication identifier	-	0A80	word Address
	-	0B80	
	-	0C80	
	-	0D80	
	-	0E80	
	-	0F80	
	-	1080	
	-	1180	
	-	1280	
	-	1380	

7.9 SR Mini HG(H-PCP-J) Series

Device	Device Name	Device Code (HEX)	Address Code
	-	0080	
	-	0180	
	-	0280	
	-	0380	
	-	0480	
	-	0580	
	-	0680	
	-	0780	
	-	0880	
Communication identifier	-	0980	Word Address
Communication identifier	-	0A80	word Address
	-	0B80	
	-	0C80	
	-	0D80	
	-	0E80	
	-	0F80	
	-	1080	
	-	1180	
	-	1280	
	-	1380	

7.10 REX-F9000 Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.11 REX-F Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.12 REX-D Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.13 REX-G9 Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.14 REX-P300 Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.15 REX-P250 Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.16 REX-AD Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.17 REX-PG Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.18 AE500 Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

7.19 LE100 Series

Device	Device Name	Device Code (HEX)	Address Code
Communication identifier	-	0080	Word Address

8 Error Messages

Error messages are displayed on the screen of Display as follows: "No. : Device Name: Error Message (Error Occurrence Area)". Each description is shown below.

Item	Description	
No.	Error No.	
Device Name	Name of External Device where error occurs. Device name is a title of External Device set with GP-Pro EX.((Initial value [PLC1])	
Error Message	Displays messages related to the error which occurs.	
Error Occurrence Area	Displays IP address or device address of External Device where error occurs, or error codes received from External Device.	
	 NOTE IP address is displayed such as "IP address (Decimal): MAC address (Hex)". Device address is displayed such as "Address: Device address". Received error codes are displayed such as "Decimal [Hex]". 	

Display Examples of Error Messages

"RHAA035: PLC1: Error has been responded for device write command (Error Code: 2 [02H])"

NOTE
Please refer to the manual of External Device for more detail of received error codes.
Please refer to "When an error message is displayed (Error code list)" of "Maintenance/ Troubleshooting" for a common error message to the driver.