




# Uni-Telway Driver

|   |                                        |    |
|---|----------------------------------------|----|
| 1 | System Configuration.....              | 3  |
| 2 | Selection of External Device .....     | 7  |
| 3 | Example of Communication Setting ..... | 8  |
| 4 | Setup Items.....                       | 23 |
| 5 | Cable Diagram .....                    | 28 |
| 6 | Supported Device.....                  | 50 |
| 7 | Device Code and Address Code.....      | 54 |
| 8 | Error Messages.....                    | 55 |

## Introduction

This manual describes how to connect the Display and the External Device (target PLC).

In this manual, the connection procedure will be described by following the below sections:



# 1 System Configuration


The system configuration in the case when the External Device of Schneider Electric Industries and the Display are connected is shown.

| Series  | CPU                                                                                                                                                                                                                                | Link I/F                                      | SIO Type          | Setting Example             | Cable Diagram             |
|---------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------|-------------------|-----------------------------|---------------------------|
| Nano    | TSX 07 3L □ □ 28<br>TSX 07 30 10 □ □<br>TSX 07 31 16 □ □<br>TSX 07 31 24 □ □<br>TSX 07 32 □ □ 28<br>TSX 07 33 □ □ 28                                                                                                               | Programming port on CPU                       | RS232C            | Setting Example 1 (page 8)  | Cable Diagram 1 (page 30) |
|         |                                                                                                                                                                                                                                    |                                               | RS422/485 (2wire) | Setting Example 2 (page 11) | Cable Diagram 2 (page 31) |
|         |                                                                                                                                                                                                                                    | Accessory box AUX or TER port on TSX P ACC 01 | RS422/485 (2wire) | Setting Example 2 (page 11) | Cable Diagram 2 (page 31) |
|         |                                                                                                                                                                                                                                    | Accessory box TSX SCA 62                      | RS422/485 (2wire) | Setting Example 2 (page 11) | Cable Diagram 3 (page 35) |
| Micro   | TSX 37 05 028DR1<br>TSX 37 08 056DR1<br>TSX 37 10 128DT1<br>TSX 37 10 128DR1<br>TSX 37 10 128DTK1<br>TSX 37 10 164DTK1<br>TSX 37 10 028AR1<br>TSX 37 10 028DR1<br>TSX 37 21 101<br>TSX 37 22 101<br>TSX 37 21 001<br>TSX 37 22 001 | TER port on CPU                               | RS232C            | Setting Example 3 (page 14) | Cable Diagram 1 (page 30) |
|         |                                                                                                                                                                                                                                    |                                               | RS422/485 (2wire) | Setting Example 4 (page 17) | Cable Diagram 2 (page 31) |
|         |                                                                                                                                                                                                                                    | AUX port on CPU                               | RS422/485 (2wire) | Setting Example 4 (page 17) | Cable Diagram 2 (page 31) |
|         |                                                                                                                                                                                                                                    | Accessory box AUX or TER port on TSX P ACC 01 | RS422/485 (2wire) | Setting Example 4 (page 17) | Cable Diagram 2 (page 31) |
|         |                                                                                                                                                                                                                                    | Accessory box TSX SCA 62                      | RS422/485 (2wire) | Setting Example 4 (page 17) | Cable Diagram 3 (page 35) |
|         | TSX 37 21 101<br>TSX 37 22 101<br>TSX 37 21 001<br>TSX 37 22 001                                                                                                                                                                   | PCMCIA card TSX SCP 114 for RS485             | RS422/485 (2wire) | Setting Example 5 (page 20) | Cable Diagram 4 (page 39) |
|         |                                                                                                                                                                                                                                    |                                               |                   |                             |                           |
| Premium | TSX P57 103M<br>TSX P57 153M<br>TSX P57 203M<br>TSX P57 253M<br>TSX P57 303M<br>TSX P57 353M<br>TSX P57 453M                                                                                                                       | TER port on CPU                               | RS232C            | Setting Example 3 (page 14) | Cable Diagram 1 (page 30) |
|         |                                                                                                                                                                                                                                    |                                               | RS422/485 (2wire) | Setting Example 4 (page 17) | Cable Diagram 2 (page 31) |
|         |                                                                                                                                                                                                                                    | AUX port on CPU                               | RS422/485 (2wire) | Setting Example 4 (page 17) | Cable Diagram 2 (page 31) |
|         |                                                                                                                                                                                                                                    | Accessory box AUX or TER port on TSX P ACC 01 | RS422/485 (2wire) | Setting Example 4 (page 17) | Cable Diagram 2 (page 31) |
|         |                                                                                                                                                                                                                                    | Accessory box TSX SCA 62                      | RS422/485 (2wire) | Setting Example 4 (page 17) | Cable Diagram 3 (page 35) |
|         |                                                                                                                                                                                                                                    | PCMCIA card TSX SCP 114 for RS485             | RS422/485 (2wire) | Setting Example 5 (page 20) | Cable Diagram 4 (page 39) |
|         |                                                                                                                                                                                                                                    | Communication Module TSX SCY 21601 for RS485  | RS422/485 (2wire) | Setting Example 4 (page 17) | Cable Diagram 5 (page 46) |


## ■ Connection Configuration

### ◆ Nano Series

- 1:1 Connection




- n:1 Connection




### ◆ Micro Series

- 1:1 Connection


You can connect the display to TER port, AUX port or PCMCIA card. Simultaneous connection is also available.



- n:1 Connection (when using accessory box)




- n:1 Connection (when using PCMCIA card for RS485)




### ◆ Premium Series

- 1:1 Connection


You can connect the display to TER port, AUX port, PCMCIA card or communication module. Simultaneous connection is also available.



- n:1 Connection (when using accessory box)



- n:1 Connection (when using PCMCIA card for RS485)



## 2 Selection of External Device

Select the External Device to be connected to the Display.

**New Project File**

Device/PLC

Maker: Schneider Electric Industries

Driver: Uni-Telway

☐ Use System Area [Refer to the manual of this Device/PLC](#)

Connection Method

Port: COM1

[Go to Device/PLC Manual](#)

Back Communication Detail Settings New Screen Cancel

| Setup Items     | Setup Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
|-----------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Maker           | Select the maker of the External Device to be connected. Select "Schneider Electric Industries".                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
| Driver          | Select a model (series) of the External Device to be connected and connection method. Select "Uni-Telway".<br>Check the External Device which can be connected in "Uni-Telway" in system configuration.<br>☞ "1 System Configuration" (page 3)                                                                                                                                                                                                                                                                                                                                                                                                                          |
| Use System Area | Check this option when you synchronize the system data area of Display and the device (memory) of External Device. When synchronized, you can use the ladder program of External Device to switch the display or display the window on the display.<br>Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"<br>This can be also set with GP-Pro EX or in off-line mode of Display.<br>Cf. GP-Pro EX Reference Manual " 5.14.6 Setting Guide of [System Setting Window]■[Main Unit Settings] Settings Guide◆System Area Setting"<br>Cf. Maintenance/Troubleshooting "2.14.1 Settings common to all Display models◆System Area Settings" |
| Port            | Select the Display port to be connected to the External Device.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |

### 3 Example of Communication Setting

Examples of communication settings of the Display and the External Device, recommended by Pro-face, are shown.

#### 3.1 Setting Example 1

##### ■ Setting of GP-Pro EX

##### ◆ Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1

Summary [Change Device/PLC](#)

Maker  Series  Port

Text Data Mode  [Change](#)

Communication Settings

SIO Type ☒ RS232C ☐ RS422/485(2wire) ☐ RS422/485(4wire)  
 Speed   
 Data Length ☐ 7 ☒ 8  
 Parity ☐ NONE ☐ EVEN ☒ ODD  
 Stop Bit ☒ 1 ☐ 2  
 Flow Control ☒ NONE ☐ ER(DTR/CTS) ☐ XON/XOFF  
 Timeout  (sec)

Client Address   
 No. of Consecutive Address

RI / VCC ☒ RI ☐ VCC  
 In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.

[Default](#)

Device-Specific Settings


Allowable No. of Device/PLCs 16 Unit(s)

| No. | Device Name | Settings                                                               |
|-----|-------------|------------------------------------------------------------------------|
| 1   | PLC1        | Network=0,Station=254,Gate=0,Selector=0,Connection Pt. / Module=254,Re |

### ◆ Device Setting

To display the setting screen, click  ([Setting]) of External Device you want to set from [Device-Specific Settings] of [Device/PLC Settings].

When [Allowable No. of Device/PLCs] is multiple, you can click  from [Device-Specific Settings] of [Device/PLC Settings] to add External Device which is available to set.



The dialog box titled "Individual Device Settings" for PLC1 contains the following sections:

- Address:** A group box containing six spinners: Network (0), Station (254), Gate (0), Selector (0), Connection Pt. / Module (254), and Reference / Channel (0).
- Communication Optimization:** A group box with "Preferred Frame Length" set to "Maximum Possible" (selected). Other options are "128 Bytes", "32 Bytes", and "Minimum Possible".
- Bit manipulation [set/reset] to Internal Device:** A group box with "Rest of the bits in this device" set to "Do not clear" (selected). Other option is "Clear". Below this is a note: "Note on when selecting 'Do not clear': If the ladder program writes data to Internal Device during the read/write process, the resulting data may be incorrect."
- Variables:** A group box with "Double Word word order" set to "Low word first" (selected via a dropdown menu).

At the bottom right are buttons for "Default", "OK (O)", and "Cancel".

## ■ Setting of External Device

Use the ladder software "PL7-07" for communication settings on External Device.

Select [Programming Port] from [Configuration] in PL7-07 and perform the communication settings as below.

| Setup Items      | Setup Description |
|------------------|-------------------|
| Type             | UNI-TELWAY Master |
| Bit/sec          | 19200             |
| DateBits         | 8 bits            |
| ParityOdd        | Odd               |
| Stop Bits        | 1 bit             |
| Number of Slaves | 8                 |

### ◆ Notes

- Do not set the address which exceeds "Number of Slaves" on External Device in Server Address and Clients Address. If you set the address which exceeds "Number of Slaves" in Server Address and Clients Address, timeout error will occur, which disables the communication with the External Device. In addition, when you connect many client devices (Display/External Device) on the same serial network, set the longer timeout on the Display.

## 3.2 Setting Example 2

### ■ Setting of GP-Pro EX

#### ◆ Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1

Summary [Change Device/PLC](#)

Maker  Series  Port

Text Data Mode  [Change](#)

Communication Settings

SIO Type ☐ RS232C ☒ RS422/485(2wire) ☐ RS422/485(4wire)

Speed

Data Length ☐ 7 ☒ 8

Parity ☐ NONE ☐ EVEN ☒ ODD

Stop Bit ☒ 1 ☐ 2

Flow Control ☒ NONE ☐ ER(DTR/CTS) ☐ XON/XOFF

Timeout  (sec)

Client Address

No. of Consecutive Address

RI / VCC ☒ RI ☐ VCC

In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.

[Default](#)

Device-Specific Settings


Allowable No. of Device/PLCs 16 Unit(s)

| No. | Device Name | Settings                                                               |
|-----|-------------|------------------------------------------------------------------------|
| 1   | PLC1        | Network=0,Station=254,Gate=0,Selector=0,Connection Pt. / Module=254,Re |

### ◆ Device Setting

To display the setting screen, click  ([Setting]) of External Device you want to set from [Device-Specific Settings] of [Device/PLC Settings].

When [Allowable No. of Device/PLCs] is multiple, you can click  from [Device-Specific Settings] of [Device/PLC Settings] to add External Device which is available to set.



The dialog box is titled "Individual Device Settings" and has a close button (X) in the top right corner. It is for "PLC1".

**Address**

|                         |     |
|-------------------------|-----|
| Network                 | 0   |
| Station                 | 254 |
| Gate                    | 0   |
| Selector                | 0   |
| Connection Pt. / Module | 254 |
| Reference / Channel     | 0   |

**Communication Optimization**

Preferred Frame Length

- ☒ Maximum Possible
- ☐ 128 Bytes
- ☐ 32 Bytes
- ☐ Minimum Possible

**Bit manipulation [set/reset] to Internal Device**

Rest of the bits in this device

- ☐ Clear
- ☒ Do not clear

Note on when selecting "Do not clear":  
If the ladder program writes data to Internal Device during the read/write process, the resulting data may be incorrect.

**Variables**

Double Word word order: Low word first

Buttons: Default, OK (O), Cancel

## ■ Setting of External Device

Use the ladder software "PL7-07" for communication settings on External Device.

Select [Programming Port] from [Configuration] in PL7-07 and perform the communication settings as below.

| Setup Items      | Setup Description |
|------------------|-------------------|
| Type             | UNI-TELWAY Master |
| Bit/sec          | 19200             |
| DateBits         | 8 bits            |
| ParityOdd        | Odd               |
| Stop Bits        | 1 bit             |
| Number of Slaves | 8                 |

### ◆ Notes

- Do not set the address which exceeds "Number of Slaves" on External Device in Server Address and Clients Address. If you set the address which exceeds "Number of Slaves" in Server Address and Clients Address, timeout error will occur, which disables the communication with the External Device. In addition, when you connect many client devices (Display/External Device) on the same serial network, set the longer timeout on the Display.

### 3.3 Setting Example 3

#### ■ Setting of GP-Pro EX

##### ◆ Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1

Summary

Maker  Series  Port  [Change Device/PLC](#)

Text Data Mode  [Change](#)

Communication Settings

SID Type ☒ RS232C ☐ RS422/485(2wire) ☐ RS422/485(4wire)  
 Speed   
 Data Length ☐ 7 ☒ 8  
 Parity ☐ NONE ☐ EVEN ☒ ODD  
 Stop Bit ☒ 1 ☐ 2  
 Flow Control ☒ NONE ☐ ER(DTR/CTS) ☐ XON/XOFF  
 Timeout  (sec)

Client Address   
 No. of Consecutive Address

RI / VCC ☒ RI ☐ VCC  
 In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.

Default

Device-Specific Settings


Allowable No. of Device/PLCs: 16 Unit(s)

| No. | Device Name | Settings                                                                    |
|-----|-------------|-----------------------------------------------------------------------------|
| 1   | PLC1        | Network=0, Station=254, Gate=0, Selector=0, Connection Pt. / Module=254, Re |

### ◆ Device Setting

To display the setting screen, click  ([Setting]) of External Device you want to set from [Device-Specific Settings] of [Device/PLC Settings].

When [Allowable No. of Device/PLCs] is multiple, you can click  from [Device-Specific Settings] of [Device/PLC Settings] to add External Device which is available to set.



The dialog box is titled "Individual Device Settings" and is for "PLC1". It contains several sections:

- Address:** A group box containing six spinners: Network (0), Station (254), Gate (0), Selector (0), Connection Pt. / Module (254), and Reference / Channel (0).
- Communication Optimization:** A group box with a "Preferred Frame Length" section containing four radio buttons: "Maximum Possible" (selected), "128 Bytes", "32 Bytes", and "Minimum Possible".
- Bit manipulation [set/reset] to Internal Device:** A group box with a "Rest of the bits in this device" section containing two radio buttons: "Clear" and "Do not clear" (selected). Below this is a note: "Note on when selecting 'Do not clear': If the ladder program writes data to Internal Device during the read/write process, the resulting data may be incorrect."
- Variables:** A group box with a "Double Word word order" section containing a dropdown menu set to "Low word first".

At the bottom right, there are three buttons: "Default", "OK (O)", and "Cancel".

## ■ Setting of External Device

Use the ladder software "PL7-07" for communication settings on External Device.

Go to [Configuration] in [Application Browser], [Hardware Configuration] and [Comm] in this order in "PL7-07", and perform the communication settings as below.

| Setup Items        | Setup Description |
|--------------------|-------------------|
| CHANNEL            | CHANNEL 0         |
|                    | UNI-TELWAY LINK   |
| Type               | Master            |
| Transmission Speed | 19200             |
| Data               | 8 bits            |
| Parity             | Odd               |
| Stop               | 1 bit             |
| Number of Slaves   | 8                 |

### ◆ Notes

- Do not set the address which exceeds "Number of Slaves" on External Device in Server Address and Clients Address. If you set the address which exceeds "Number of Slaves" in Server Address and Clients Address, timeout error will occur, which disables the communication with the External Device. In addition, when you connect many client devices (Display/External Device) on the same serial network, set the longer timeout on the Display.

### 3.4 Setting Example 4

#### ■ Setting of GP-Pro EX

##### ◆ Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1

Summary [Change Device/PLC](#)

Maker  Series  Port

Text Data Mode  [Change](#)

Communication Settings

SIO Type ☐ RS232C ☒ RS422/485(2wire) ☐ RS422/485(4wire)

Speed

Data Length ☐ 7 ☒ 8

Parity ☐ NONE ☐ EVEN ☒ ODD

Stop Bit ☒ 1 ☐ 2

Flow Control ☒ NONE ☐ ER(DTR/CTS) ☐ XON/XOFF

Timeout  (sec)

Client Address

No. of Consecutive Address

RI / VCC ☒ RI ☐ VCC

In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.

[Default](#)

Device-Specific Settings


Allowable No. of Device/PLCs 16 Unit(s)

| No. | Device Name | Settings                                                               |
|-----|-------------|------------------------------------------------------------------------|
| 1   | PLC1        | Network=0,Station=254,Gate=0,Selector=0,Connection Pt. / Module=254,Re |

### ◆ Device Setting

To display the setting screen, click  ([Setting]) of External Device you want to set from [Device-Specific Settings] of [Device/PLC Settings].

When [Allowable No. of Device/PLCs] is multiple, you can click  from [Device-Specific Settings] of [Device/PLC Settings] to add External Device which is available to set.



The dialog box titled "Individual Device Settings" for PLC1 contains the following sections:

- Address:** A group box containing six spinners: Network (0), Station (254), Gate (0), Selector (0), Connection Pt. / Module (254), and Reference / Channel (0).
- Communication Optimization:** A group box with "Preferred Frame Length" set to "Maximum Possible" (selected via radio button). Other options are "128 Bytes", "32 Bytes", and "Minimum Possible".
- Bit manipulation [set/reset] to Internal Device:** A group box with "Rest of the bits in this device" set to "Do not clear" (selected via radio button). The other option is "Clear". A note below states: "Note on when selecting 'Do not clear': If the ladder program writes data to Internal Device during the read/write process, the resulting data may be incorrect."
- Variables:** A group box with "Double Word word order" set to "Low word first" (selected via a dropdown menu).

At the bottom right, there are three buttons: "Default", "OK (O)", and "Cancel".

## ■ Setting of External Device

Use the ladder software "PL7-07" for communication settings on External Device.

Go to [Configuration] in [Application Browser], [Hardware Configuration] and [Comm] in this order in "PL7-07", and perform the communication settings as below.

| Setup Items       | Setup Description |
|-------------------|-------------------|
| CHANNEL           | CHANNEL 0         |
|                   | UNI-TELWAY LINK   |
| Type              | Master            |
| Trasmission Speed | 19200             |
| Data              | 8 bits            |
| Parity            | Odd               |
| Stop              | 1 bit             |
| Number of Slaves  | 8                 |

### ◆ Notes

- Do not set the address which exceeds "Number of Slaves" on External Device in Server Address and Clients Address. If you set the address which exceeds "Number of Slaves" in Server Address and Clients Address, timeout error will occur, which disables the communication with the External Device. In addition, when you connect many client devices (Display/External Device) on the same serial network, set the longer timeout on the Display.

## 3.5 Setting Example 5

### ■ Setting of GP-Pro EX

#### ◆ Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1

Summary [Change Device/PLC](#)

Maker  Series  Port

Text Data Mode  [Change](#)

Communication Settings

SIO Type ☐ RS232C ☒ RS422/485(2wire) ☐ RS422/485(4wire)

Speed

Data Length ☐ 7 ☒ 8

Parity ☐ NONE ☐ EVEN ☒ ODD

Stop Bit ☒ 1 ☐ 2

Flow Control ☒ NONE ☐ ER(DTR/CTS) ☐ XON/XOFF

Timeout  (sec)

Client Address

No. of Consecutive Address

RI / VCC ☒ RI ☐ VCC

In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.

[Default](#)

Device-Specific Settings


Allowable No. of Device/PLCs 16 Unit(s)

| No. | Device Name | Settings                                                               |
|-----|-------------|------------------------------------------------------------------------|
| 1   | PLC1        | Network=0,Station=254,Gate=0,Selector=0,Connection Pt. / Module=254,Re |

### ◆ Device Setting

To display the setting screen, click  ([Setting]) of External Device you want to set from [Device-Specific Settings] of [Device/PLC Settings].

When [Allowable No. of Device/PLCs] is multiple, you can click  from [Device-Specific Settings] of [Device/PLC Settings] to add External Device which is available to set.



The dialog box is titled "Individual Device Settings" and contains the following sections:

- PLC1** (Header)
- Address** (Group box):
  - Network: 0
  - Station: 254
  - Gate: 0
  - Selector: 0
  - Connection Pt. / Module: 254
  - Reference / Channel: 0
- Communication Optimization** (Group box):
  - Preferred Frame Length:
    - ☒ Maximum Possible
    - ☐ 128 Bytes
    - ☐ 32 Bytes
    - ☐ Minimum Possible
- Bit manipulation [set/reset] to Internal Device** (Group box):
  - Rest of the bits in this device:
    - ☐ Clear
    - ☒ Do not clear
  - Note on when selecting "Do not clear":  
If the ladder program writes data to Internal Device during the read/write process, the resulting data may be incorrect.
- Variables** (Group box):
  - Double Word word order: Low word first (dropdown menu)
- Buttons**: Default, OK (O), Cancel

## ■ Setting of External Device

Use the ladder software "PL7-07" for communication settings on External Device.

Go to [Configuration] in [Application Browser], [Hardware Configuration] and [Comm] in this order in "PL7-07", and perform the communication settings as below.

| Setup Items       | Setup Description                |
|-------------------|----------------------------------|
| CHANNEL           | CHANNEL 1                        |
|                   | TSX SCP 114 RS485 MP PCMCIA CARD |
|                   | UNI-TELWAY LINK                  |
| Type              | Master                           |
| Trasmission Speed | 19200                            |
| Data              | 8 bits                           |
| Parity            | Odd                              |
| Stop              | 1 bit                            |
| Number of Slaves  | 8                                |

### ◆ Notes

- Do not set the address which exceeds "Number of Slaves" on External Device in Server Address and Clients Address. If you set the address which exceeds "Number of Slaves" in Server Address and Clients Address, timeout error will occur, which disables the communication with the External Device. In addition, when you connect many client devices (Display/External Device) on the same serial network, set the longer timeout on the Display.

## 4 Setup Items

Set communication settings of Display with GP-Pro EX or in off-line mode of Display.

The setting of each parameter must be identical to that of External Device.

☞ "3 Example of Communication Setting" (page 8)

### 4.1 Setup Items in GP-Pro EX

#### ■ Communication Settings

To display the setting screen, select [Device/PLC Settings] from [System setting window] in workspace.

Device/PLC 1

Summary

Maker  Series  Port  [Change Device/PLC](#)

Text Data Mode  [Change](#)

Communication Settings

SIO Type ☒ RS232C ☐ RS422/485(2wire) ☐ RS422/485(4wire)

Speed

Data Length ☐ 7 ☒ 8

Parity ☐ NONE ☐ EVEN ☒ ODD

Stop Bit ☒ 1 ☐ 2

Flow Control ☒ NONE ☐ ER(DTR/CTS) ☐ XON/XOFF

Timeout  (sec)

Client Address

No. of Consecutive Address

RI / VCC ☒ RI ☐ VCC

In the case of RS232C, you can select the 9th pin to RI (Input) or VCC (5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.

Default

Device-Specific Settings

Allowable No. of Device/PLCs: 16 Unit(s)

No. Device Name Settings

1 PLC1


| Setup Items                              | Setup Description                                                                                                         |
|------------------------------------------|---------------------------------------------------------------------------------------------------------------------------|
| SIO Type                                 | Select the SIO type to communicate with the External Device.                                                              |
| Speed                                    | Select speed between the External Device and the Display.                                                                 |
| Data Length                              | Display data length.                                                                                                      |
| Parity                                   | Select how to check parity.                                                                                               |
| Stop Bit                                 | Select stop bit length.                                                                                                   |
| Flow Control                             | Display the communication control method to prevent overflow of transmission and reception data.                          |
| Timeout                                  | Use an integer from 1 to 127 to enter the time (s) for which the Display waits for the response from the External Device. |
| Client Address                           | Use an integer from 1 to 98 to enter the client address (source address).                                                 |
| No. of Consecutive Address <sup>*1</sup> | Use an integer 1 to 5 to enter the No. of consecutive address.                                                            |
| RI/VCC                                   | You can switch RI/VCC of the 9th pin when you select RS232C for SIO type.                                                 |

<sup>\*1</sup> Set the value of "Client address + Consecutive address number - 1" to 98 or less. Address which exceeds 98 is not used because it is not polled from the master.

## ■ Device Setting

To display the setting screen, click  ([Setting]) of External Device you want to set from [Device-Specific Settings] of [Device/PLC Settings].

When [Allowable No. of Device/PLCs] is multiple, you can click  from [Device-Specific Settings] of [Device/PLC Settings] to add External Device which is available to set.



**Individual Device Settings**

PLC1

Address

Network: 0

Station: 254

Gate: 0

Selector: 0

Connection Pt. / Module: 254

Reference / Channel: 0

Communication Optimization

Preferred Frame Length: ☒ Maximum Possible  
☐ 128 Bytes  
☐ 32 Bytes  
☐ Minimum Possible

Bit manipulation [set/reset] to Internal Device

Rest of the bits in this device: ☐ Clear  
☒ Do not clear

Note on when selecting "Do not clear":  
 If the ladder program writes data to Internal Device during the read/write process, the resulting data may be incorrect.

Variables

Double Word word order: Low word first

Default

OK (O) Cancel

| Setup Items                          | Setup Description                                                                                                                                    |
|--------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------|
| Network                              | Enter the Network No. of the destination External Device.                                                                                            |
| Station                              | Enter the station No. in the network.                                                                                                                |
| Gate                                 | Enter the gate No. in the network.                                                                                                                   |
| Selector                             | Enter the connected communication channel. This item becomes available only when the gate value is "8."                                              |
| Connection Pt./Module                | Enter the connection point in case of Level 6 Addressing, and enter the module number in case of Level 5 Addressing.                                 |
| Reference/Channel                    | Enter the reference in case of Level 6 Addressing, and enter the channel in case of Level 5 Addressing.                                              |
| Preferred Frame Length               | Specify the frame length.                                                                                                                            |
| Rest of the bits in this device      | From "Clear" or "Do not clear", select treatment of the rest of the bits in the same word when the bit manipulation to Internal Device is performed. |
| Double Word word order <sup>*1</sup> | Specify the word order when displaying the 16-bit device in 32-bit.                                                                                  |

\*1 When you change the word order, set all devices in the screen data again.

## 4.2 Setup Items in Off-Line Mode

**NOTE**

- Please refer to Maintenance/Troubleshooting for more information on how to enter off-line mode or about operation.

Cf. Maintenance/Troubleshooting "2.2 Offline Mode"

### ■ Communication Settings

To display the setting screen, touch [Device/PLC Settings] from [Peripheral Settings] in off-line mode. Touch the External Device you want to set from the displayed list.

| Comm.                      | Device                                                                                     | Option |  |                        |
|----------------------------|--------------------------------------------------------------------------------------------|--------|--|------------------------|
| Uni-Telway [COM1] Page 1/1 |                                                                                            |        |  |                        |
| SIO Type                   | RS232C                                                                                     |        |  |                        |
| Speed                      | 19200                                                                                      |        |  |                        |
| Data Length                | 8                                                                                          |        |  |                        |
| Parity                     | <input type="radio"/> NONE <input type="radio"/> EVEN <input checked="" type="radio"/> ODD |        |  |                        |
| Stop Bit                   | <input checked="" type="radio"/> 1 <input type="radio"/> 2                                 |        |  |                        |
| Flow Control               | NONE                                                                                       |        |  |                        |
| Timeout(s)                 | 3                                                                                          |        |  |                        |
| Client Address             | 4                                                                                          |        |  |                        |
| No. of Consecutive         | 1                                                                                          |        |  |                        |
| Exit                       |                                                                                            | Back   |  | 2006/04/12<br>14:53:43 |

| Setup Items                      | Setup Description                                                                                                         |
|----------------------------------|---------------------------------------------------------------------------------------------------------------------------|
| SIO Type                         | Select the SIO type to communicate with the External Device.                                                              |
| Speed                            | Select speed between the External Device and the Display.                                                                 |
| Data Length                      | Display data length.                                                                                                      |
| Parity                           | Select how to check parity.                                                                                               |
| Stop Bit                         | Select stop bit length.                                                                                                   |
| Flow Control                     | Display the communication control method to prevent overflow of transmission and reception data.                          |
| Timeout                          | Use an integer from 1 to 127 to enter the time (s) for which the Display waits for the response from the External Device. |
| Client Address                   | Use an integer from 1 to 98 to enter the client address (source address).                                                 |
| No. of Consecutive <sup>*1</sup> | Use an integer 1 to 5 to enter the No. of consecutive address.                                                            |

<sup>\*1</sup> Set the value of "Client address + Consecutive address number - 1" to 98 or less. Address which exceeds 98 is not used because it is not polled from the master.

## ■ Device Setting

To display the setting screen, touch [Device/PLC Settings] from [Peripheral Settings]. Touch the External Device you want to set from the displayed list, and touch [Device].

| Comm.                                             | Device                                        | Option |        |                        |
|---------------------------------------------------|-----------------------------------------------|--------|--------|------------------------|
| Uni-Telway                                        |                                               |        | [COM1] | Page 1/1               |
| Device/PLC Name <input type="text" value="PLC1"/> |                                               |        |        |                        |
| Network                                           | <input type="text" value="0"/>                | ▼ ▲    |        |                        |
| Station                                           | <input type="text" value="254"/>              | ▼ ▲    |        |                        |
| Gate                                              | <input type="text" value="0"/>                | ▼ ▲    |        |                        |
| Selector                                          | <input type="text" value="0"/>                | ▼ ▲    |        |                        |
| Connection Pt./Module                             | <input type="text" value="254"/>              | ▼ ▲    |        |                        |
| Reference/Channel                                 | <input type="text" value="0"/>                | ▼ ▲    |        |                        |
| Frame Length                                      | <input type="text" value="Maximum Possible"/> |        |        |                        |
| Bit manipulation to Internal Device               |                                               |        |        |                        |
| Rest of bits in word are not cleared              |                                               |        |        |                        |
| Double Word word order Low word first             |                                               |        |        |                        |
| Exit                                              |                                               | Back   |        | 2006/04/12<br>14:53:45 |

| Setup Items                         | Setup Description                                                                                                                                                                                                                                 |
|-------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Device/PLC Name                     | Select the External Device for device setting. Device name is a title of External Device set with GP-Pro EX.(Initial value [PLC1])                                                                                                                |
| Network                             | Enter the Network No. of the destination External Device.                                                                                                                                                                                         |
| Station                             | Enter the station No. in the network.                                                                                                                                                                                                             |
| Gate                                | Enter the gate No. in the network.                                                                                                                                                                                                                |
| Selector                            | Enter the connected communication channel. This item becomes available only when the gate value is "8."                                                                                                                                           |
| Connection Pt./Module               | Enter the connection point in case of Level 6 Addressing, and enter the module number in case of Level 5 Addressing.                                                                                                                              |
| Reference/Channel                   | Enter the reference in case of Level 6 Addressing, and enter the channel in case of Level 5 Addressing.                                                                                                                                           |
| Frame Length                        | Specify the frame length.                                                                                                                                                                                                                         |
| Bit manipulation to Internal Device | From "Rest of bits in word are cleared" or "Rest of bits in word are not cleared", display treatment of the rest of the bits in the same word when the bit manipulation to Internal Device is performed. (Not available to set in off-line mode.) |
| Double Word word order              | The word order when displaying the 16-bit device in 32-bit is displayed. You cannot change the word order in [Device Setting] in off-line mode.                                                                                                   |

## ■ Option

To display the setting screen, touch [Device/PLC Settings] from [Peripheral Settings]. Touch the External Device you want to set from the displayed list, and touch [Option].

|       |        |        |  |  |
|-------|--------|--------|--|--|
| Comm. | Device | Option |  |  |
|       |        |        |  |  |

Uni-Telway [COM1] Page 1/1

RI / VCC      ☒ RI      ☐ VCC

In the case of RS232C, you can select the 9th pin to RI(Input) or VCC(5V Power Supply). If you use the Digital's RS232C Isolation Unit, please select it to VCC.

|  |      |  |      |                        |
|--|------|--|------|------------------------|
|  | Exit |  | Back | 2006/04/12<br>14:53:48 |
|--|------|--|------|------------------------|

| Setup Items | Setup Description                                                         |
|-------------|---------------------------------------------------------------------------|
| RI/VCC      | You can switch RI/VCC of the 9th pin when you select RS232C for SIO type. |

## 5 Cable Diagram

The cable diagram shown below may be different from the cable diagram recommended by Schneider Electric Industries. Please be assured there is no operational problem in applying the cable diagram shown in this manual.

- The FG pin of the main body of External Device must be D-class grounded. Please refer to the manual of External Device for more details.
- SG and FG are connected inside Display. When connecting SG to External Device, design the system not to form short-circuit loop.
- Connect the isolation unit, when communication is not stabilized under the influence of a noise etc..
- When connecting IPC with External Device by RS-232C, the COM port which can be used changes with series. Please refer to the manual of IPC for details.

Usable port

| Series                 | Usable port                                                         |
|------------------------|---------------------------------------------------------------------|
| PS-2000B               | COM1 <sup>*1</sup> , COM2, COM3 <sup>*1</sup> , COM4                |
| PS-3650A, PS-3651A     | COM1 <sup>*1</sup>                                                  |
| PS-3700A (Pentium®4-M) | COM1 <sup>*1</sup> , COM2 <sup>*1</sup> , COM3 <sup>*2</sup> , COM4 |

\*1 The RI/5V can be switched. Please switch with the change switch of IPC.

\*2 It is necessary to set up the SIO type with the Dip switch.

- When connecting to the COM3 of PS-3700A (Pentium®4-M) with External Device, it is necessary to set up the SIO type of COM3 with a Dip switch. Please refer to the manual of PS-3700A (Pentium®4-M) for details.

Dip switch setting: RS-232C

| Dip switch | Setting | Description                                      |
|------------|---------|--------------------------------------------------|
| 1          | OFF     | Reserve (always OFF)                             |
| 2          | OFF     | SIO type of COM3: RS-232C                        |
| 3          | OFF     |                                                  |
| 4          | OFF     | Output mode of TX data: Always output            |
| 5          | OFF     | Terminal resistance insertion to TX (220Ω): None |
| 6          | OFF     | Terminal resistance insertion to RX (220Ω): None |
| 7          | OFF     | Short-circuit of TXA and RXA: Does not Exist     |
| 8          | OFF     | Short-circuit of TXB and RXB: Does not Exist     |
| 9          | OFF     | Auto Detection: Disable                          |
| 10         | OFF     |                                                  |


Dip switch setting: RS-422/485 (2 wire)

| Dip switch | Setting | Description                                      |
|------------|---------|--------------------------------------------------|
| 1          | OFF     | Reserve (always OFF)                             |
| 2          | ON      | SIO type of COM3: RS-422/485                     |
| 3          | ON      |                                                  |
| 4          | OFF     | Output mode of TX data: Always output            |
| 5          | OFF     | Terminal resistance insertion to TX (220Ω): None |
| 6          | OFF     | Terminal resistance insertion to RX (220Ω): None |
| 7          | ON      | Short-circuit of TXA and RXA: Exists             |
| 8          | ON      | Short-circuit of TXB and RXB: Exists             |
| 9          | ON      | Auto Detection: Enable                           |
| 10         | ON      |                                                  |

Cable Diagram 1

| Display<br>(Connection Port) | Cable                                                         | Notes |
|------------------------------|---------------------------------------------------------------|-------|
| GP (COM1)<br>IPC*1*2         | Cable by Schneider Electric Industries<br>TSX PCX 1031 (2.5m) |       |

- \*1 Usable ports are different by the series.  
    ☞ Usable port (page 28)
- \*2 When use the COM3 of PS -3700A (Pentium®4-M) , set the SIO type of COM3 with Dip switch.  
    ☞ Dip switch setting: RS-232C (page 28)



Cable Diagram 2

| Display<br>(Connection Port)                | Cable |                                                                                                                                                           | Notes                                       |
|---------------------------------------------|-------|-----------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------|
| GP <sup>*1</sup> (COM1)<br>AGP-3302B (COM2) | A     | COM port conversion adapter by Pro-face<br>CA3-ADPCOM-01<br>+<br>Terminal block conversion adapter<br>by Pro-face<br>CA3-ADPTRM-01<br>+<br>Your own cable | The cable length<br>must be 10m or<br>less. |
|                                             | B     | Your own cable                                                                                                                                            |                                             |
| GP <sup>*2</sup> (COM2)                     | C     | Online adapter by Pro-face<br>CA4-ADPONL-01<br>+<br>Terminal block conversion adapter<br>by Pro-face<br>CA3-ADPTRM-01<br>+<br>Your own cable              |                                             |
|                                             | D     | Online adapter by Pro-face<br>CA4-ADPONL-01<br>+<br>Your own cable                                                                                        |                                             |
| IPC <sup>*3</sup> (COM3)                    | E     | COM port conversion adapter by Pro-face<br>CA3-ADPCOM-01<br>+<br>Terminal block conversion adapter<br>by Pro-face<br>CA3-ADPTRM-01<br>+<br>Your own cable |                                             |
|                                             | F     | Your own cable                                                                                                                                            |                                             |


\*1 All GP models except AGP-3302B

\*2 All GP models except GP-3200 series and AGP-3302B


\*3 Only COM3 of PS -3700A (Pentium®4-M) can be used. When use the COM3, set the SIO type of COM3 with Dip switch.

☞ Dip switch setting: RS-422/485 (2 wire) (page 29)


A) When using the COM port conversion adapter (CA3-ADPCOM-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable




B) When using your own cable




C) When using the online adapter (CA4-ADPONL-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable




D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable



E) When using the COM port conversion adapter (CA3-ADPCOM-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable



F) When using your own cable



Cable Diagram 3

| Display<br>(Connection Port)                | Cable |                                                                                                                                                           | Notes                                       |
|---------------------------------------------|-------|-----------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------|
| GP <sup>*1</sup> (COM1)<br>AGP-3302B (COM2) | A     | COM port conversion adapter by Pro-face<br>CA3-ADPCOM-01<br>+<br>Terminal block conversion adapter<br>by Pro-face<br>CA3-ADPTRM-01<br>+<br>Your own cable | The cable length<br>must be 10m or<br>less. |
|                                             | B     | Your own cable                                                                                                                                            |                                             |
| GP <sup>*2</sup> (COM2)                     | C     | Online adapter by Pro-face<br>CA4-ADPONL-01<br>+<br>Terminal block conversion adapter<br>by Pro-face<br>CA3-ADPTRM-01<br>+<br>Your own cable              |                                             |
|                                             | D     | Online adapter by Pro-face<br>CA4-ADPONL-01<br>+<br>Your own cable                                                                                        |                                             |
| IPC <sup>*3</sup> (COM3)                    | E     | COM port conversion adapter by Pro-face<br>CA3-ADPCOM-01<br>+<br>Terminal block conversion adapter<br>by Pro-face<br>CA3-ADPTRM-01<br>+<br>Your own cable |                                             |
|                                             | F     | Your own cable                                                                                                                                            |                                             |


\*1 All GP models except AGP-3302B

\*2 All GP models except GP-3200 series and AGP-3302B


\*3 Only COM3 of PS -3700A (Pentium®4-M) can be used. When use the COM3, set the SIO type of COM3 with Dip switch.

☞ Dip switch setting: RS-422/485 (2 wire) (page 29)


A) When using the COM port conversion adapter (CA3-ADPCOM-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable




B) When using your own cable




C) When using the online adapter (CA4-ADPONL-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable




D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable



E) When using the COM port conversion adapter (CA3-ADPCOM-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable



F) When using your own cable



Cable Diagram 4

| Display<br>(Connection Port)                | Cable |                                                                                                                                                                                                                                 | Notes                                                                                                                                          |
|---------------------------------------------|-------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| GP* <sup>1</sup> (COM1)<br>AGP-3302B (COM2) | A     | COM port conversion adapter by Pro-face<br>CA3-ADPCOM-01<br>+<br>Terminal block conversion adapter<br>by Pro-face<br>CA3-ADPTRM-01<br>+<br>Uni-Telway connection cable TSX SCP CU 4030 (3m)<br>by Schneider Electric Industries | The cable length<br>must be 10m or<br>less.<br>For n:1 connection,<br>you need your own<br>cable for<br>connection<br>between the<br>Displays. |
|                                             | B     | Your own cable<br>+<br>Uni-Telway cable by Schneider Electric Industries<br>TSX SCP CU 4030 (3m)                                                                                                                                |                                                                                                                                                |
| GP* <sup>2</sup> (COM2)                     | C     | Online adapter by Pro-face<br>CA4-ADPONL-01<br>+<br>Terminal block conversion adapter<br>by Pro-face<br>CA3-ADPTRM-01<br>+<br>Uni-Telway cable by Schneider Electric Industries<br>TSX SCP CU 4030 (3m)                         |                                                                                                                                                |
|                                             | D     | Online adapter by Pro-face<br>CA4-ADPONL-01<br>+<br>Your own cable<br>+<br>Uni-Telway cable by Schneider Electric Industries<br>TSX SCP CU 4030 (3m)                                                                            |                                                                                                                                                |
| IPC* <sup>3</sup> (COM3)                    | E     | COM port conversion adapter by Pro-face<br>CA3-ADPCOM-01<br>+<br>Terminal block conversion adapter<br>by Pro-face<br>CA3-ADPTRM-01<br>+<br>Uni-Telway connection cable TSX SCP CU 4030 (3m)<br>by Schneider Electric Industries |                                                                                                                                                |
|                                             | F     | Your own cable<br>+<br>Uni-Telway cable by Schneider Electric Industries<br>TSX SCP CU 4030 (3m)                                                                                                                                |                                                                                                                                                |

\*1 All GP models except AGP-3302B

\*2 All GP models except GP-3200 series and AGP-3302B


\*3 Only COM3 of PS -3700A (Pentium®4-M) can be used. When use the COM3, set the SIO type of COM3 with Dip switch.

 Dip switch setting: RS-422/485 (2 wire) (page 29)


- NOTE** • Line color for both D (A) and SG is white. As SG (red) and SG (white) are twisted pair, as well as D (A) and D (B), you can judge which line is SG or D (A).

A) When using the COM port conversion adapter (CA3-ADPCOM-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and Uni-Telway connection cable (TSX SCP CU 4030)

- 1:1 Connection




- n:1 Connection




B) When using your own cable and Uni-Telway connection cable (TSX SCP CU 4030) by Schneider Electric Industries

• 1:1 Connection




• n:1 Connection




C) When using the online adapter (CA4-ADPONL-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and Uni-Telway connection cable (TSX SCP CU 4030) by Schneider Electric Industries

- 1:1 Connection




- n:1 Connection




D) When using the online adapter (CA4-ADPONL-01) by Pro-face, your own cable and Uni-Telway connection cable (TSX SCP CU 4030) by Schneider Electric Industries

- 1:1 Connection




- n:1 Connection




E) When using the COM port conversion adapter (CA3-ADPCOM-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and Uni-Telway connection cable (TSX SCP CU 4030)

- 1:1 Connection




- n:1 Connection




F) When using your own cable and Uni-Telway connection cable (TSX SCP CU 4030) by Schneider Electric Industries

- 1:1 Connection



- n:1 Connection



Cable Diagram 5

| Display<br>(Connection Port)                | Cable |                                                                                                                                                        | Notes                                       |
|---------------------------------------------|-------|--------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------|
| GP <sup>*1</sup> (COM1)<br>AGP-3302B (COM2) | A     | COM port conversion adapter by Pro-face<br>CA3-ADPCOM-01<br>+<br>Terminal block conversion adapter by Pro-face<br>CA3-ADPTRM-01<br>+<br>Your own cable | The cable length<br>must be 10m or<br>less. |
|                                             | B     | Your own cable                                                                                                                                         |                                             |
| GP <sup>*2</sup> (COM2)                     | C     | Online adapter by Pro-face<br>CA4-ADPONL-01<br>+<br>Terminal block conversion adapter by Pro-face<br>CA3-ADPTRM-01<br>+<br>Your own cable              |                                             |
|                                             | D     | Online adapter by Pro-face<br>CA4-ADPONL-01<br>+<br>Your own cable                                                                                     |                                             |
| IPC <sup>*3</sup> (COM3)                    | E     | COM port conversion adapter by Pro-face<br>CA3-ADPCOM-01<br>+<br>Terminal block conversion adapter by Pro-face<br>CA3-ADPTRM-01<br>+<br>Your own cable |                                             |
|                                             | F     | Your own cable                                                                                                                                         |                                             |


\*1 All GP models except AGP-3302B

\*2 All GP models except GP-3200 series and AGP-3302B


\*3 Only COM3 of PS -3700A (Pentium®4-M) can be used. When use the COM3, set the SIO type of COM3 with Dip switch.

 Dip switch setting: RS-422/485 (2 wire) (page 29)


A) When using the COM port conversion adapter (CA3-ADPCOM-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable




B) When using your own cable




C) When using the online adapter (CA4-ADPONL-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable




D) When using the online adapter (CA4-ADPONL-01) by Pro-face and your own cable



E) When using the COM port conversion adapter (CA3-ADPCOM-01), the connector terminal block conversion adapter (CA3-ADPTRM-01) by Pro-face and your own cable



F) When using your own cable



## 6 Supported Device

Range of supported device address is shown in the table below. Please note that the actually supported range of the devices varies depending on the External Device to be used. Please check the actual range in the manual of your External Device.

As it also varies depending on the "Software Configuration" setting of the ladder software, please check accordingly.

### 6.1 Nano Series

 This address can be specified as system data area.

| Device               | Bit Address                 | Word Address        | 32bits                                                                                                                                                                                                                                                             | Notes                                                                                                                                                                               |
|----------------------|-----------------------------|---------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Internal Word        | %MW00000:X00 - %MW00255:X15 | %MW00000 - %MW00255 | <div style="display: flex; align-items: center;"> <div style="border: 1px solid black; padding: 2px; margin-right: 5px;">L/H</div> <div style="border: 1px solid black; padding: 2px; margin-right: 5px;">H/L</div> <div style="margin-left: 5px;">*1</div> </div> | *2<br>                                                                                           |
| Internal Double Word | %MD00000:X00 - %MD00254:X31 | %MD00000 - %MD00254 |                                                                                                                                                                                                                                                                    | *3 *4<br><br> |
| Constant Word        | ---                         | %KW00000 - %KW00063 |                                                                                                                                                                                                                                                                    | *5<br>                                                                                           |
| System Word          | ---                         | %SW00000 - %SW00127 |                                                                                                                                                                                                                                                                    |                                                                                                  |
| Internal Bit         | %M00000 - %M00127           | ---                 |                                                                                                                                                                                                                                                                    |                                                                                                                                                                                     |
| System Bit           | %S00000 - %S00127           | ---                 |                                                                                                                                                                                                                                                                    |                                                                                                                                                                                     |

\*1 High and low relationship of the stored data is specified by the [Double Word word order] setting of [Device Setting].

"4.1 Setup Items in GP-Pro EX ■ Device Setting" (page 24), "4.2 Setup Items in Off-Line Mode ■ Device Setting" (page 26)

\*2 An access method at the time of Bit Set varies depending on the [Rest of the bits in this word] setting of [Device Setting].

- Clear..... 

- Do not clear..... When you write the bit address, the Display reads the word address corresponding to that of the External Device first. Then, it changes the target bit address among the word data once read and returns the word data to the External Device. Note that the correct data may not be written if you change the word address value in the ladder program while the Display reads the data of the External Device and returns it to the External Device.

\*3 An access method at the time of Bit Set varies depending on the [Rest of the bits in this word] setting of [Device Setting].

- Clear..... 

- Do not clear..... When you write the bit address, the Display reads the word address corresponding to that of the External Device first. Then, it changes the target bit address among the word data once read and returns the word data to the External Device. Note that the correct data may not be written if you change the word address value in the ladder program while the Display reads the data of the External Device and returns it to the External Device.

\*4 Use in 32-bit specification. When you perform 16-bit or bit specification, use %MW device. They use the same area inside the External Device.

\*5 Write disable.

**NOTE**

- Please refer to the GP-Pro EX Reference Manual for system data area.  
Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
- Please refer to the precautions on manual notation for icons in the table.  
 "Manual Symbols and Terminology"

## 6.2 Micro Series

 This address can be specified as system data area.

| Device               | Bit Address                    | Word Address        | 32bits                           | Notes                                                                        |
|----------------------|--------------------------------|---------------------|----------------------------------|------------------------------------------------------------------------------|
| Internal Word        | %MW00000:X00 -<br>%MW17543:X15 | %MW00000 - %MW17543 | <div>[L/H]<br/>or [H/L] *1</div> | *2<br><div> <div>15</div> <div>Bit</div> </div>                              |
| Internal Double Word | %MD00000:X00 -<br>%MD17542:X31 | %MD00000 - %MD17542 |                                  | *3 *4<br><div> <div>2</div> <div>+</div> <div>31</div> <div>Bit</div> </div> |
| Constant Word        | ---                            | %KW00000 - %KW13879 |                                  | *5<br><div> <div>15</div> <div>Bit</div> </div>                              |
| System Word          | ---                            | %SW00000 - %SW00127 |                                  | <div> <div>15</div> <div>Bit</div> </div>                                    |
| Internal Bit         | %M00000 - %M00255              | ---                 |                                  |                                                                              |
| System Bit           | %S00000 - %S00127              | ---                 |                                  |                                                                              |

\*1 High and low relationship of the stored data is specified by the [Double Word word order] setting of [Device Setting].

"4.1 Setup Items in GP-Pro EX ■ Device Setting" (page 24), "4.2 Setup Items in Off-Line Mode ■ Device Setting" (page 26)

\*2 An access method at the time of Bit Set varies depending on the [Rest of the bits in this word] setting of [Device Setting].

- Clear..... 

15

Bit

- Do not clear..... When you write the bit address, the Display reads the word address corresponding to that of the External Device first. Then, it changes the target bit address among the word data once read and returns the word data to the External Device. Note that the correct data may not be written if you change the word address value in the ladder program while the Display reads the data of the External Device and returns it to the External Device.

\*3 An access method at the time of Bit Set varies depending on the [Rest of the bits in this word] setting of [Device Setting].

- Clear..... 

31

Bit

- Do not clear..... When you write the bit address, the Display reads the word address corresponding to that of the External Device first. Then, it changes the target bit address among the word data once read and returns the word data to the External Device. Note that the correct data may not be written if you change the word address value in the ladder program while the Display reads the data of the External Device and returns it to the External Device.

\*4 Use in 32-bit specification. When you perform 16-bit or bit specification, use %MW device. They use the same area inside the External Device.

\*5 Write disable.

**NOTE**

- Please refer to the GP-Pro EX Reference Manual for system data area.  
Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
- Please refer to the precautions on manual notation for icons in the table.  
 "Manual Symbols and Terminology"

## 6.3 Premium Series

 This address can be specified as system data area.

| Device               | Bit Address                    | Word Address        | 32bits                           | Notes                                                                                                                                                                               |
|----------------------|--------------------------------|---------------------|----------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Internal Word        | %MW00000:X00 -<br>%MW32463:X15 | %MW00000 - %MW32463 | <div>[L/H]<br/>or [H/L] *1</div> | *2<br>                                                                                           |
| Internal Double Word | %MD00000:X00 -<br>%MD32462:X31 | %MD00000 - %MD32462 |                                  | *3 *4<br><br> |
| Constant Word        | ---                            | %KW00000 - %KW32759 |                                  | *5<br>                                                                                           |
| System Word          | ---                            | %SW00000 - %SW00255 |                                  |                                                                                                  |
| Internal Bit         | %M00000 - %M32633              | ---                 |                                  |                                                                                                                                                                                     |
| System Bit           | %S00000 - %S00127              | ---                 |                                  |                                                                                                                                                                                     |

\*1 High and low relationship of the stored data is specified by the [Double Word word order] setting of [Device Setting].

"4.1 Setup Items in GP-Pro EX ■ Device Setting" (page 24), "4.2 Setup Items in Off-Line Mode ■ Device Setting" (page 26)

\*2 An access method at the time of Bit Set varies depending on the [Rest of the bits in this word] setting of [Device Setting].

- Clear..... 

- Do not clear..... When you write the bit address, the Display reads the word address corresponding to that of the External Device first. Then, it changes the target bit address among the word data once read and returns the word data to the External Device. Note that the correct data may not be written if you change the word address value in the ladder program while the Display reads the data of the External Device and returns it to the External Device.

\*3 An access method at the time of Bit Set varies depending on the [Rest of the bits in this word] setting of [Device Setting].

- Clear..... 

- Do not clear..... When you write the bit address, the Display reads the word address corresponding to that of the External Device first. Then, it changes the target bit address among the word data once read and returns the word data to the External Device. Note that the correct data may not be written if you change the word address value in the ladder program while the Display reads the data of the External Device and returns it to the External Device.

\*4 Use in 32-bit specification. When you perform 16-bit or bit specification, use %MW device. They use the same area inside the External Device.

\*5 Write disable.

**NOTE**

- Please refer to the GP-Pro EX Reference Manual for system data area.  
Cf. GP-Pro EX Reference Manual "Appendix 1.4 LS Area (only for direct access method)"
- Please refer to the precautions on manual notation for icons in the table.

 "Manual Symbols and Terminology"

## 7 Device Code and Address Code

Use device code and address code when you select "Device Type & Address" for the address type in data displays.

| Device               | Device Name | Device Code (HEX) | Address Code                       |
|----------------------|-------------|-------------------|------------------------------------|
| Internal word        | %MW         | 0000              | Word Address                       |
| Internal Double Word | %MD         | 0002              | Value of word address divided by 2 |
| Constant Word        | %KW         | 0003              | Word Address                       |
| System Word          | %SW         | 0004              | Word Address                       |

## 8 Error Messages

Error messages are displayed on the screen of Display as follows: "No. : Device Name: Error Message (Error Occurrence Area)". Each description is shown below.

| Item                  | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
|-----------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| No.                   | Error No.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| Device Name           | Name of External Device where error occurs. Name of External Device is a title of External Device set with GP-Pro EX. (Initial value [PLC1])                                                                                                                                                                                                                                                                                                                                                              |
| Error Message         | Displays messages related to the error which occurs.                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| Error Occurrence Area | <p>Displays IP address or device address of External Device where error occurs, or error codes received from External Device.</p> <div style="border: 1px solid black; padding: 2px; margin-bottom: 5px;"><b>NOTE</b></div> <ul style="list-style-type: none"> <li>• IP address is displayed such as "IP address(Decimal): MAC address( Hex)".</li> <li>• Device address is displayed such as "Address: Device address".</li> <li>• Received error codes are displayed such as "Decimal[Hex]".</li> </ul> |

Display Examples of Error Messages

"RHAA035: PLC1: Error has been responded for device write command (Error Code: 2 [02H])"

**NOTE**

- Please refer to the manual of External Device for more detail of received error codes.
- Please refer to "When an error message is displayed (Error code list)" of "Maintenance/Troubleshooting" for a common error message to the driver.

