Combining two trigger conditions

You can combine 2 trigger conditions at maximum by using "And" / "Or" when specifying the trigger condition. First, specify a trigger condition. Then click the list button of [Trigger Condition] to select [and] or [or], and specify the second trigger condition in the [Condition 2] tab.

						×
Trigger Condition Name	Trigger1					Circl Marks
Node Name	PC1		💌 📑 Add	Node		Find Node
Trigger Condition						
When Disconnected from Node PC1						
						•
AND						
UR		, U				
Specify the Trigger Condition.						
۳. ۱	When Turned ON		While Device is ON	1	While Conditio	n Satisfied
Ö	Specified Time	1	While Device is OFF		When Conditio	n Satisfied

Operation timing with the trigger conditions given below

There are 4 types of trigger conditions that you can specify by using "At Device On" and "At Device Off", and the examples of timing chart with each condition are as follows:

- [Turn OFF the Specified Symbol after Processing] is checked under "At Device On".
- [Turn ON the Specified Symbol after Processing] is checked under "At Device Off".

